

Model: Model J-C2 Fax Unit		Date: 15-Feb-06	No.: RB712001
Subject: Communication Switch 16		Prepared by: H.Taguchi	
From: 1st Tech. Support Sec. Service Support Dept.			
Classification:	<input type="checkbox"/> Troubleshooting <input type="checkbox"/> Part information <input type="checkbox"/> Action required <input type="checkbox"/> Mechanical <input type="checkbox"/> Electrical <input checked="" type="checkbox"/> Service manual revision <input type="checkbox"/> Paper path <input type="checkbox"/> Transmit/receive <input type="checkbox"/> Retrofit information <input type="checkbox"/> Product Safety <input type="checkbox"/> Other ()		

The Service Manual (Fax) was corrected as follows:

- **Replace** the description for “Communication Switch 16” with the following (section 4.2.4):

Communication Switch 16 023		SP No. 1-104-
No	FUNCTION	COMMENTS
0	Not used	Do not change the settings.
1	Optional G3 unit (G3-2) 0: Not installed 1: Installed	Change this bit to 1 when installing the first optional G3 unit.
2	Not used	
3	Select PSTN Connection 0: Off 1: On	This switch enables the G3-2. 0: Off, no connection 1: Recognizes and enables G3-2. This switch can be used only after G3-2 has been installed.
4-7	Not used	Do not change the settings.

Model: Model J-C2 Fax Unit		Date: 19-Jun-07	No.: RB712002
Subject: User Parameter Switch 34		Prepared by: K. Moriizumi	
From: 1st Tech. Support Sec. Service Support Dept.			
Classification:	<input type="checkbox"/> Troubleshooting <input type="checkbox"/> Mechanical <input type="checkbox"/> Paper path <input type="checkbox"/> Product Safety	<input type="checkbox"/> Part information <input type="checkbox"/> Electrical <input type="checkbox"/> Transmit/receive <input type="checkbox"/> Other ()	<input type="checkbox"/> Action required <input checked="" type="checkbox"/> Service manual revision <input type="checkbox"/> Retrofit information

The Service Manual (Fax) was corrected as follows:

- **Correct** the description for “User Parameter Switch 34”.
(section 4.5 page 4-77):

Incorrect:

6800F2(H) - User parameter switch 34 (SWUSR_22)

Bit 0: SIP server used with IP-Fax 0: Disabled, 1: Enabled

Bit 1: Gatekeeper server used with IP-Fax 0: Disabled, 1: Enabled

Correct:

6800F2(H) - User parameter switch 34 (SWUSR_22)

Bit 0: Gatekeeper server used with IP-Fax 0: Disabled, 1: Enabled

Bit 1: SIP server used with IP-Fax 0: Disabled, 1: Enabled