# Fax Option Type C1500 Machine Code: B267

# **SERVICE MANUAL**

Feb. 28th, 2006 Subject to change Read This First 28-Feb-06

# **Read This First**

### Important Safety Notices

#### **MARNING**

- Never install telephone wiring during a lightning storm.
- Never install telephone jacks in wet locations unless the jack is specifically designed for wet locations.
- Never touch uninsulated telephone wires or terminals unless the telephone line has been disconnected at the network interface.
- Use caution when installing or modifying telephone lines.
- Avoid using a telephone (other than a cordless type) during an electrical storm.
   There may be remote risk of electric shock from lightning.
- Do not use a telephone or cellular phone to report a gas leak in the vicinity of the leak.

### **CAUTION**

- Before installing the fax unit, switch off the main switch, and disconnect the power cord.
- The fax unit contains a lithium battery. The danger of explosion exists if a battery of this type is incorrectly replaced. Replace only with the same or an equivalent type recommended by the manufacturer. Discard batteries in accordance with the manufacturer's instructions and local regulations.




- Note for Australia:
- Unit must be connected to Telecommunication Network through a line cord which meets the requirements of ACA Technical Standard TS008.

# Symbols and Abbreviations

#### Conventions Used in this Manual

This manual uses several symbols.

Symbol	What it means	
•	Refer to section number	
F	Screw	
	Connector	
C	E-ring	
ℴℴ	Clip ring	
Ţ	Clamp	



#### Cautions, Notes, etc.

The following headings provide special information:

### **<b>∴**WARNING

Failure to obey warning information could result in serious injury or death.

### CAUTION

Obey these guidelines to ensure safe operation and prevent minor injuries.

#### mportant 🖈

- Obey these guidelines to avoid problems such as misfeeds, damage to originals, loss of valuable data and to prevent damage to the machine.
- Always obey these guidelines to avoid serious problems such as misfeeds, damage to originals, loss of valuable data and to prevent damage to the machine. bold is added for emphasis.



This information provides tips and advice about how to best service the machine.

# Table of Contents

Read This First	i
Important Safety Notices	i
Symbols and Abbreviations	ii
Conventions Used in this Manual	ii
Cautions, Notes, etc.	ii
Table of Contents	iii
Installation	1
Fax Unit (B267)	1
Accessory Check	1
Installation Procedure	2
Fax Unit Options	8
Handset (B433)	8
Replacement and Adjustment	9
FCU	9
Troubleshooting	10
Error Codes	10
IFAX Troubleshooting	30
IP-Fax Troubleshooting	33
IP-Fax Transmission	33
IP-Fax Reception	36
Service Tables	40
Beforehand	40
Service Tables	41
SP1-XXX (Bit Switches)	41
SP2-XXX (RAM Data)	42
SP3-XXX (Tel Line Settings)	43
SP4-XXX (ROM Versions)	45
SP5-XXX (Initializing)	46
SP6-XXX (Reports)	46
SP7-XXX (Test Modes)	49
SP9-XXX (Design Switch Mode)	51
Bit Switches	52
System Switches	52
I-Fax Switches	64

Printer Switches	71
Communication Switches	77
G3 Switches	84
IP Fax Switches	93
NCU Parameters	101
Dedicated Transmission Parameters	117
Programming Procedure	117
Parameters	117
Service RAM Addresses	125
Detailed Section Descriptions	135
Overview	135
Boards	136
FCU	136
MBU	137
Video Data Path	138
Transmission	138
Reception	140
Fax Communication Features	141
Internet Mail Communication	141
IP-Fax	150
What is IP-FAX?	150
Specifications	151
General Specifications	151
IFAX Specifications	153
IP-FAX Specifications	155
Fax Unit Configuration	156

# Installation

# Fax Unit (B267)


# Accessory Check

No.	Description	Q'ty
1	Fax Unit	1
2	Fax Operation Panel	1
3	Ferrite Core	EU: 1, NA: 2
4	Module Cable (NA only)	1
5	Tel Cap (NA only)	1
6	Handset Bracket (NA only)	1
7	Serial Number Decal	1
8	G3 Decal	1
9	FCC Decal (NA only)	1


#### Installation Procedure

### **<b> ▲**CAUTION


- Before installing the fax option:
  - 1. Print out all data in the printer buffer (if the printer option is installed).
  - 2. Turn the main switch off and disconnect the power cord and the network cable.



- 1. Unplug the DF cable [A] (if installed).
- 2. Remove the rear cover [B] ( x 4).




3. Remove the interface cover [C] ( x 2).



4. Switch the jumper switch [D] on the MBU [E] to "ON" position.




• The jumper switch works as the battery switch.



- 5. Remove the slot cover [F] ( x 3).
- 6. Install the Fax unit [G] ( x 3).




- Before installing the Fax unit, push the MBU and confirm that the MBU is properly connected to the FCU.
- 7. Install the Tel cap [H] in the "TEL" jack if the optional handset or external telephone is not installed.



8. Attach the ferrite core [I] to the telephone cable [J]. The length [K] must be about 10 cm (4").



 Attach the ferrite core to the handset cable also if the handset is installed to the copier. In case of attaching to the handset cable, the length [K] must be about 4 cm (1.6").



- 9. Reassemble the interface cover ( x 2) and rear cover ( x 4).
- 10. Connect the telephone cable [L] to the "LINE" jack as shown.




 Connect the handset cable [M] to the "TEL" jack as shown if the handset is installed.



11. Remove the dummy cover [N] from the operation panel.




12. Install the fax operation panel [O] on the operation panel as shown.





Slide the fax panel to the right pressing down the right edge of the fax operation panel. Make sure that the connection between the fax operation panel and the operation panel of the copier is firmly stable.



13. Attach the super G3 decal [P] to the front door as shown.



- 14. Attach the FCC decal to the right side [Q] of the rear cover if you do this procedure on the NA model. Go to the next step if you do not have the NA model.
- 15. Attach the serial number label to right side [Q] of the rear cover.
- 16. Plug in the machine and turn on the main switch.



- The copier must be connected to a properly-grounded socket outlet.
- 17. Make sure that the clock (date and time) is set.
- 18. Enter the SP mode and program the serial number into the fax unit with SP 3102. The serial number can be found on the serial number label (attached to the machine in step 15).
- 19. When you press the Fax key for the first time after installation, the error "SRAM problem occurred / SRAM was formatted" will show on the LCD for initializing the program of the fax unit. Turn the main power switch off/on to clear the error display.



• If another error occurs after initialization, this can be a functional problem.

#### Initial Setting

Set the country code with "BIT SW" in the "Fax SP".


Set the service station number with "Machine Set" in the "Fax SP".

# Fax Unit Options

#### Handset (B433)



The optional handset is available for the U.S. version only.



- 1. Make two holes [A] in the scanner left cover.
- 2. Attach the bracket [B] enclosed with the fax unit (F x 2) as shown.
- 3. Remove the label [C] from the handset cradle [D]. Attach the cradle [D] to the bracket [B] ( x 2), and then replace the label [C].
- 4. Install the handset [E] on the cradle [D].
- 5. Attach the ferrite core to the cable. (see step 8 in the fax unit installation procedure)
- 6. Connect the cable [F] to the "TEL" jack at the rear of the machine.

# Replacement and Adjustment

#### **FCU**

- 1. When you replace the FCU board, remove the MBU board from the old FCU board and install it on the new FCU board.
- 2. Set the correct date and time with the User Tools: User Tools> System Settings> Timer Setting> Set Date/Time



- Do not turn off the battery switch (SW1).
- Do SP6101 to print the system parameters, and check the settings.

# Troubleshooting

### **Error Codes**

If an error code occurs, retry the communication. If the same problem occurs, try to fix the problem as suggested below. Note that some error codes appear only in the error code display and on the service report.

Code	Meaning	Suggested Cause/Action
0-00	DIS/NSF not detected within 40 s of Start being pressed	<ul> <li>Check the line connection.</li> <li>The machine at the other end may be incompatible.</li> <li>Replace the NCU or FCU.</li> <li>Check for DIS/NSF with an oscilloscope.</li> <li>If the rx signal is weak, there may be a bad line.</li> </ul>
0-01	DCN received unexpectedly	<ul> <li>The other party is out of paper or has a jammed printer.</li> <li>The other party pressed Stop during communication.</li> </ul>
0-03	Incompatible modem at the other end	The other terminal is incompatible.
0-04	CFR or FTT not received after modem training	<ul> <li>Check the line connection.</li> <li>Try changing the tx level and/or cable equalizer settings.</li> <li>Replace the FCU.</li> <li>The other terminal may be faulty; try sending to another machine.</li> <li>If the rx signal is weak or defective, there may be a bad line.</li> <li>Cross reference:</li> <li>Tx level - NCU Parameter 01 (PSTN)</li> <li>Cable equalizer - G3 Switch 07 (PSTN)</li> </ul>

Code	Meaning	Suggested Cause/Action
		Dedicated Tx parameters in Service Program  Mode
0-05	Modem training fails even G3 shifts down to 2400 bps.	<ul> <li>Check the line connection.</li> <li>Try adjusting the tx level and/or cable equalizer.</li> <li>Replace the FCU.</li> <li>Check for line problems.</li> <li>Cross reference:</li> <li>See error code 0-04.</li> </ul>
0-06	The other terminal did not reply to DCS	<ul> <li>Check the line connection.</li> <li>Try adjusting the tx level and/or cable equalizer settings.</li> <li>Replace the NCU or FCU.</li> <li>The other end may be defective or incompatible; try sending to another machine.</li> <li>Check for line problems.</li> <li>Cross reference:</li> <li>See error code 0-04.</li> </ul>
0-07	No post-message response from the other end after a page was sent	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>The other end may have jammed or run out of paper.</li> <li>The other end user may have disconnected the call.</li> <li>Check for a bad line.</li> <li>The other end may be defective; try sending to another machine.</li> </ul>
0-08	The other end sent RTN or PIN after receiving a page, because there were too many errors	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>The other end may have jammed, or run out of paper or memory space.</li> <li>Try adjusting the tx level and/or cable</li> </ul>

Code	Meaning	Suggested Cause/Action
		<ul> <li>equalizer settings.</li> <li>The other end may have a defective modem/NCU/FCU; try sending to another machine.</li> <li>Check for line problems and noise.</li> <li>Cross reference:</li> <li>Tx level - NCU Parameter 01 (PSTN)</li> <li>Cable equalizer - G3 Switch 07 (PSTN)</li> <li>Dedicated Tx parameters in Service Program Mode</li> </ul>
0-14	Non-standard post message response code received	<ul> <li>Incompatible or defective remote terminal; try sending to another machine.</li> <li>Noisy line: resend.</li> <li>Try adjusting the tx level and/or cable equalizer settings.</li> <li>Replace the NCU or FCU.</li> <li>Cross reference:</li> <li>See error code 0-08.</li> </ul>
0-15	The other terminal is not capable of specific functions.	The other terminal is not capable of accepting the following functions, or the other terminal's memory is full.  Confidential rx Transfer function SEP/SUB/PWD/SID
0-16	CFR or FTT not detected after modem training in confidential or transfer mode	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>Try adjusting the tx level and/or cable equalizer settings.</li> <li>The other end may have disconnected, or it may be defective; try calling another machine.</li> <li>If the rx signal level is too low, there may be a line problem.</li> </ul>

Code	Meaning	Suggested Cause/Action
		Cross reference: See error code 0-08.
0-20	Facsimile data not received within 6 s of retraining	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>Check for line problems.</li> <li>Try calling another fax machine.</li> <li>Try adjusting the reconstruction time for the first line and/or rx cable equalizer setting.</li> <li>Cross reference:</li> <li>Reconstruction time - G3 Switch 0A, bit 6</li> <li>Rx cable equalizer - G3 Switch 07 (PSTN)</li> </ul>
0-21	EOL signal (end-of-line) from the other end not received within 5 s of the previous EOL signal	<ul> <li>Check the connections between the FCU, NCU, &amp; line.</li> <li>Check for line noise or other line problems.</li> <li>Replace the NCU or FCU.</li> <li>The remote machine may be defective or may have disconnected.</li> <li>Cross reference:</li> <li>Maximum interval between EOLs and between ECM frames - G3 Bit Switch 0A, bit 4</li> </ul>
0-22	The signal from the other end was interrupted for more than the acceptable modem carrier drop time (default: 200 ms)	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>Defective remote terminal.</li> <li>Check for line noise or other line problems.</li> <li>Try adjusting the acceptable modem carrier drop time.</li> <li>Cross reference:         <ul> <li>Acceptable modem carrier drop time - G3 Switch 0A, bits 0 and 1</li> </ul> </li> </ul>
0-23	Too many errors during reception	<ul> <li>Check the line connection.</li> <li>Replace the NCU or FCU.</li> <li>Defective remote terminal.</li> </ul>

Code	Meaning	Suggested Cause/Action
		<ul> <li>Check for line noise or other line problems.</li> <li>Try asking the other end to adjust their tx level.</li> <li>Try adjusting the rx cable equalizer setting and/or rx error criteria.</li> <li>Cross reference:</li> <li>Rx cable equalizer - G3 Switch 07 (PSTN)</li> <li>Rx error criteria - Communication Switch 02, bits 0 and 1</li> </ul>
0-30	The other terminal did not reply to NSS(A) in Al short protocol mode	<ul> <li>Check the line connection.</li> <li>Try adjusting the tx level and/or cable equalizer settings.</li> <li>The other terminal may not be compatible.</li> <li>Cross reference:</li> <li>Dedicated tx parameters - Section 4</li> </ul>
0-32	The other terminal sent a DCS, which contained functions that the receiving machine cannot handle.	<ul> <li>Check the protocol dump list.</li> <li>Ask the other party to contact the manufacturer.</li> </ul>
0-33	The data reception (not ECM) is not completed within 10 minutes.	<ul> <li>Check the line connection.</li> <li>The other terminal may have a defective modem/NCU/FCU.</li> </ul>
0-52	Polarity changed during communication	Check the line connection.  Retry communication.
0-55	FCU does not detect the SG3.	<ul><li>FCU firmware or board defective.</li><li>SG3 firmware or board defective.</li></ul>
0-56	The stored message data exceeds the capacity of the mailbox in the SG3.	SG3 firmware or board defective.
0-70	The communication mode specified in CM/JM was	The other terminal did not have a compatible communication mode (e.g., the other terminal

Code	Meaning	Suggested Cause/Action
	not available (V.8 calling and called terminal)	was a V.34 data modem and not a fax modem.)  • A polling tx file was not ready at the other terminal when polling rx was initiated from the calling terminal.
0-74	The calling terminal fell back to T.30 mode, because it could not detect ANSam after sending CI.	<ul> <li>The calling terminal could not detect ANSam due to noise, etc.</li> <li>ANSam was too short to detect.</li> <li>Check the line connection and condition.</li> <li>Try making a call to another V.8/V.34 fax.</li> </ul>
0-75	The called terminal fell back to T.30 mode, because it could not detect a CM in response to ANSam (ANSam timeout).	<ul> <li>The terminal could not detect ANSam.</li> <li>Check the line connection and condition.</li> <li>Try receiving a call from another V.8/V.34 fax.</li> </ul>
0-76	The calling terminal fell back to T.30 mode, because it could not detect a JM in response to CM (CM timeout).	<ul> <li>The called terminal could not detect a CM due to noise, etc.</li> <li>Check the line connection and condition.</li> <li>Try making a call to another V.8/V.34 fax.</li> </ul>
0-77	The called terminal fell back to T.30 mode, because it could not detect a CJ in response to JM (JM timeout).	<ul> <li>The calling terminal could not detect a JM due to noise, etc.</li> <li>A network that has narrow bandwidth cannot pass JM to the other end.</li> <li>Check the line connection and condition.</li> <li>Try receiving a call from another V.8/V.34 fax.</li> </ul>
0-79	The called terminal detected CI while waiting for a V.21 signal.	<ul> <li>Check for line noise or other line problems.</li> <li>If this error occurs, the called terminal falls back to T.30 mode.</li> </ul>
0-80	The line was disconnected due to a timeout in V.34	<ul> <li>The guard timer expired while starting these phases. Serious noise, narrow bandwidth, or</li> </ul>

Code	Meaning	Suggested Cause/Action
0-81	phase 2 – line probing.  The line was disconnected due to a timeout in V.34 phase 3 – equalizer training.  The line was disconnected due to a timeout in the V.34 phase 4 – control channel	low signal level can cause these errors.  If these errors happen at the transmitting terminal:  Try making a call at a later time.  Try using V.17 or a slower modem using dedicated tx parameters.  Try increasing the tx level.  Try adjusting the tx cable equalizer setting.  If these errors happen at the receiving terminal:  Try adjusting the rx cable equalizer setting.
0-83	start-up.  The line was disconnected due to a timeout in the V.34 control channel restart sequence.	<ul> <li>Try increasing the tx level.</li> <li>Try using V.17 or a slower modem if the same error is frequent when receiving from multiple senders.</li> </ul>
0-84	The line was disconnected due to abnormal signaling in V.34 phase 4 – control channel start-up.	<ul> <li>The signal did not stop within 10 s.</li> <li>Turn off the machine, then turn it back on.</li> <li>If the same error is frequent, replace the FCU.</li> </ul>
0-85	The line was disconnected due to abnormal signaling in V.34 control channel restart.	<ul> <li>The signal did not stop within 10 s.</li> <li>Turn off the machine, then turn it back on.</li> <li>If the same error is frequent, replace the FCU.</li> </ul>
0-86	The line was disconnected because the other terminal requested a data rate using MPh that was not available in the currently selected symbol rate.	<ul> <li>The other terminal was incompatible.</li> <li>Ask the other party to contact the manufacturer.</li> </ul>
0-87	The control channel started after an unsuccessful primary channel.	The receiving terminal restarted the control channel because data reception in the primary channel was not successful.

Code	Meaning	Suggested Cause/Action
		This does not result in an error communication.
0-88	The line was disconnected because PPR was transmitted/received 9 (default) times within the same ECM frame.	<ul> <li>Try using a lower data rate at the start.</li> <li>Try adjusting the cable equalizer setting.</li> </ul>
2-11	Only one V.21 connection flag was received	Replace the FCU.
2-12	Modem clock irregularity	Replace the FCU.
2-13	Modem initialization error	<ul> <li>Turn off the machine, then turn it back on.</li> <li>Update the modem ROM.</li> <li>Replace the FCU.</li> </ul>
2-23	JBIG compression or reconstruction error	Turn off the machine, then turn it back on.
2-24	JBIG ASIC error	Turn off the machine, then turn it back on.
2-25	JBIG data reconstruction error (BIH error)	
2-26	JBIG data reconstruction error (Float marker error)	<ul><li>JBIG data error</li><li>Check the sender's JBIG function.</li></ul>
2-27	JBIG data reconstruction error (End marker error)	<ul> <li>Update the MBU ROM.</li> </ul>
2-28	JBIG data reconstruction error (Timeout)	
2-29	JBIG trailing edge maker error	<ul><li>FCU defective</li><li>Check the destination device.</li></ul>
2-50	The machine resets itself for a fatal FCU system	If this is frequent, update the ROM, or replace the FCU.

Code	Meaning	Suggested Cause/Action
	error	
2-51	The machine resets itself because of a fatal communication error	If this is frequent, update the ROM, or replace the FCU.
2-53	Snd msg() in the manual task is an error because the mailbox for the operation task is full.	The user did the same operation many times, and this gave too much load to the machine.
4-01	Line current was cut	<ul> <li>Check the line connector.</li> <li>Check for line problems.</li> <li>Replace the FCU or the NCU.</li> </ul>
4-10	Communication failed because of an ID Code mismatch (Closed Network) or Tel. No./CSI mismatch (Protection against Wrong Connections)	<ul> <li>Get the ID Codes the same and/or the CSIs programmed correctly, then resend.</li> <li>The machine at the other end may be defective.</li> </ul>
5-10	DCR timer expired	Replace the FCU.
5-20	Storage impossible because of a lack of memory	<ul><li>Temporary memory shortage.</li><li>Test the SAF memory.</li></ul>
5-21	Memory overflow	
5-23	Print data error when printing a substitute rx or confidential rx message	<ul><li>Test the SAF memory.</li><li>Ask the other end to resend the message.</li></ul>
5-25	SAF file access error	<ul><li>Replace an SD card or HDD.</li><li>Replace the FCU.</li></ul>
6-00	G3 ECM - T1 time out	Try adjusting the rx cable equalizer.

Code	Meaning	Suggested Cause/Action
	during reception of facsimile data	
6-01	G3 ECM - no V.21 signal was received	Replace the FCU.
6-02	G3 ECM - EOR was received	
6-04	G3 ECM - RTC not detected	<ul> <li>Check the line connection.</li> <li>Check for a bad line or defective remote terminal.</li> <li>Replace the FCU.</li> </ul>
6-05	G3 ECM - facsimile data frame not received within 18 s of CFR, but there was no line fail	<ul> <li>Check the line connection.</li> <li>Check for a bad line or defective remote terminal.</li> <li>Replace the FCU.</li> <li>Try adjusting the rx cable equalizer</li> <li>Cross reference:</li> <li>Rx cable equalizer - G3 Switch 07 (PSTN)</li> </ul>
6-06	G3 ECM - coding/decoding error	<ul><li>Defective FCU.</li><li>The other terminal may be defective.</li></ul>
6-08	G3 ECM - PIP/PIN received in reply to PPS.NULL	<ul> <li>The other end pressed Stop during communication.</li> <li>The other terminal may be defective.</li> </ul>
6-09	G3 ECM - ERR received	<ul> <li>Check for a noisy line.</li> <li>Adjust the tx levels of the communicating machines.</li> <li>See code 6-05.</li> </ul>
6-10	G3 ECM - error frames still received at the other end after all communication attempts at 2400 bps	<ul> <li>Check for line noise.</li> <li>Adjust the tx level (use NCU parameter 01 or the dedicated tx parameter for that address).</li> <li>Check the line connection.</li> </ul>

Code	Meaning	Suggested Cause/Action
		Defective remote terminal.
6-21	V.21 flag detected during high speed modem communication	The other terminal may be defective or incompatible.
6-22	The machine resets the sequence because of an abnormal handshake in the V.34 control channel	<ul> <li>Check for line noise.</li> <li>If the same error occurs frequently, replace the FCU.</li> <li>Defective remote terminal.</li> </ul>
6-99	V.21 signal not stopped within 6 s	Replace the FCU.
13-17	SIP user name registration error	<ul> <li>Double registration of the SIP user name.</li> <li>Capacity for user-name registration in the SIP server is not sufficient.</li> </ul>
13-18	SIP server access error	<ul><li>Incorrect initial setting for the SIP server.</li><li>Defective SIP server.</li></ul>
14-00	SMTP Send Error	<ul> <li>Error occurred during sending to the SMTP server. Occurs for any error other than 14-01 to 16. For example, the mail address of the system administrator is not registered.</li> </ul>
14-01	SMTP Connection Failed	<ul> <li>Failed to connect to the SMTP server (timeout) because the server could not be found.</li> <li>The PC is not ready to transfer files.</li> <li>SMTP server not functioning correctly.</li> <li>The DNS IP address is not registered.</li> <li>Network not operating correctly.</li> <li>Destination folder selection not correct.</li> </ul>
14-02	No Service by SMTP Service (421)	<ul> <li>SMTP server operating incorrectly, or the destination for direct SMTP sending is not correct.</li> <li>Contact the system administrator and check</li> </ul>

Code	Meaning	Suggested Cause/Action
		that the SMTP server has the correct settings and operates correctly.  Contact the system administrator for direct SMTP sending and check the sending destination.
14-03	Access to SMTP Server Denied (450)	<ul> <li>Failed to access the SMTP server because the access is denied.</li> <li>SMTP server operating incorrectly. Contact the system administrator to determine if there is a problem with the SMTP server and to check that the SMTP server settings are correct.</li> <li>Folder send destination is incorrect. Contact the system administrator to determine that the SMTP server settings and path to the server are correct.</li> <li>Device settings incorrect. Confirm that the user name and password settings are correct.</li> <li>Direct SMTP destination incorrect. Contact the system administrator to determine if there is a problem at the destination at that the settings at the destination are correct.</li> </ul>
14-04	Access to SMTP Server Denied (550)	<ul> <li>SMTP server operating incorrectly</li> <li>Direct SMTP sending not operating correctly</li> </ul>
14-05	SMTP Server HDD Full (452)	<ul> <li>Failed to access the SMTP server because the HDD on the server is full.</li> <li>Insufficient free space on the HDD of the SMTP server. Contact the system administrator and check the amount of space remaining on the SMTP server HDD.</li> <li>Insufficient free space on the HDD where the destination folder is located. Contact the</li> </ul>

Code	Meaning	Suggested Cause/Action
		system administrator and check the amount of space remaining on the HDD where the target folder is located.  Insufficient free space on the HDD at the target destination for SMTP direct sending. Contact the system administrator and check the amount of space remaining on the target HDD.
14-06	User Not Found on SMTP Server (551)	<ul> <li>The designated user does not exist.</li> <li>The designated user does not exist on the SMTP server.</li> <li>The designated address is not for use with direct SMTP sending.</li> </ul>
14-07	Data Send to SMTP Server Failed (4XX)	<ul> <li>Failed to access the SMTP server because the transmission failed.</li> <li>PC not operating correctly.</li> <li>SMTP server operating incorrectly</li> <li>Network not operating correctly.</li> <li>Destination folder setting incorrect.</li> <li>Direct SMTP sending not operating correctly.</li> </ul>
14-08	Data Send to SMTP Server Failed (5XX)	<ul> <li>Failed to access the SMTP server because the transmission failed.</li> <li>SMTP server operating incorrectly</li> <li>Destination folder setting incorrect.</li> <li>Direct SMTP sending not operating correctly.</li> <li>Software application error.</li> </ul>
14-09	Authorization Failed for Sending to SMTP Server	<ul> <li>POP-Before-SMTP or SMTP authorization failed.</li> <li>Incorrect setting for file transfer</li> </ul>
14-10	Addresses Exceeded	<ul> <li>Number of broadcast addresses exceeded the limit for the SMTP server.</li> </ul>

Code	Meaning	Suggested Cause/Action
14-11	Buffer Full	The send buffer is full so the transmission could not be completed. Buffer is full due to using Scan-to-Email while the buffer is being used send mail at the same time.
14-12	Data Size Too Large	<ul> <li>Transmission was cancelled because the detected size of the file was too large.</li> </ul>
14-13	Send Cancelled	<ul> <li>Processing is interrupted because the user pressed Stop.</li> </ul>
14-14	Security Locked File Error	<ul> <li>Update the software because of the defective software.</li> </ul>
14-15	Mail Data Error	<ul> <li>The transmitting a mail is interrupted via DCS due to the incorrect data.</li> <li>Update the software because of the defective software.</li> </ul>
14-16	Maximum Division Number Error	<ul> <li>When a mail is divided for the mail transmission and the division number of a mail are more than the specified number, the mail transmission is interrupted.</li> <li>Update the software because of the defective software.</li> </ul>
14-17	Incorrect Ticket	<ul> <li>Update the software because of the defective software.</li> </ul>
14-18	Access to MCS File Error	<ul> <li>The access to MCS file is denied due to the no permission of access.</li> <li>Update the software because of the defective software.</li> </ul>
14-30	MCS File Creation Failed	Failed to create the MCS file because:  The number of files created with other applications on the Document Server has exceeded the limit.

Code	Meaning	Suggested Cause/Action
		<ul><li>HDD is full or not operating correctly.</li><li>Software error.</li></ul>
14-31	UFS File Creation Failed	<ul> <li>UFS file could not be created:</li> <li>Not enough space in UFS area to handle both Scan-to-Email and IFAX transmission.</li> <li>HDD full or not operating correctly.</li> <li>Software error.</li> </ul>
14-32	Cancelled the Mail Due to Error Detected by NFAX	Error detected with NFAX and send was cancelled due to a software error.
14-33	No Mail Address For the Machine	<ul> <li>Neither the mail address of the machine nor the mail address of the network administrator is registered.</li> </ul>
14-34	Address designated in the domain for SMTP sending does not exist	<ul> <li>Operational error in normal mail sending or direct SMTP sending.</li> <li>Check the address selected in the address book for SMTP sending.</li> <li>Check the domain selection.</li> </ul>
14-50	Mail Job Task Error	Due to an FCU mail job task error, the send was cancelled:  Address book was being edited during creation of the notification mail.  Software error.
14-51	UCS Destination Download Error	Not even one return notification can be downloaded:  The address book was being edited.  The number for the specified destination does not exist (it was deleted or edited after the job was created).
14-60	Send Cancel Failed	The cancel operation by the user failed to cancel the send operation.

Code	Meaning	Suggested Cause/Action
14-61	Notification Mail Send Failed for All Destinations	<ul> <li>All addresses for return notification mail failed.</li> </ul>
14-62	Transmission Error due to the existence of zero line page	<ul> <li>When the 0 line page exists in received pages with G3 communication, the transmission is interrupted.</li> </ul>
15-01	POP3/IMAP4 Server Not Registered	<ul> <li>At startup, the system detected that the IP address of the POP3/IMAP4 server has not been registered in the machine.</li> </ul>
15-02	POP3/IMAP4 Mail Account Information Not Registered	<ul> <li>The POP3/IMAP4 mail account has not been registered.</li> </ul>
15-03	Mail Address Not Registered	The mail address has not been registered.
15-10	DCS Mail Receive Error	■ Error other than 15-11 to 15-18.
15-11	Connection Error	The DNS or POP3/IMAP4 server could not be found:  The IP address for DNS or POP3/IMAP4 server is not stored in the machine.  The DNS IP address is not registered.  Network not operating correctly.
15-12	Authorization Error	POP3/IMAP4 send authorization failed:  Incorrect IFAX user name or password.  Access was attempted by another device, such as the PC.  POP3/IMAP4 settings incorrect.
15-13	Receive Buffer Full	<ul> <li>Occurs only during manual reception.         Transmission cannot be received due to insufficient buffer space. The buffer is being used for mail send or Scan-to-Email.     </li> </ul>
15-14	Mail Header Format Error	The mail header is not standard format. For

Code	Meaning	Suggested Cause/Action
		example, the Date line description is incorrect.
15-15	Mail Divide Error	The e-mail is not in standard format. There is no boundary between parts of the e-mail, including the header.
15-16	Mail Size Receive Error	The mail cannot be received because it is too large.
15-17	Receive Timeout	May occur during manual receiving only because the network is not operating correctly.
15-18	Incomplete Mail Received	Only one portion of the mail was received.
15-31	Final Destination for Transfer Request Reception Format Error	The format of the final destination for the transfer request was incorrect.
15-39	Send/Delivery Destination Error	The transmission cannot be delivered to the final destination:  Destination file format is incorrect.  Could not create the destination for the file transmission.
15-41	SMTP Receive Error	<ul> <li>Reception rejected because the transaction exceeded the limit for the "Auth. E-mail RX" setting.</li> </ul>
15-42	Off Ramp Gateway Error	The delivery destination address was specified with Off Ramp Gateway OFF.
15-43	Address Format Error	<ul> <li>Format error in the address of the Off Ramp Gateway.</li> </ul>
15-44	Addresses Over	The number of addresses for the Off Ramp Gateway exceeded the limit of 30.
15-61	Attachment File Format Error	■ The attached file is not TIFF format.

Code	Meaning	Suggested Cause/Action
15-62	TIFF File Compatibility Error	Could not receive transmission due to:  Resolution error  Image of resolution greater than 200 dpi without extended memory.  Resolution is not supported.  Page size error  The page size was larger than A3.  Compression error  File was compressed with other than MH, MR, or MMR.
15-63	TIFF Parameter Error	The TIFF file sent as the attachment could not be received because the TIFF header is incorrect:  The TIFF file attachment is a type not supported.  The TIFF file attachment is corrupted.  Software error.
15-64	TIFF Decompression Error	The file received as an attachment caused the TIFF decompression error:  The TIFF format of the attachment is corrupted.  Software error.
15-71	Not Binary Image Data	The file could not be received because the attachment was not binary image data.
15-73	MDN Status Error	Could not find the Disposition line in the header of the Return Receipt, or there is a problem with the firmware.
15-74	MDN Message ID Error	<ul> <li>Could not find the Original Message ID line in the header of the Return Receipt, or there is a problem with the firmware.</li> </ul>
15-80	Mail Job Task Read Error	Could not receive the transmission because the destination buffer is full and the destination

Code	Meaning	Suggested Cause/Action
		could not be created (this error may occur when receiving a transfer request or a request for notification of reception).
15-81	Repeated Destination Registration Error	Could not repeat receive the transmission because the destination buffer is full and the destination could not be created (this error may occur when receiving a transfer request or a request for notification of reception).
15-91	Send Registration Error	Could not receive the file for transfer to the final destination:  The format of the final destination or the transfer destination is incorrect.  Destinations are full so the final and transfer destinations could not be created.
15-92	Memory Overflow	Transmission could not be received because memory overflowed during the transaction.
15-93	Memory Access Error	Transaction could not complete due to a malfunction of SAF memory.
15-94	Incorrect ID Code	The machine rejected an incoming e-mail for transfer request, because the ID code in the incoming e-mail did not match the ID code registered in the machine.
15-95	Transfer Station Function	The machine rejected an incoming e-mail for transfer because the transfer function was unavailable.
22-00	Original length exceeded the maximum scan length	<ul> <li>Divide the original into more than one page.</li> <li>Check the resolution used for scanning. Lower the scan resolution if possible.</li> <li>Add optional page memory.</li> </ul>
22-01	Memory overflow while	Wait for the files in the queue to be sent.

Code	Meaning	Suggested Cause/Action
	receiving	<ul> <li>Delete unnecessary files from memory.</li> <li>Transfer the substitute reception files to an another fax machine, if the machine's printer is busy or out of order.</li> <li>Add an optional SAF memory card or hard disk.</li> </ul>
22-02	Tx or rx job stalled due to line disconnection at the other end	<ul> <li>The job started normally but did not finish normally; data may or may not have been received fully.</li> <li>Restart the machine.</li> </ul>
22-04	The machine cannot store received data in the SAF	<ul><li>Update the ROM</li><li>Replace the FCU.</li></ul>
22-05	No G3 parameter confirmation answer	Defective FCU board or firmware.
23-00	Data read timeout during construction	<ul><li>Restart the machine.</li><li>Replace the FCU.</li></ul>
25-00	The machine software resets itself after a fatal transmission error occurred	<ul><li>Update the ROM</li><li>Replace the FCU.</li></ul>
F0-xx	V.34 modem error	Replace the FCU.
F6-xx	SG3 modem error	<ul> <li>Update the SG3 modem ROM.</li> <li>Replace the SG3 board.</li> <li>Check for line noise or other line problems.</li> <li>Try communicating another V.8/V.34 fax.</li> </ul>

# **IFAX Troubleshooting**

Use the following procedures to determine whether the machine or another part of the network is causing the problem.

Communication Route	ltem	Action [Remarks]
General LAN	1. Connection with the LAN	<ul> <li>Check that the LAN cable is connected to the machine.</li> <li>Check that the LEDs on the hub are lit.</li> </ul>
	2. LAN activity	Check that other devices connected to the LAN can communicate through the LAN.
Between IFAX and PC	Network settings     on the PC	• Check the network settings on the PC. [Is the IP address registered in the TCP/IP properties in the network setup correct? Check the IP address with the administrator of the network.]
	2. Check that PC can connect with the machine	<ul> <li>Use the "ping" command on the PC to contact the machine.</li> <li>[At the MS-DOS prompt, type ping then the IP address of the machine, then press Enter.]</li> </ul>
	3. LAN settings in the machine	<ul> <li>Check the LAN parameters</li> <li>Check if there is an IP address conflict with other PCs.</li> <li>[Use the "Network" function in the User Tools.</li> <li>If there is an IP address conflict, inform the administrator.]</li> </ul>
Between machine and e-mail server	LAN settings in the machine	<ul> <li>Check the LAN parameters</li> <li>Check if there is an IP address conflict with other PCs.</li> <li>[Use the "Network" function in the User Tools.</li> <li>If there is an IP address conflict, inform the administrator.]</li> </ul>

Communication Route	Item	Action [Remarks]
Between machine and e-mail server	E-mail account     on the server	<ul> <li>Make sure that the machine can log into the e-mail server.</li> <li>Check that the account and password stored in the server are the same as in the machine.</li> <li>[Ask the administrator to check.]</li> </ul>
	2. E-mail server	Make sure that the client devices which have an account in the server can send/receive e-mail.  [Ask the administrator to check.  Send a test e-mail with the machine's own number as the destination. The machine receives the returned e-mail if the communication is performed successfully.]
Between e-mail server and internet	E-mail account     on the Server	<ul> <li>Make sure that the PC can log into the e-mail server.</li> <li>Check that the account and password stored in the server are the same as in the machine.</li> <li>[Ask the administrator to check.]</li> </ul>
	2. E-mail server	Make sure that the client devices which have an account in the server can send/receive e-mail.  [Ask the administrator to check.  Send a test e-mail with the machine's own number as the destination. The machine receives the returned e-mail if the communication is performed successfully.]
	3. Destination e-mail address	<ul> <li>Make sure that the e-mail address is actually used.</li> <li>Check that the e-mail address contains</li> </ul>

Communication Route	Item	Action [Remarks]
		no incorrect characters such as spaces.
Between e-mail server and internet	Router settings	<ul> <li>Use the "ping" command to contact the router.</li> <li>Check that other devices connected to the router can sent data over the router.</li> <li>[Ask the administrator of the server to check.]</li> </ul>
Between e-mail server and internet	Error message by e-mail from the network of the destination.	<ul> <li>Check whether e-mail can be sent to another address on the same network, using the application e-mail software.</li> <li>Check the error e-mail message.</li> <li>[Inform the administrator of the LAN.]</li> </ul>

# IP-Fax Troubleshooting

### IP-Fax Transmission

### Cannot send by IP Address/Host Name

Che	eck Point	Action
1	LAN cable connected?	Check the LAN cable connection.
2	Specified IP address/host name correct?	Check the IP address/host name.
3	Firewall/NAT is installed?	Cannot breach the firewall. Send by using another method (Fax, Internet Fax)
4	Transmission sent manually?	Manual sending not supported.
5	IP address of local machine registered?	Register the IP address.
6	Remote terminal port number setting other than 1720?	Send by specifying the port number.
7	Specified port number correct?	Confirm the port number of the remote fax.
8	DNS server registered when host name specified?	Contact the network administrator.
9	Remote fax a T.38 terminal?	Check whether the remote fax is a T38 terminal.
10	Remote fax switched off or busy?	Check that the remote fax is switched on.
		Request the network administrator to increase the bandwidth.
11	Network bandwidth too narrow?	Raise the delay level.  IPFAX SW 01 Bit 0 to 3
		IP-Fax bandwidth is the same as the

		DCS speed. Set IP-Fax SW00 Bit 6 to 1.
12	Remote fax cancelled transmission?	Check whether the remote fax cancelled the transmission.

### Cannot send via VoIP Gateway

Che	ck Point	Action
1	LAN cable connected?	Check the LAN cable connection.
2	VoIP Gateway T.38 standard?	Contact the network administrator.
3	VoIP Gateway installed correctly?	Contact the network administrator.
4	VoIP Gateway power switched on?	Contact the network administrator.
5	Is the IP address/host name of the specified Gateway correct?	Check the IP address/host name.
6	Number of the specified fax correct?	Check the remote fax number.
7	Firewall/NAT is installed?	Cannot breach the firewall. Send by using another method (Fax, Internet Fax)
8	Transmission sent manually?	Manual sending not supported.
9	IP address of local fax registered?	Register the IP address.
10	DNS registered when host name specified?	Contact the network administrator.
11	Remote fax a G3 fax?	Check that the remote fax is a G3 fax.
12	G3 fax is connected to VoIP gateway?	Check that G3 fax is connected.
13	Remote G3 fax turned on?	Check that G3 fax is switched on.
14	Network bandwidth too narrow?	Request the network administrator to increase the bandwidth.

	Raise the network delay level.  IPFAX SW 01 Bit 0 to 3
	IP-Fax bandwidth is the same as the DCS speed. Set IP-Fax SW00 Bit 6 to 1.

### Cannot send by Alias Fax number.

Check Point		Action
1	LAN cable connected?	Check the LAN cable connection.
2	Number of specified Alias fax correct?	Confirm the Alias of the remote fax.  Error Code: 13-14
3	Firewall/NAT installed?	Cannot breach the firewall. Send by using another method (Fax, Internet Fax)
4	Transmission sent manually?	Manual sending not supported.
5	Gatekeeper installed correctly?	Contact the network administrator.
6	Gatekeeper power switched on?	Contact the network administrator.
7	IP address/host name of Gatekeeper correct?	Check the IP address/host name.
8	DNS server registered when Gatekeeper host name specified?	Contact the network administrator.
9	Enable H.323 SW is set to on?	Check the settings. See User Parameter SW 34 Bit 0
10	IP address of local fax registered?	Register the IP address of the local fax.
11	Alias number of local fax registered?	Register the Alias number of the local fax.
12	Remote fax registered in Gatekeeper?	Contact the network administrator.

13	Remote fax a T.38 terminal?	Check whether the remote fax is a T38 terminal.
14	Remote fax switched off or busy?	Contact the network administrator.
	Network bandwidth too narrow?	Request the system administrator to increase the bandwidth.
15		Raise the delay level.  IPFAX SW 01 Bit 0 to 3
		Lower the modem transmission baud rate.  IPFAX SW 05
16	Remote fax cancelled transmission?	Check whether the remote fax cancelled the transmission.

### IP-Fax Reception

### Cannot receive by IP Address/Host name.

Che	eck Point	Action
1	LAN cable connected?	Check the LAN cable connection.
2	Firewall/NAT is installed?	Cannot breach the firewall. Send by using another method (Fax, Internet Fax)
3	IP address of local fax registered?	Register the IP address.
4	Port number specified at remote sender fax (if required)?	Request the sender to specify the port number.
5	Specified port number correct (if required)?	Request the sender to check the port number.
6	DNS server registered when host name specified on sender side?	Contact the network administrator.  Note  The sender machine displays this

		error code if the sender fax is a Ricoh model.
7 1	Network bandwidth too narrow?	Request the system administrator to increase the bandwidth.
		Lower the start modem reception baud rate on the receiving side.  IPFAX SW06
8	Remote fax cancelled transmission?	Check whether the remote fax cancelled the transmission.

### Cannot receive by VoIP Gateway.

Check Point		Action
1	LAN cable connected?	Check the LAN cable connection.
2	Firewall/NAT is installed?	Cannot breach the firewall. Request the remote fax to send by using another method (Fax, Internet Fax)
3	VoIP Gateway installed correctly?	Contact the network administrator.
4	VoIP Gateway power switched on?	Contact the network administrator.
5	IP address/host name of specified VoIP Gateway correct on sender's side?	Request the remote fax to check the IP address/host name.
6	DNS server registered when host name specified on sender side?	Contact the network administrator.
7	Network bandwidth too narrow?	Request the network administrator to increase the bandwidth.
8	G3 fax connected?	Check that G3 fax is connected.
9	G3 fax power switched on?	Check that G3 fax is switched on.

### Cannot receive by Alias Fax number.

Check Point		Action
1	LAN cable connected?	Check the LAN cable connection.
2	Firewall/NAT is installed?	Cannot the breach firewall. Request the remote fax to send by using another method (Fax, Internet Fax)
3	Gatekeeper installed correctly?	Contact the network administrator.  Note  The sender machine displays this error code when the sender fax is a Ricoh model.
4	Power to Gatekeeper switched on?	Contact the network administrator.  Note  The sender machine displays this error code when the sender fax is a Ricoh model.
5	IP address/host name of Gatekeeper correct on the sender's side?	Request the sender to check the IP address/host name.  Note  The sender machine displays this error code when the sender fax is a Ricoh model.
6	DNS server registered when Gatekeeper host name specified on sender's side?	Contact the network administrator.  Note  The sender machine displays this error code when the sender fax is a Ricoh model.
7	Enable H.323 SW is set to on?	Request the sender to check the settings.  User Parameter SW 34 Bit 0  Note  Only if the remote sender fax is a

		Ricoh fax.
8	Local fax IP address registered?	Register the IP address.
9	Local fax Alias number registered?	Register the Alias number.
	Network bandwidth too narrow?	Request the system administrator to increase the bandwidth.
10		Lower the start modem reception baud rate on the receiving side.  IPFAX SW06
11	Remote fax cancelled transmission?	Check whether the remote fax cancelled the transmission.
12	Local fax registered in Gatekeeper?	Contact the network administrator.  Note  The sender machine displays this error code when the sender fax is a Ricoh model.

## Service Tables

### Beforehand

### CAUTION

Never turn off the main power switch when the power LED is lit or flashing. To avoid damaging the hard disk or memory, press the operation power switch to switch the power off, wait for the power LED to go off, and then switch the main power switch off



■ The main power LED ( ) lights or flashes while the platen cover or ARDF is open, while the main machine is communicating with a facsimile or the network server, or while the machine is accessing the hard disk or memory for reading or writing data.

## Service Tables

### SP1-XXX (Bit Switches)

#### Bit Switches

1	Mode No.		Function	
	System Switch			
101	001 – 032	00 – 1F	Change the bit switches for system settings for the fax option  ( Bit Switches)	
	Ifax Switch			
102	001 – 016	00 – 0F	Change the bit switches for internet fax settings for the fax option  (**Bit Switches)	
	Printer Switch			
103	001 – 016	00 – 0F	Change the bit switches for printer settings for the fax option (** "Bit Switches")	
	Communication Switch			
104	001 – 032	00 – 1F	Change the bit switches for communication settings for the fax option  "Bit Switches"	
	G3-1 Switch			
105	001 – 016	00 – 0F	Change the bit switches for the protocol settings of the standard G3 board  "Bit Switches"	
	G3-2 Switch			
106	001 – 016	00 – 0F	Change the bit switches for the protocol settings of the optional G3 board	

			"Bit Switches"
	G3-3 Switch		
107	001 – 016	00 – 0F	Change the bit switches for the protocol settings of the optional G3 board  "Bit Switches"
108	G4 Internal Switch		
100	001 – 032	00 – 1F	Not used (Do not change the bit switches)
109	G4 Parameter Switch		
	001 – 016	00 – 0F	Not used (Do not change the bit switches)
	IP fax Switch		
111	001 – 016	00 – 0F	Change the bit switches for optional IP fax parameters  "Bit Switches"

### SP2-XXX (RAM Data)

2	Mode No.		Function
	RAM Read/\	Vrite	
101	001		Change RAM data for the fax board directly.  "Service RAM Addresses"
102	Memory Dump		
	001	G3-1 Memory Dump	Print out RAM data for the fax board.  "Service RAM Addresses"
	002	G3-2 Memory Dump	Print out RAM data for the optional SG3 board.
	003	G3-3 Memory Dump	Print out RAM data for the optional SG3 board.

	004	G4 Memory Dump	Print out RAM data for the SiG4 board.
	G3-1 NCU Parameters		
103	001 – 023	CC, 01 – 22	NCU parameter settings for the standard G3 board. "NCU Parameters"
	G3-2 NCU Parameters		
104	001 – 023	CC, 01 – 22	NCU parameter settings for the optional G3 board. TNCU Parameters
	G3-3 NCU Parameters		
105	001 – 023	CC, 01 – 22	NCU parameter settings for the optional G3 board. "NCU Parameters"

## SP3-XXX (Tel Line Settings)

3	Mode No.		Function
	Service Stati	on	
101	001	Fax Number	Enter the fax number of the service station.
	002	Select Line	Select the line type.
102	Serial Numb	er	
.02	000		Enter the fax unit's serial number.
	PSTN-1 Port Settings		
103	001	Select Line	Select the line type setting for the G3-1 line. If the machine is installed on a PABX line, select "PABX", "PABX(GND)" or "PABX(FLASH)".
100	002	PSTN Access Number	Enter the PSTN access number for the G3-1 line.
	003	Memory Lock Disabled	If the customer does not want to receive transmissions using Memory Lock on this line,

			turn this SP on.	
	PSTN-2 Port Settings			
	001	Select Line	Select the line setting for the G3-2 line. If the machine is installed on a PABX line, select "PABX", "PABX(GND)" or "PABX(FLASH)".	
104	002	PSTN Access Number	Enter the PSTN access number for the G3-2 line.	
	003	Memory Lock Disabled	If the customer does not want to receive transmissions using Memory Lock on this line, change this SP to on.	
	004	Transmission Disabled	If you turn this SP on, the machine does not send any fax messages on the G3-2 line.	
	PSTN-3 Port Settings			
	001	Select Line	Select the line setting for the G3-3 line. If the machine is installed on a PABX line, select "PABX", "PABX(GND)" or "PABX(FLASH)".	
105	002	PSTN Access Number	Enter the PSTN access number for the G3-3 line.	
	003	Memory Lock Disabled	If the customer does not want to receive transmissions using Memory Lock on this line, change this SP to on.	
	004	Transmission Disabled	If you turn this SP on, the machine does not send any fax messages on the G3-3 line.	
	ISDN Port Settings			
	001	Select Line	Not used (Do not change the bit switches)	
106	002	PSTN Access Number		
	003	Memory Lock		

		Disabled	
106	004	Transmission Disabled	
	IPFAX Port S	Settings	
	001	H323 Port	
	002	SIP Port	
	003	RAS Port	
107	004	Gatekeeper port	
	005	T.38 Port	
	006	SIP Server Port	
	007	IPFAX Protocol Priority	Select "H323" or "SIP".
201	FAX SW		
201	001 – 032	00 – 1F	

### SP4-XXX (ROM Versions)

4	Mode No.		Function
101	001	FCU ROM Version	Displays the FCU ROM version.
102	001	Error Codes	Displays the latest 64 fax error codes.
103	001	G3-1 ROM Version	Displays the G3-1 modem version.
104	001	G3-2 ROM Version	Displays the G3-2 modem version.
105	001	G3-3 ROM Version	Displays the G3-3 modem version.
106	001	G4 ROM Version	Not used (Do not change the bit switches)
107	001	Charge ROM Version	Not used (Do not change the bit switches)

### SP5-XXX (Initializing)

5	Mode No.	Function		
	Initialize SRAM			
101	000	Initializes the bit switches and user parameters, user data in the SRAM, files in the SAF memory, and clock.		
102	Erase All Files			
102	000	Erases all files stored in the SAF memory.		
103	Reset Bit Switches			
	000	Resets the bit switches and user parameters.		
	Factory setting			
104	000	Resets the bit switches and user parameters, user data in the SRAM and files in the SAF memory.		
105	Initialize All Bit Switches			
100	000	Initializes all the current bit switch settings.		
	Initialize Security Bit Switches			
106	000	Initializes only the security bit switches. If you select automatic output/display for the user parameter switches, the security settings are initialized.		

### SP6-XXX (Reports)

6	Mode No.		Function
	System Parameter List		
101	000	-	Touch the "ON" button to print the system parameter list.

	Service N	Nonitor Report	
102	000	-	Touch the "ON" button to print the service monitor report.
	G3 Protocol Dump List		
	001	G3 All Communications	Prints the protocol dump list of all communications for all G3 lines.
	002	G3-1 (All Communications)	Prints the protocol dump list of all communications for the G3-1 line.
	003	G3-1 (1 Communication)	Prints the protocol dump list of the last communication for the G3-1 line.
103	004	G3-2 (All Communications)	Prints the protocol dump list of all communications for the G3-2 line.
	005	G3-2 (1 Communication)	Prints the protocol dump list of the last communication for the G3-2 line.
	006	G3-3 (All Communications)	Prints the protocol dump list of all communications for the G3-3 line.
	007	G3-3 (1 Communication)	Prints the protocol dump list of the last communication for the G3-3 line.
	G4 Protocol Dump List		
	001	Dch + Bch 1	
	002	Dch	
104	003	Bch 1 Link Layer	Not used (Do not change the bit switches)
	004	Dch Link Layer	(= 2 mai amango ano an amanoo)
	005	Dch +Bch 2	
	006	Bch 2 Link Layer	

	All Files print out			
105	000	-	Prints out all the user files in the SAF memory, including confidential messages.  Note  Do not use this function, unless the customer is having trouble printing confidential messages or recovering files stored using the memory lock feature.	
	Journal P	rint out		
106	001	All Journals	The machine prints all the communication records on the report.	
	002	Specified Date	The machine prints all communication records after the specified date.	
107	Log List F	Print out		
	001	All log files	These log print out functions are for designer	
	002	Printer	use only.	
	003	SC/TRAP Stored		
	004	Decompression		
	005	Scanner		
	006	JOB/SAF		
	007	Reconstruction		
	008	JBIG		
	009	Fax Driver		
	010	G3CCU		
	011	Fax Job		
	012	CCU		

	013	Scanner Condition	
	IP Protoco	ol Dump List	
108	001	All Communications	Prints the protocol dump list of all communications for the IP fax line.
	002	1 Communication	Prints the protocol dump list of the last communication for the IP fax line.

### SP7-XXX (Test Modes)

These are the test modes for PTT approval.

7	Function
101	G3-1 Modem Tests
102	G3-1 DTMF Tests
103	Ringer Test
104	G3-1 V34 (S2400baud)
105	G3-1 V34 (S2800baud)
106	G3-1 V34 (S3000baud)
107	G3-1 V34 (S3200baud)
108	G3-1 V34 (S3429baud)
109	Recorded Message Test
110	G3-2 Modem Tests
111	G3-2 DTMF Tests
112	G3-2 V34 (S2400baud)
113	G3-2 V34 (S2800baud)
114	G3-2 V34 (S3000baud)

115	G3-2 V34 (S3200baud)
116	G3-2 V34 (S3429baud)
117	G3-3 Modem Tests
118	G3-3 DTMF Tests
119	G3-3 V34 (S2400baud)
120	G3-3 V34 (S2800baud)
121	G3-3 V34 (S3000baud)
122	G3-3 V34 (S3200baud)
123	G3-3 V34 (S3429baud)
124	IG3-1 Modem Tests - <b>Not used</b>
125	IG3-1 DTMF Tests - Not used
126	IG3-1 V34 (S2400baud) - <b>Not used</b>
127	IG3-1 V34 (S2800baud) - <b>Not used</b>
128	IG3-1 V34 (S3000baud) - <b>Not used</b>
129	IG3-1 V34 (S3200baud) - <b>Not used</b>
130	IG3-1 V34 (S3429baud) - <b>Not used</b>
131	IG3-2 Modem Tests - <b>Not used</b>
132	IG3-2 DTMF Tests - Not used
133	IG3-2 V34 (S2400baud) - <b>Not used</b>
134	IG3-2 V34 (S2800baud) - <b>Not used</b>
135	IG3-2 V34 (S3000baud) - <b>Not used</b>
136	IG3-2 V34 (S3200baud) - <b>Not used</b>
137	IG3-2 V34 (S3429baud) - <b>Not used</b>

### SP9-XXX (Design Switch Mode)

9	Mode No.		Function
702	Design Switch	DFU	

### Bit Switches

### **<b>⚠WARNING**

Do not adjust a bit switch or use a setting that is described as "Not used", as this may cause the machine to malfunction or to operate in a manner that is not accepted by local regulations. Such bits are for use only in other areas, such as Japan.



 Default settings for bit switches are not listed in this manual. Refer to the System Parameter List printed by the machine.

#### System Switches

Syst	System Switch 00 [SP No. 1-101-001]		
No	FUNCTION	COMMENTS	
0	Dedicated transmission parameter programming 0: Disabled, 1: Enabled	Set this bit to 1 before changing any dedicated transmission parameters.  Reset this bit to 0 after programming dedicated transmission parameters.	
1	Not used	Do not change	
2	Technical data printout on the Journal 0: Disabled 1: Enabled	1: Instead of the personal name, the following data are listed on the Journal for each G3 communication.	
	e.g. 0000 (1) // 32 (2) V34 (3) // 288 (4) // 264 (5) // L0100 (6) 03 (7) 04 (8) (1): EQM value (Line quality data). A larger number means more errors. (2): Symbol rate (V.34 only) (3): Final modem type used (4): Starting data rate (for example, 288 means 28.8 kbps) (5): Final data rate (6): Rx revel (refer to the note after this table for how to read the rx level) (7): Total number of error lines that occurred during non-ECM reception. (8): Total number of burst error lines that occurred during non-ECM reception.		

• EQM and rx level are fixed at "FFFF" in tx mode.

■ The seventh and eighth numbers are fixed at "00" for transmission records and ECM reception records.

Rx level calculation

Example: 0000 // 32 V34 // 288/264 // L 01 00 03 04

The four-digit hexadecimal value (N) after "L" indicates the rx level.

The high byte is given first, followed by the low byte. Divide the decimal value of N by -16 to get the rx level.

In the above example, the decimal value of N (= 0100 [H]) is 256.

So, the actual rx level is 256/-16 = -16 dB

3	Not used	Do not change this setting.
4	Line error mark print 0: OFF, 1: ON (print)	When "1" is selected, a line error mark is printed on the printout if a line error occurs during reception.
5	G3/G4 communication parameter display 0: Disabled 1: Enabled	This is a fault-finding aid. The LCD shows the key parameters (see below). This is normally disabled because it cancels the CSI display for the user. Be sure to reset this bit to 0 after testing.
6	Protocol dump list output after each communication 0: Off 1: On	This is only used for communication troubleshooting. It shows the content of the transmitted facsimile protocol signals. Always reset this bit to 0 after finishing testing.  If system switch 09 bit 6 is at "1", the list is only printed if there was an error during the communication.
7	Not used	Do not change the setting.

**System Switch 01 - Not used** (Do not change the factory settings.)

Syst	System Switch 02 [SP No. 1-101-003]			
No	FUNCTION	COMMENTS		
0-1	Not used	Do not change these settings.		
2	Force after transmission stall 0: Off 1: On	With this setting on, the machine resets itself automatically if a transmission stalls and fails to complete the job.		
3-4	Not used	Do not change these settings.		
5	Not used	Do not change this setting.		
6-7	Memory read/write by RDS Bit 7: 0, Bit 6: 0 Always disabled Bit 7: 0, Bit 6: 1 User selectable Bit 7: 1, Bit 6: 0 User selectable Bit 7: 1, Bit 6: 1 Always enabled	(0,0): All RDS systems are always locked out. (0,1), (1,0): Normally, RDS systems are locked out, but the user can temporarily switch RDS on to allow RDS operations to take place. RDS will automatically be locked out again after a certain time, which is stored in System Switch 03. Note that if an RDS operation takes place, RDS will not switch off until this time limit has expired. (1,1): At any time, an RDS system can access the machine.		

System Switch 03 [SP No. 1-101-004]			
No	FUNCTION	COMMENTS	
0-7	Length of time that RDS is temporarily switched on when bits 6 and 7 of System Switch	00 - 99 hours (BCD). This setting is only valid if bits 6 and 7 of System Switch 02 are set to "User selectable".	
	02 are set to "User selectable"	The default setting is 24 hours.	

System Switch 04 [SP No. 1-101-005]		
No	FUNCTION	COMMENTS
0-2	Not used	Do not change these settings.

4-7	Not used	Do not change these settings.
	0: Disabled 1: Enabled	dedicated tx parameters; 34 bytes of data are printed (the other 24 bytes have no use for service technicians).
3	Dial Lists	The first 10 bytes of data are the programmed
	Printing dedicated tx parameters on Quick/Speed	1: Each Quick/Speed dial number on the list is printed with the dedicated tx parameters (10 bytes each).

System Switch 05 - Not used (Do not change the factory settings.)

**System Switch 06 - Not used** (Do not change the factory settings.)

System Switch 07 - Not used (Do not change the factory settings.)

**System Switch 08 - Not used** (Do not change the factory settings.)

Syst	System Switch 09 [SP No. 1-101-010]		
No	FUNCTION	COMMENTS	
0	Not used	Do not change these settings.	
1	Inclusion of communications on the Journal when no image data was exchanged.  0: Disabled 1: Enabled	O: Communications that reached phase C (message tx/rx) of the T.30 protocol are listed on the Journal.  1: Communications that reached phase A (call setup) of T.30 protocol are listed on the Journal.  This will include telephone calls.	
2	Automatic error report printout 0: Disabled 1: Enabled	O: Error reports will not be printed.     1: Error reports will be printed automatically after failed communications.	
3	Printing of the error code on the error report  0: No 1: Yes	1: Error codes are printed on the error reports.	

4	Not used	Do not change this setting.
5	Power failure report 0: Disabled 1: Enabled	1: A power failure report will be automatically printed after the power is switched on if a fax message disappeared from the memory when the power was turned off last.
6	Conditions for printing the protocol dump list  0: Print for all communications  1: Print only when there is a communication error	This switch becomes effective only when system switch 00 bit 6 is set to 1.  1: Set this bit to 1 when you wish to print a protocol dump list only for communications with errors.
7	Priority given to various types of remote terminal ID when printing reports  0: RTI > CSI > Dial label > Tel.  Number  1: Dial label > Tel. number > RTI > CSI	This bit determines which set of priorities the machine uses when listing remote terminal names on reports.  Dial Label: The name stored, by the user, for the Quick/Speed Dial number.

Syst	System Switch 0A [SP No. 1-101-011]		
No	FUNCTION	COMMENTS	
0-3	Not used	Do not change these settings.	
4	Dialing on the ten-key pad when the external telephone is off-hook 0: Disabled 1: Enabled	0: Prevents dialing from the ten-key pad while the external telephone is off-hook. Use this setting when the external telephone is not by the machine, or if a wireless telephone is connected as an external telephone.  1: The user can dial on the machine's ten-key pad when the handset is off-hook.	
5	On hook dial 0: Disabled 1: Enabled	0: On hook dial is disabled.	
6-7	Not used	Do not change the factory settings	

System Switch 0B - Not used (Do not change the factory settings.)

**System Switch 0C - Not used** (Do not change the factory settings.)

System Switch 0D - Not used (Do not change the factory settings.)

Syst	System Switch 0E [SP No. 1-101-015]		
No	FUNCTION	COMMENTS	
0-1	Not used	Do not change the settings.	
2	Not used	This machine does not have the capture function.	
3	Action when the external handset goes off-hook  0: Manual tx and rx operation  1: Memory tx and rx operation (the display remains the same)	<ul> <li>0: Manual tx and rx are possible while the external handset is off-hook. However, memory tx is not possible.</li> <li>1: The display stays in standby mode even when the external handset is used, so that other people can use the machine for memory tx operation.</li> <li>Note that manual tx and rx are not possible with this setting.</li> </ul>	
4-7	Not used	Do not change these settings.	

Syst	System Switch 0F [SP No. 1-101-016]		
No	FUNCTION		COMMENTS
0-7	Country/area consettings (Hex)	ode for functional	This country/area code determines the factory settings of bit switches and RAM addresses.
	00: France	11: USA	However, it has no effect on the NCU parameter settings and communication
	01: Germany	12: Asia	parameter RAM addresses.
	02: UK	13: Japan	Cross reference:  NCU country code:
	03: Italy	14: Hong Kong	SP No. 2-103-001 for G3-1

04: Austria	15: South Africa
05: Belgium	16: Australia
06: Denmark	17: New Zealand
07: Finland	18: Singapore
08: Ireland	19: Malaysia
09: Norway	1A: China
0A: Sweden	1B: Taiwan
0B: Switz.	1C: Korea
0C: Portugal	20: Turkey
0D: Holland	21: Greece
0E: Spain	22: Hungary
0F: Israel	23: Czech
10:	24: Poland

Syst	System Switch 10 [SP No. 1-101-017]		
No	FUNCTION	COMMENTS	
0-7	Threshold memory level for parallel memory transmission	Threshold = N x 128 KB + 256 KB  N can be between 00 - FF(H)  Default setting: 02(H) = 512 KB	

Syst	System Switch 11 [SP No. 1-101-018]		
No	FUNCTION	COMMENTS	
0	TTI printing position 0: Superimposed on the page data 1: Printed before the data	Change this bit to 1 if the TTI overprints information that the customer considers to be important (G3 transmissions).	

	leading edge	
1	Not used	Japan Only
2-7	Not used	Do not change the factory settings.

Syst	System Switch 12 [SP No. 1-101-019]		
No	FUNCTION	COMMENTS	
0-7	TTI printing position in the main scan direction	TTI: 08 to 92 (BCD) mm Input even numbers only. This setting determines the print start position for the TTI from the left edge of the paper. If the TTI is moved too far to the right, it may overwrite the file number which is on the top right of the page. On an A4 page, if the TTI is moved over by more than 50 mm, it may overwrite the page number.	

System Switch 13 - Not used (do not change these settings)

System Switch 14 - Not used (do not change these settings)

Syst	System Switch 15 [SP No. 1-101-022]		
No	FUNCTION	COMMENTS	
0	Not used	Do not change the settings.	
1	Going into the Energy Saver mode automatically 0: Enabled 1: Disabled	1: The machine will restart from the Energy Saver mode quickly, because the +5V power supply is active even in the Energy Saver mode.	
2-3	Not used	Do not change these settings.	
4-5	Interval for preventing the machine from entering Energy	If there is a file waiting for transmission, the machine does not go to Energy Saver mode	

	Saver mode if there is a pending transmission file. Bit 5: 0, Bit 4: 0 1 min Bit 5: 0, Bit 4: 1 30 min1 Bit 5: 1, Bit 4: 0 1 hour Bit 5: 1, Bit 4: 1	during the selected period.  After transmitting the file, if there is no file waiting for transmission, the machine goes to the Energy Saver mode.
	24 hours	
6-7	Not used	Do not change

Syst	System Switch 16 [SP No. 1-101-023]		
No	FUNCTION	COMMENTS	
0	Parallel Broadcasting 0: Disabled 1: Enabled	1: The machine sends messages simultaneously using all available ports during broadcasting.	
1-7	Not used	Do not change these settings.	

System Switch 17 - Not used (do not change these settings)

System Switch 18 - Not used (do not change these settings)

Syst	System Switch 19 [SP No. 1-101-026]		
No	FUNCTION	COMMENTS	
0-6	Not used	Do not change the settings.	
7	Special Original mode 0: Disabled 1: Enabled	1: If the customer frequently wishes to transmit a form or letterhead which has a colored or printed background, change this bit to "1". "Original 1" and "Original 2" can be selected in addition to the "Text",	

ű	"Text/Photo" and "Photo" modes.
---	---------------------------------

Syst	System Switch 1A [SP No. 1-101-027]		
No.	FUNCTION COMMENTS		
0-7	Not used	Do not change the settings.	

#### **System Switch 1B [SP No. 1-101-028]**

In this switch setting, there is a limitation. Do not select the same image quality in two modes.

e.g) these setting combination is not allowed:

[Bit1: 0, Bit 0: 0 = **Text**] [Bit3: 0, Bit 2:0 = Text/ Photo] [Bit 6: 0, Bit 5: 0, Bit 4: 0 = **Text**]

No.	FUNCTION			COMMENTS		
0-1	Image Quality in Text mode Bit 1: 0, Bit 0: 0 = Text Bit 1: 0, Bit 0: 1 = Text/ Picture		image q	ting determines the desirable scanning uality when the text mode is selected with ration panel.		
2-3	Image Quality in Photo mode Bit 3: 0, Bit 2: 0 = Text/ Photo Bit 3: 0, Bit 2: 1 = Text		image q	ting determines the desirable scanning uality when the photo mode is selected with ration panel.		
4-6		nage Quality in Special riginal mode		image q	ting determines the desirable scanning uality when the special original mode is I with the operation panel.	
	Bit 6	Bit 5	Bit 4	М	ode	
	0	0	0	Text		
	0	0	1	Text/ Picture		
	0	1	0	Text/ Photo		
	0	1	1	Pł	noto	

	1	0	0	Special 1			
	1	0	1	Spe	cial 2		
7	Not used		Do not c	change these settings.			

### System Switch 1C - Not used (do not change these settings)

Syst	System Switch 1D [SP No. 1-101-030]			
No	FUNCTION	COMMENTS		
0	RTI/CSI/CPS code display 0: Enable 1: Disable	0: RTI, CSI, CPS codes are displayed on the top line of the LCD panel during communication.  1: Codes are switched off (no display)		
1	Not used	Do not change this setting.		
2	Destination telephone number display limitation 0: OFF, 1: ON	When "1" is selected, the destination telephone number display is limited and redial is disabled.		
3	Operation selection without PIN code registered 0: Transmission interrupted 1: No interrupted transmission	0: When "0" is selected without PIN code registration, transmission is interrupted and an alert message shows on the LCD.		
4-7	Not used	Do not change these settings.		

Syst	System Switch 1E [SP No. 1-101-031]			
No	FUNCTION	COMMENTS		
0	Communication after the Journal data storage area has become full 0: Impossible	0: When this switch is on and the journal history becomes full, the next report prints. If the journal history is not deleted, the next transmission cannot be received. This prevents overwriting		

	1: Possible	communication records before the machine can print them.  1: If the buffer memory of the communication records for the Journal is full, fax communications are still possible. But the machine will overwrite the oldest communication records.  Note: This setting is effective only when Automatic Journal printout is enabled but the machine cannot print the report (e.g., no paper).
1	Action when the SAF memory has become full during scanning 0: The current page is erased. 1: The entire file is erased.	O: If the SAF memory becomes full during scanning, the successfully scanned pages are transmitted.  1: If the SAF memory becomes full during scanning, the file is erased and no pages are transmitted.  This bit switch is ignored for parallel memory transmission.
2	RTI/CSI display priority 0: RTI 1: CSI	This bit determines which identifier, RTI or CSI, is displayed on the LCD while the machine is communicating in G3 non-standard mode.
3	File No. printing 0: Enabled 1: Disabled	1: File numbers are not printed on any reports.
4	Action when authorized reception is enabled but authorized RTIs/CSIs are not yet programmed 0: All fax reception is disabled 1: Faxes can be received if the sender has an RTI or CSI	If authorized reception is enabled but the user has stored no acceptable sender RTIs or CSIs, the machine will not be able to receive any fax messages.  If the customer wishes to receive messages from any sender that includes an RTI or CSI, and to block messages from senders that do not include an RTI or CSI, change this bit to "1", then enable Authorized Reception.  Otherwise, keep this bit at "0 (default setting)".

5-7	Not used	Do not change the settings
-----	----------	----------------------------

Syst	System Switch 1F [SP No. 1-101-032]			
No	FUNCTION	COMMENTS		
0	Not used	Do not change the settings.		
1	Report printout after an original jam during SAF storage or if the SAF memory fills up 0: Enabled 1: Disabled	0: When an original jams, or the SAF memory overflows during scanning, a report will be printed. Change this bit to "1" if the customer does not want to have a report in these cases.  Memory tx – Memory storage report  Parallel memory tx – Transmission result report		
2	Not used	Do not change the settings.		
3	Received fax print start timing (G3 reception)  0: After receiving each page  1: After receiving all pages	O: The machine prints each page immediately after the machine receives it.  1: The machine prints the complete message after the machine receives all the pages in the memory.		
4-6	Not used	Do not change the factory settings.		
7	Action when a fax SC has occurred 0: Automatic reset 1: Fax unit stops	0: When the fax unit detects a fax SC code other than SC1201 and SC1207, the fax unit automatically resets itself.  1: When the fax unit detects any fax SC code, the fax unit stops.  Cross reference:  Fax SC codes - See "Troubleshooting"		

### I-Fax Switches

I-fax Switch 00 [SP No. 1-102-001]		
No	FUNCTION	COMMENTS

	Original Width of TX Attachment File	This setting sets the maximum size of the original that the destination can receive. (Bits 3~7 are reserved for future use or not used.)
0	A4	0: Off (not selected), 1: On (selected)
1	B4	If more than one of these three bits is set to "1", the larger size has priority. For example, if both Bit
2	А3	2 and Bit 1 are set to "1" then the maximum size is
3-6	Reserved	"A3" (Bit 2).  When mail is sent, there is no negotiation with the
7	Not used	receiving machine at the destination, so the sending machine cannot make a selection for the receiving capabilities (original width setting) of the receiving machine. The original width selected with this switch is used as the RX machine's original width setting, and the original is reduced to this size before sending. The default is A4. If the width selected with this switch is higher than the receiving machine can accept, the machine detects this and this causes an error.

I-fax	I-fax Switch 01 [SP No. 1-102-002]				
No	FUNCTION	COMMENTS			
	Original Line Resolution of TX Attachment File	These settings set the maximum resolution of the original that the destination can receive.			
0	200x100 Standard	0: Not selected			
1	200x200 Detail	1: Selected  If more than one of these three bits is set to "1",			
2	200x400 Fine	the higher resolution has priority. For example, if			
3	300 x 300 Reserve	both Bit 0 and Bit 2 are set to "1" then the resolution is set for "Bit 2 200 x 400.			
4	400 x 400 Super Fine				
5	600 x 600 Reserve				

6	Reserve	
	mm/inch	
7	There is no switch for converting Unlike G3 fax transmissions wh	conversion) ne converts millimeters to inches for sending mail. g inches to millimeters. ich can negotiate between sender and receiver to not negotiate between terminals; the mm/inch sender fax.  sent in inches. t in mm. ransmitted in inches. ssmitted in mm.  sent in inches. verted to inches. ransmitted in inches.

I-fax Switch 02 [SP No. 1-102-003]			
No	FUNCTION	COMMENTS	
	RX Text Mail Header Processing		
0	This setting determines whether the header information is printed with text e-mails when they are received.  0: Prints only text mail.  1: Prints mail header information attached to text mail.  When a text mail is received with this switch On (1), the "From" address and "Subject" address are printed as header information.  When a mail with only binary data is received (a TIFF-F file, for example), this setting is ignored and no header is printed.		
1	Output from Attached Document at E-mail TX Error		

This setting determines whether only the first page or all pages of an e-mail attachment are printed at the sending station when a transmission error occurs.

This allows the customer to see which documents have not reached their intended destinations if sent to the wrong e-mail addresses, for example.

0: Prints 1st page only.

1: Prints all pages.

#### Text String for Return Receipt

This setting determines the text string output for the Return Receipt that confirms the transmission was received normally at the destination.

00: "Dispatched"

Sends from PC mail a request for a Return Receipt. Receives the Return Receipt with "dispatched" in the 2nd part:

Disposition: Automatic-action/MDN-send automatically; dispatched

The "dispatched" string is included in the Subject string.

2-3 01: "Displayed"

Sends from PC mail a request for a Return Receipt. Receives the Return Receipt with "displayed" in the 2nd part:

Disposition: Automatic-action/MDN-send automatically; displayed

The "displayed" string is included in the Subject string.

10: Reserved

11: Reserved

A mail requesting a Return Receipt sent from an IFAX with this switch set to "00" (for "dispatched") received by Microsoft Outlook 2000 may cause an error. If any setting other than "displayed" (01) causes a problem, change the setting to "01" to enable normal sending of the Return Receipt.

#### Media accept feature

This setting adds or does not add the media accept feature to the answer mail to confirm a reception.

0: Does not add the media accept feature to the answer mail

1: Adds the media accept feature to the answer mail.

Use this bit switch if a problem occurs when the machine receives an answer mail, which contains the media accept feature field.

5-6	Not Used
	Image Resolution of RX Text Mail
7	This setting determines the image resolution of the received mail.  0: 200 x 200  1: 400 x 400  The "1" setting requires installation of the Function Upgrade Card in order to have enough SAF (Store and Forward) memory to receive images at 400 x 400 resolution.

I-fax Switch 03 - Not used (do not change the settings) [ SP No. 1-102-004]

I-fax Switch 04 [SP No. 1-102-005]		
No	FUNCTION	COMMENTS
	Subject for Delivery TX/Memory	r Transfer
0	This setting determines whether the RTI/CSI registered on this machine or the RTI/CSI of the originator is used in the subject lines of transferred documents.  0: Puts the RTI/CSI of the originator in the Subject line. If this is used, either the RTI or CSI is used. Only one of these can be received for use in the subject line.  1: Puts the RTI/CSI registered on this machine in the Subject line.  When this switch is used to transfer and deliver mail to a PC, the information in the Subject line that indicates where the transmission originated can be used to determine automatically the destination folder for each e-mail.	
1	Subject corresponding to mail post database  0: Standard subject  1: Mail post database subject  The standard subject is replaced by the mail post database subject in the following three cases:  1) When the service technician sets the service (software) switch.  2) When memory sending, delivery specified by F code or SMTP reception is done.  3) With relay broadcasting (1st stage without the Schmidt 4 function).	

This switch does not apply for condition 3) when the RX system is memory sending, delivery by F-code, sending with SMTP RX and v operators are using FOL (to prevent problems when receiving trans	
2-7	

I-fax Switch 05 [SP No. 1-102-006]		
No	FUNCTION	COMMENTS
	Mail Addresses of SMTP Broadcast Recipients	
0	Determines whether the e-mail addresses of the destinations that receive transmissions broadcasted using SMTP protocol are recorded in the Journal. For example:  "1st destination + Total number of destinations: 9" in the Journal indicates a broadcast to 9 destinations.  0: Not recorded  1: Recorded	
1	I-Fax Automatic Re-dial Setting 0: OFF 1: ON	Determines whether the I-fax automatically redials when an error occurs.
2-7	Not Used	

I-fax Switch 06 - Not used (do not change the settings) [SP No. 1-102-007]

I-fax Switch 07 - Not used (do not change the settings) [SP No. 1-102-008]

I-fax Switch 08 [SP No. 1-102-009]		
No	FUNCTION	COMMENTS
0-7	Memory Threshold for POP Mail Reception	
	This setting determines the amount of SAF (Store and Forward) memory. (SAF	

stores fax messages to send later for transmission to more than one location, and also holds incoming messages if they cannot be printed.) When the amount of SAF memory available falls below this setting, mail can no longer be received; received mail is then stored on the mail server.

00-FF (0 to 1024 KB: HEX)



 The hexadecimal number you enter is multiplied by 4 KB to determine the amount of memory.

I-fax	I-fax Switch 09 [SP No. 1-102-010]		
No	FUNCTION	COMMENTS	
0-3	Not used	Do not change the settings	
4-7	Restrict TX Retries	This setting determines the number of retries when connection and transmission fails due to errors.  01-F (1-15 Hex)	

I-fax Switch 0A - Not used (do not change the settings) [SP No. 1-102-011]
I-fax Switch 0B - Not used (do not change the settings) [SP No. 1-102-012]
I-fax Switch 0C - Not used (do not change the settings) [SP No. 1-102-013]
I-fax Switch 0D - Not used (do not change the settings) [SP No. 1-102-014]
I-fax Switch 0E - Not used (do not change the settings) [SP No. 1-102-015]

I-fax	I-fax Switch 0F [SP No. 1-102-016]		
No	FUNCTION COMMENTS		
	Delivery Method for SMTP RX Files		
0	This setting determines whether files received with SMTP protocol are delivered or output immediately.		

	0: Off. Files received via SMTP are output immediately without delivery.  1: On. Files received via SMTP are delivered immediately to their destinations.
1-7	Not used

## **Printer Switches**

Print	Printer Switch 00 [SP No. 1-103-001]		
No	FUNCTION	COMMENTS	
0	Select page separation marks 0: Off 1: On	<ul> <li>0: If a 2 page RX transmission is split, [*] is printed in the bottom right corner of the 1st page and only a [2] is printed in the upper right corner of the 2nd page.</li> <li>1: If a 2 page RX transmission is split into two pages, for example, [*] [2] is printed in the bottom right corner of the 1st page and only a [2] is printed in the upper right corner of the 2nd page.</li> <li>■ This helps the user to identify pages that have been split because the size of the paper is smaller than the size of the document received. (When A5 is used to print an A4 size document, for example.)</li> </ul>	
1	Repetition of data when the received page is longer than the printer paper 0: Off 1: On	1: Default. 10 mm of the trailing edge of the previous page are repeated at the top of the next page.  0: The next page continues from where the previous page stopped without any repeated text.	
2	Prints the date and time on received fax messages 0: Disabled 1: Enabled	This switch is only effective when user parameter 02 - bit 2 (printing the received date and time on received fax messages) is enabled.  1: The machine prints the received and printed date and time at the bottom of each received	

		page.
3-7	Not used	Do not change the settings.

Print	Printer Switch 01 [SP No. 1-103-002]		
No	FUNCTION	COMMENTS	
0-2	Not used	Do not change the settings.	
3-4	Maximum print width used in the setup protocol Bit 4: 0, Bit 3: 0 = Not used Bit 4: 0, Bit 3: 1 = A3 Bit 4: 1, Bit 3: 0 = B4 Bit 4: 1, Bit 3: 1 = A4	These bits are only effective when bit 7 of printer switch 01 is "1".	
5-6	Not used	Do not change the settings.	
7	Received message width restriction in the protocol signal to the sender 0: Disabled 1: Enabled	0: The machine informs the transmitting machine of the print width depending on the paper size available from the paper feed stations.  Refer to the table on the next page for how the machine chooses the paper width used in the setup protocol (NSF/DIS).  1: The machine informs the transmitting machine of the fixed paper width which is specified by bits 3 and 4 above.	

Print	Printer Switch 02 [SP No. 1-103-003]				
No	FUNCTION	COMMENTS			
0	1st paper feed station usage for fax printing 0: Enabled 1: Disabled	<ul><li>0: The paper feed station can be used to print fax messages and reports.</li><li>1: The specified paper feed station will not be used for printing fax messages and reports.</li></ul>			
1	2nd paper feed station usage	<b>↓</b> Note			

	for fax printing 0: Enabled 1: Disabled	<ul> <li>Do not disable usage for a paper feed station which has been specified by User Parameter Switch 0F (15), or which is used for the</li> </ul>
2	3rd paper feed station usage for fax printing 0: Enabled 1: Disabled	Specified Cassette Selection feature.
3	4th paper feed station usage for fax printing 0: Enabled 1: Disabled	
4-7	Not used	Do not change the settings.

Print	Printer Switch 03 [SP No. 1-103-004]				
No	FUNCTION	COMMENTS			
0	Length reduction of received data 0: Disabled 1: Enabled	0: Incoming pages are printed without length reduction. (Page separation threshold: Printer Switch 03, bits 4 to 7) 1: Incoming page length is reduced when printing. (Maximum reducible length: Printer Switches 04, bits 0 to 4)			
1-3	Not used	Do not change the settings			
4-7	Page separation setting when sub scan compression is forbidden 00-0F (0-15 mm: Hex) Default: 6 mm	Page separation threshold (with reduction disabled with switch 03-0 above).  For example, if this setting is set to "10", and A4 is the selected paper size:  If the received document is 10 mm or less longer than A4, then the 10 mm are cut and only 1 page prints.  If the received document is 10 mm longer than A4,			

then the document is split into 2 pages
---

Printer Switch 04 [SP No. 1-103-005]							
No	FUNCTION			COMMENTS			
	Maximum reducible length when length reduction is enabled with switch 03-0 above. <maximum length="" reducible=""> = <paper length=""> + (N x 5mm)  "N" is the decimal value of the binary setting of bits 0 to 4.</paper></maximum>						
	Bit 4	Bit 3	i	Bit 2	Bit 1	Bit 0	Setting
0-4	0	0		0	0	0	0 mm
	0	0		0	0	1	5 mm
	0	0		1	0	0	20 mm
	1	1 1			1	1	155 mm
	For A5 sideways and B5 sideways paper <maximum length="" reducible=""> = <paper length=""> + 0.75 x (N x 5mm)</paper></maximum>						
5	Length of the duplicated image on the next page, when page separation has taken place.  Bit 6: 0, Bit 5: 0 = 4 mm  Bit 6: 1, Bit 5: 0 = 10 mm  Bit 6: 0, Bit 5: 1 = 15 mm  Bit 6: 1, Bit 5: 1 = <b>Not used</b>						
7	Not used.			Do not ch	nange the sett	ing.	

Printer Switch 05 - Not used (do not change the settings)

Print	Printer Switch 06 [SP No. 1-103-007]			
No	FUNCTION	COMMENTS		

0	Printing while a paper cassette is pulled out, when the Just Size Printing feature is enabled.  0: Printing will not start  1: Printing will start if another cassette has a suitable size of paper, based on the paper size selection priority tables.	Cross reference: Just size printing on/off – User switch 05, bit 5
1-7	Not used.	Do not change the settings.

Print	Printer Switch 07 [SP No. 1-103-008]				
No	FUNCTION	COMMENTS			
0-3	Not used.	Do not change the settings.			
4	List of destinations in the Communication Failure Report for broadcasting 0: All destinations 1: Only destinations where communication failure occurred	1: Only destinations where communication failure occurred are printed on the Communication Failure Report.			
5-7	Not used.	Do not change the settings.			

Printer Switch 08 - Not used (do not change the settings)		
Printer Switch 09 - Not used (do not change the settings)		
Printer Switch 0A - Not used (do not change the settings)		

Print	Printer Switch 0B [SP No. 1-103-012]			
0-2	Erase margin at the trailing	Adjusts the erase margin at the trailing edge for		

	edge for the fax printout			out	
	Bit 2	Bit 1	Bit 0	Setting	
	0	0	0	0 mm	
	0	0	1	1 mm	the fax printout.
	0	1	0	2 mm	
	0	1	1	3 mm	
	1	0	0	4 mm	
3-7	7 Not used.				Do not change the settings.

Printer Switch 0C - Not used (do not change the settings)

Printer Switch 0D - Not used (do not change the settings)

Prin	Printer Switch 0E [SP No. 1-103-015]				
No	FUNCTION	COMMENTS			
0	Paper size selection priority 0: Width 1: Length	0: A paper size that has the same width as the received data is selected first.  1: A paper size which has enough length to print all the received lines without reduction is selected first.			
1	Paper size selected for printing A4 width fax data 0: 8.5" x 11" size 1: A4 size	This switch determines which paper size is selected for printing A4 width fax data, when the machine has both A4 and 8.5" x 11" size paper.			
2	Page separation 0: Enabled 1: Disabled	1: If all paper sizes in the machine require page separation to print a received fax message, the machine does not print the message (Substitute Reception is used).  After a larger size of paper is set in a cassette, the machine automatically prints the fax message.			

3-4	Printing the sample image on reports Bit 4: 0, Bit 3: 0 = The upper half only Bit 4: 0, Bit 3: 1 = 50% reduction in sub-scan only Bit 4: 1, Bit 3: 0 = Same size Bit 4: 1, Bit 3: 1 = <b>Not used</b>	"Same size" means the sample image is printed at 100%, even if page separation occurs.  User Parameter Switch 19 (13H) bit 4 must be set to "0" to enable this switch.  Refer to Detailed Section Descriptions for more on this feature.
5-6	Not used	Do not change the settings.
	Equalizing the reduction ratio	0: When page separation has taken place, all the

Print	Printer Switch 0F [SP No. 1-103-016]		
No	FUNCTION	COMMENTS	
0-1	Smoothing feature  Bit 1: 0 Bit 0: 0 = Disabled  Bit 1: 0 Bit 0: 1 = Disabled  Bit 1: 1 Bit 0: 0 = Enabled  Bit 1: 1 Bit 0: 1 = <b>Not used</b>	(0, 0) (0, 1): Disable smoothing if the machine receives halftone images from other manufacturers fax machines frequently.	
2-7	Not used	Do not change the settings.	

# Communication Switches

Com	Communication Switch 00 [SP No. 1-104-001]		
No	FUNCTION	COMMENTS	
0-1	Compression modes available in receive mode	These bits determine the compression capabilities to be declared in phase B (handshaking) of the	

	Bit 1: 0 Bit 0: 0 = MH only Bit 1: 0 Bit 0: 1 = MH/MR Bit 1: 1 Bit 0: 0 = MH/MR/MMR Bit 1: 1 Bit 0: 1 = MH/MR/ MMR/JBIG	T.30 protocol.
2-3	Compression modes available in transmit mode Bit 3: 0 Bit 2: 0 = MH only Bit 3: 0 Bit 2: 1 = MH/MR Bit 3: 1 Bit 2: 0 = MH/MR/MMR Bit 3: 1 Bit 2: 1 = MH/MR/ MMR/JBIG	These bits determine the compression capabilities to be used in the transmission and to be declared in phase B (handshaking) of the T.30 protocol.
4	Not used	Do not change the settings.
5	JBIG compression method: Reception 0: Only basic supported 1: Basic and optional both supported	Do not change the settings.  Change the setting when communication problems occur using JBIG compression.
	JBIG compression method: Reception 0: Only basic supported 1: Basic and optional both	Change the setting when communication

Communication Switch 01 [SP No. 1-104-002]		
No	FUNCTION	COMMENTS
0	ECM 0: Off 1: On	If this bit is set to 0, ECM is switched off for all communications. In addition, V.8 protocol and JBIG compression are switched off automatically.
1-5	Not used	Do not change the setting.

6-7	Maximum printable page length available Bit 7: 0 Bit 6: 0 = No limit Bit 7: 0 Bit 6: 1 = B4 (364 mm) Bit 7: 1 Bit 6: 0 = A4 (297 mm) Bit 7: 1 Bit 6: 1 = <b>Not used</b>	The setting determined by these bits is informed to the transmitting terminal in the pre-message protocol exchange (in the DIS/NSF frames).
-----	--	---

Com	Communication Switch 02 [SP No. 1-104-003]			
No	FUNCTION		COMMENTS	
	G3 Burst error threshold	received pa send a nega threshold va	more consecutive error lines in the ge than the threshold, the machine will ative response. The Low and High alues depend on the sub-scan and are as follows.	
0	0: Low 1: High	100 dpi	6(L) ⇒ 12(H)	
		200 dpi	12(L) ⇒ 24(H)	
		300 dpi	18(L) ⇒ 36(H)	
		400 dpi	24(L) ⇒ 48(H)	
1	Acceptable total error line ratio 0: 5% 1: 10%		ine ratio for a page exceeds the ratio, RTN will be sent to the other end.	
2	Treatment of pages received with errors during G3 reception 0: Deleted from memory without printing 1: Printed	0: Pages re	ceived with errors are not printed.	
3	Hang-up decision when a negative code (RTN or PIN) is received during G3 immediate transmission	received.	page will be sent even if RTN or PIN is hine will send DCN and hang up if it TN or PIN.	

	0: No hang-up, 1: Hang-up	This bit is ignored for memory transmissions or if ECM is being used.
4-7	Not used	Do not change the settings.

Communication Switch 03 [SP No. 1-104-004]		
No	FUNCTION	COMMENTS
0-7	Maximum number of page retransmissions in a G3 memory transmission	00 - FF (Hex) times. This setting is not used if ECM is switched on. Default setting - 03(H)

Communication Switch 04 - Not used (do not change the settings)	
Communication Switch 05 - Not used (do not change the settings)	
Communication Switch 06 - Not used (do not change the settings)	
Communication Switch 07 - Not used (do not change the settings)	
Communication Switch 08 - Not used (do not change the settings)	

Communication Switch 09 [SP No. 1-104-010]		
No	FUNCTION	COMMENTS
0-7	I-Fax dial interval setting	Adjusts the interval of the I-fax dialing.  The interval of I-fax dialing is calculated by following formula.  [Interval time = specified value with this switch x 0.2 msec]

Com	Communication Switch 0A [SP No. 1-104-011]		
No	FUNCTION	COMMENTS	
0	Point of resumption of memory	0: The transmission begins from the page where	

	transmission upon redialing	transmission failed the previous time.
	0: From the error page	1: Transmission begins from the first page, using
	1: From page 1	normal memory transmission.
1-7	Not used	Do not change the settings.

**Communication Switch 0B – Not used** (do not change the settings)

Communication Switch 0C – Not used (do not change the settings)

Com	Communication Switch 0D [SP No. 1-104-014]		
No	FUNCTION	COMMENTS	
0-7	The available memory threshold, below which ringing detection (and therefore reception into memory) is disabled	00 to FF (Hex), unit = 4 kbytes (e.g., 06(H) = 24 kbytes) One page is about 24 kbytes. The machine refers to this setting before each fax reception. If the amount of remaining memory is below this threshold, the machine cannot receive any fax messages. If this setting is kept at 0, the machine will detect ringing signals and go into receive mode even if there is no memory available. This will result in communication failure.	

Communication Switch 0E [SP No. 1-104-015]		
No	FUNCTION	COMMENTS
0-7	Minimum interval between automatic dialing attempts	06 to FF (Hex), unit = 2 s (e.g., 06(H) = 12 s) This value is the minimum time that the machine waits before it dials the next destination.

Communication Switch 0F – Not used (do not change the settings.)

Com	Communication Switch 10 [SP No. 1-104-017]		
No	FUNCTION	COMMENTS	
0-7	Memory transmission: Maximum number of dialing attempts to the same destination	01 – FE (Hex) times	

Communication Switch 11 – Not used (do not change the settings.)

Communication Switch 12 [SP No. 1-104-019]		
No	FUNCTION	COMMENTS
0-7	Memory transmission: Interval between dialing attempts to the same destination	01 – FF (Hex) minutes

Communication Switch 13 – Not used (do not change the settings.)

Com	Communication Switch 14 [SP No. 1-104-021]		
No	FUNCTION	COMMENTS	
0	Inch-to-mm conversion during transmission 0: Disabled 1: Enabled	O: In immediate transmission, data scanned in inch format are transmitted without conversion.  In memory transmission, data stored in the SAF memory in mm format are transmitted without conversion.  Note: When storing the scanned data into SAF memory, the fax unit always converts the data into mm format.  1: The machine converts the scanned data or stored data in the SAF memory to the format	

		which was specified in the set-up protocol (DIS/NSF) before transmission.
1-5	Not used	Do not change the factory settings.
6-7	Available unit of resolution in which fax messages are received Bit 7: 0, Bit 6: 0 = mm Bit 7: 0, Bit 6: 1 = inch Bit 7: 1, Bit 6: 0 = mm and inch (default) Bit 7: 1, Bit 6: 1 = <b>Not used</b>	For the best performance, do not change the factory settings.  The setting determined by these bits is informed to the transmitting terminal in the pre-message protocol exchange (in the DIS/NSF frames).

Communication Switch 15 – Not used (do not change the settings)		
Communication Switch 16 – Not used (do not change the settings)		
Communication Switch 17 – Not used (do not change the settings)		
Communication Switch 18 - Not used (do not change the settings)		
Communication Switch 19 - Not used (do not change the settings)		
Communication Switch 1A - Not used (do not change the settings)		

Com	Communication Switch 1B [SP No. 1-104-028]		
No	FUNCTION	COMMENTS	
0-7	Extension access code (0 to 7) to turn V.8 protocol On/Off 0: On 1: Off	If the PABX does not support V.8/V.34 protocol procedure, set this bit to "1" to disable V.8.  Example: If "0" is the PSTN access code, set bit 0 to 1. When the machine detects "0" as the first dialed number, it automatically disables V.8 protocol. (Alternatively, if "3" is the PSTN access code, set bit 3 to 1.)	

Com	Communication Switch 1C [SP No. 1-104-029]		
No	FUNCTION	COMMENTS	
0-1	Extension access code (8 and 9) to turn V.8 protocol On/Off 0: On 1: Off	Refer to communication switch 1B.  Example: If "8" is the PSTN access code, set bit 0 to 1. When the machine detects "8" as the first dialed number, it automatically disables V.8 protocol. (If "9" is the PSTN access code, use bit 1.)	
2-7	Not used	Do not change the settings.	

Communication Switch 1D - Not used (do not change the settings)

Communication Switch 1E - Not used (do not change the settings)

Communication Switch 1F - Not used (do not change the settings)

### G3 Switches

G3 S	G3 Switch 00 [SP No. 1-105-001]		
No	FUNCTION	COMMENTS	
0 1	Monitor speaker during communication (tx and rx) Bit 1: 0, Bit 0: 0 = Disabled Bit 1: 0, Bit 0: 1 = Up to Phase B Bit 1: 1, Bit 0: 0 = All the time Bit 1: 1, Bit 0: 1 = <b>Not used</b>	<ul> <li>(0, 0): The monitor speaker is disabled all through the communication.</li> <li>(0, 1): The monitor speaker is on up to phase B in the T.30 protocol.</li> <li>(1, 0): Used for testing. The monitor speaker is on all through the communication. Make sure that you reset these bits after testing.</li> </ul>	
2	Monitor speaker during memory transmission 0: Disabled 1: Enabled	1: The monitor speaker is enabled during memory transmission.	

3-7 <b>N</b>	ot used	Do not change the settings.
--------------	---------	-----------------------------

G3 S	witch 01 [SP No. 1-105-002]	
No	FUNCTION	COMMENTS
0-1	Not used	Do not change the settings.
2-3	Not used	Do not change the settings.
4	DIS frame length 0: 10 bytes 1: 4 bytes	1: The bytes in the DIS frame after the 4th byte will not be transmitted (set to 1 if there are communication problems with PC-based faxes which cannot receive the extended DIS frames).
5	Not used	Do not change the setting.
6	Forbid CED/AMsam output 0: Off 1: On (Forbid output)	Do not change this setting (Default: 0: Off), unless communication problem is caused by a CED or ANSam transmission.
7	Not used	Do not change the setting.

G3 S	Switch 02 [SP No. 1-105-003]	
No	FUNCTION	COMMENTS
0	G3 protocol mode used 0: Standard and non-standard 1: Standard only	Change this bit to 1 only when the other end can only communicate with machines that send T.30-standard frames only.  1: Disables NSF/NSS signals (these are used in non-standard mode communication)
1-6	Not used	Do not change the settings.
7	Short preamble 0: Disabled 1: Enabled	Refer to Appendix B in the Group 3 Facsimile  Manual for details about Short Preamble.

# G3 Switch 03 [SP No. 1-105-004]

No	FUNCTION	COMMENTS
0	DIS detection number (Echo countermeasure) 0: 1 1: 2	O: The machine will hang up if it receives the same DIS frame twice.  1: Before sending DCS, the machine will wait for the second DIS which is caused by echo on the line.
1	Not Used	Do not change the settings.
2	V.8 protocol 0: Disabled 1: Enabled	0: V.8/V.34 communications will not be possible.  Note:  Do not set to 0 unless the line condition is always bad enough to slow down the data rate to 14.4 kbps or lower.
3	ECM frame size 0: 256 bytes 1: 64 bytes	Keep this bit at "0" in most cases.
4	CTC transmission conditions 0: After one PPR signal received 1: After four PPR signals received (ITU-T standard)	0: When using ECM in non-standard (NSF/NSS) mode, the machine sends a CTC to drop back the modem rate after receiving a PPR, if the following condition is met in communications at 14.4, 12.0, 9.6, and 7.2 kbps.  ✓ NTransmit ≤ NResend  NTransmit- Number of transmitted frames NResend- Number of frames to be retransmitted 1: When using ECM, the machine sends a CTC to drop back the modem rate after receiving four PPRs.  PPR, CTC: These are ECM protocol signals. This bit is not effective in V.34 communications.
5	Modem rate used for the next page after receiving a negative code (RTN or PIN)	1: The machine's tx modem rate will fall back before sending the next page if a negative code is received. This bit is ignored if ECM is being used.

	0: No change 1: Fallback	
6	Not Used	Do not change the settings
7	Select detection of reverse polarity in ringing 0: Off 1: On	This switch is used to prevent reverse polarity in ringing on the phone line (applied to PSTN-G3 ringing). Do not change this setting  0: No detection ⇒ Outside Japan  1: Detection ⇒ Inside Japan only

G3 S	G3 Switch 04 [SP No. 1-105-005]						
No	FUNCTION	COMMENTS					
0-3	Training error detection threshold	0 - F (Hex); 0 - 15 bits  If the number of error bits in the received TCF is below this threshold, the machine informs the sender that training has succeeded.					
4-7	Not used	Do not change the settings.					

G3 S	witch	05 [SF	P No. 1	-105-0	06]	
No	FUNC	CTION				COMMENTS
0-3	3 Initial Tx modem rate					These bits set the initial starting modem rate for
	Bit 3	Bit 2	Bit 1	Bit 0	bps	transmission.  Use the dedicated transmission parameters if
	0	0	0	1	2.4k	If a modem rate 14.4 kbps or slower is selected.
	0	0	1	0	4.8k	
	0	0	1	1	7.2k	Cross reference:
	0	1	0	0	9.6k	V.8 protocol on/off - G3 switch 03, bit2
	0	1	0	1	12.0k	
	0	1	1	0	14.4k	

	0	1	1	1	16.8k	
	1	0	0	0	19.2k	
	1	0	0	1	21.6k	
	1	0	1	0	24.0k	
	1	0	1	1	26.4k	
	1	1	0	0	28.8k	
	1	1	0	1	31.2k	
	1	1	1	0	33.6k	
	Other	settin	gs - No	ot used	t	
4-5	7.2 kt Bit 5: Bit 5: Bit 5:	moder ops. 0, Bit 4 0, Bit 4 1, Bit 4	4: 0 = \ 4: 1 = \ 4: 0 = \	V.29 V.17 V.34		These bits set the initial modem type for 9.6 and 7.2 kbps, if the initial modem rate is set at these speeds.
6-7	Not u	sed				Do not change the settings.

G3 S	witch	06 [SF	P No. 1	-105-0		
No			FUN	CTION		COMMENTS
0-3	Initial	Tx mo	dem ra	ate		These bits set the initial starting modem
	Bit 3	Bit 2	Bit 1	Bit 0	Bps	rate for reception.  Use a lower setting if high speeds pose
	0	0	0	1	2.4k	problems during reception.  If a modem rate 14.4 kbps or slower is selected, V.8 protocol should be disabled manually.
	0	0	1	0	4.8k	
	0	0	1	1	7.2k	
	0	1	0	0	9.6k	Cross reference:

	0	1	0	1	12.0k	V.8 protocol on/off - G3 switch 03, bit2
	0	1	1	0	14.4k	
	0	1	1	1	16.8k	
	1	0	0	0	19.2k	
	1	0	0	1	21.6k	
	1	0	1	0	24.0k	
	1	0	1	1	26.4k	
	1	1	0	0	28.8k	
	1	1	0	1	31.2k	
	1	1	1	0	33.6k	
	Other settings - Not used				ı	
	Mode	m type	s avail	able fo	or reception	<ul> <li>The setting of these bits is used to inform the transmitting terminal of the available modem type for the machine in receive mode.</li> <li>If V.34 is not selected, V.8 protocol must be disabled manually.</li> </ul>
	Bit 7	Bit 6	Bit 5	Bit 4	Setting	
	0	0	0	1	V.27ter	
	0	0	1	0	V.27ter, V.29	
	0	0	1	1	V.27ter, V.29, V.33	Cross reference: V.8 protocol on/off - G3 switch 03, bit2
4-7	0	1	0	0	V.27ter, V.29, V.17/V.33	
	0	1	0	1	V.27ter, V.29, V.17/V33, V.34	
	Other	settino	gs - No	t used	Í	

G3 S	witch 07 [SP No. 1-105-008]	
No	FUNCTION	COMMENTS
0-1	PSTN cable equalizer (tx mode: Internal) Bit 1: 0, Bit 0: 0 = None Bit 1: 0, Bit 0: 1 = Low Bit 1: 1, Bit 0: 0 = Medium Bit 1: 1, Bit 0: 1 = High	Use a higher setting if there is signal loss at higher frequencies because of the length of wire between the modem and the telephone exchange.  Use the dedicated transmission parameters for specific receivers.  Also, try using the cable equalizer if one or more of the following symptoms occurs.  Communication error  Modem rate fallback occurs frequently.  This setting is not effective in V.34 communications.
2-3	PSTN cable equalizer (rx mode: Internal) Bit 3: 0, Bit 2: 0 = None Bit 3: 0, Bit 2: 1 = Low Bit 3: 1, Bit 2: 0 = Medium Bit 3: 1, Bit 2: 1 = High	Use a higher setting if there is signal loss at higher frequencies because of the length of wire between the modem and the telephone exchange.  Also, try using the cable equalizer if one or more of the following symptoms occurs.  Communication error with error codes such as 0-20, 0-23, etc.  Modem rate fallback occurs frequently.  Note  This setting is not effective in V.34 communications.
4	PSTN cable equalizer (V.8/V.17 rx mode: External) 0: Disabled 1: Enabled	Keep this bit at "1".
5	Not used	Do not change the settings.
6	Parameter selection for dial tone detection	0: This uses the fixed table in the ROM for dial tone detection.

	Normal parameter     Specific parameter	1: This uses the specific parameter adjusted with SRAM (69ECBEH - 69ECDEH). Select this if the dial tone cannot be detected when the "Normal parameter: 0" is selected.
7	Not used	Do not change the settings.

G3 Switch 08 - Not used (do not change the settings)

G3 Switch 09 - Not used (do not change the settings)

G3 Sv	G3 Switch 0A [SP No. 1-105-011]						
No	FUNCTION	COMMENTS					
0-1	Maximum allowable carrier drop during image data reception Bit 1: 0, Bit 0: 0 = 200 Bit 1: 0, Bit 0: 1 = 400 Bit 1: 1, Bit 0: 0 = 800 Bit 1: 1, Bit 0: 1 = <b>Not used</b>	These bits set the acceptable modem carrier drop time.  Try using a longer setting if error code 0-22 is frequent.					
2	Select cancellation of high-speed RX if carrier signal lost while receiving 0: Off 1: On	This switch setting determines if high-speed receiving ends if the carrier signal is lost when receiving during non-ECM mode					
3	Not used	Do not change the settings					
4	Maximum allowable frame interval during image data reception.  0: 5 s 1: 13 s	This bit set the maximum interval between EOL (end-of-line) signals and the maximum interval between ECM frames from the other end.  Try using a longer setting if error code 0-21 is frequent.					
5	Not used	Do not change the settings.					

6	Reconstruction time for the first line in receive mode 0: 6 s 1: 12 s	When the sending terminal is controlled by a computer, there may be a delay in receiving page data after the local machine accepts set-up data and sends CFR. This is outside the T.30 recommendation. But, if this delay occurs, set this bit to 1 to give the sending machine more time to send data.  Refer to error code 0-20.  ITU-T T.30 recommendation: The first line should come within 5 s of CFR.
7	Not used	Do not change the settings.

G3 Switch 0B Not used (do not change the settings).

G3 Switch 0C Not used (do not change the settings).

G3 Switch 0D Not used (do not change the settings).

G3 S	G3 Switch 0E [SP No 1-105-015]			
	Set CNG send time interval  Some machines on the receiving side may not be able to automatically switch the  3-second CNG interval.			
0-7 High order bit 3000-2250ms: 3000-50xNms 3000 – 50 x Nms 0F (3000 ms)		3000-2250ms: 3000-50xNms 3000 − 50 x Nms 0F (3000 ms) ≤ N ≤ FF (2250 ms)		
	Low order bit	00-0E(3000-3700ms: 3000+50xNms 3000 − 50 x Nms 0F (3000 ms) ≤ N ≤ 0F (3700 ms)		

G3 S	G3 Switch 0F [SP No. 1-105-016]				
No	FUNCTION	COMMENTS			
0	Alarm when an error occurred in Phase C or later	If the customer wants to hear an alarm after each error communication, change this bit to "1".			

	0: Disabled 1: Enabled	
1	Alarm when the handset is off-hook at the end of communication 0: Disabled 1: Enabled	If the customer wants to hear an alarm if the handset is off-hook at the end of fax communication, change this bit to "1".
2-7	Not used	Do not change the settings.

### IP Fax Switches

IP Fax	IP Fax Switch 00 [SP No. 1-111-001]				
No.	FUNCTION	COMMENTS			
0	Not used	Do not change this setting.			
1	IP Fax Transport 0: TCP, 1: UDP	Selects TCP or UDP protocol for IP-Fax			
2	IP Fax single port selection 0: OFF, 1: ON (enable)  Selects single data port.				
3	IP Fax double ports (single data port) selection 0: OFF, 1: ON (enable)	Selects whether IP-Fax uses a double port.			
4	IP Fax Gatekeeper 0: OFF, 1: ON (enable)	Enables/disables the communication via the gatekeeper for IP-Fax.			
5	IP Fax T30 bit signal reverse 0: LSB first, 1: MSB first	Reverses the T30 bit signal.			
6	IP Fax max bit rate setting 0: Not affected, 1: Affected	When "0" is selected, the max bit rate does not affect the value of the DIS/DCS. When "1" is selected, the max bit rate affects the value of the DIS/DCS.			

7	IP Fax received telephone number confirmation 0: No confirmation, 1: Confirmation	When "0" is selected, fax data is received without checking the telephone number. When "1" is selected, fax data is received only when confirming that the telephone number from the sender matches the registered telephone number in this
	Confirmation	registered telephone number in this machine. If this confirmation fails, the line is
		disconnected.

IP-Fax Switch 01							
No.			FUNC	TION		COMMENTS	
	Select IP FAX Delay Level					Raise the level by selecting a higher setting	
	Bit3	Bit2	Bit1	Bit0	Setting	if too many transmission errors are occurring on the network.	
	0	0	0	0	Level 0	If TCP/UDP is enabled on the network, raise	
0-3	0	0	0	1	Level 1	this setting on the T.30 machine. Increasing the delay time allows the recovery of more	
	0	0	1	0	Level 2	lost packets.	
	0	0	1	1	Level 3	If only UDP is enabled, increase the number of redundant packets.	
						Level 1~2: 3 Redundant packets Level 3: 4 Redundant packets	
4-7	IP Fa	x prea	mble w	ait tim	Selects the preamble wait time.  [00 to 0f]  There are 16 values in this 4-bit binary switch combination.  Waiting time: set value level x 100 ms  Max: 0f (1500 ms) Min: 00 (No wait time)  The default is "0000" (00H).		

IP Fax Switch 02 [SP No. 1-111-003]			
No.	FUNCTION	COMMENTS	

0	IP Fax bit signal reverse setting 0: Maker code setting 1: Internal bit switch setting	When "0" is selected, the bit signal reverse method is decided by the maker code. When "1" is selected, the bit signal reverse method is decided by the internal bit switch. When communicating between IP Fax devices, LSB first is selected.)
1	IP Fax transmission speed setting 0: Modem speed 1: No limitation	Selects the transmit speed for IP Fax communication.
2	SIP transport setting 0: TCP 1: UDP	This bit switch sets the transport that has priority for receiving IP Fax data.  This function is activated only when the sender has both TCP and UDP.
3	CCM connection 0: No CCM connection 1: CCM connection	When "1" is selected, only the connection call message with H.323 or no tunneled H.245 is transmitted via CCM.
4	Message reception selection from non-registered SIP server 0: Answer 1: Not answer	O: This answers the INVITE message from the SIP server not registered for the machine.  1: This does not receive the INVITE message from the SIP server not registered for the machine and send a refusal message.
5	ECM communication setting 0: No limit for image compression 1: Limit for image compression	O: This does not limit the type of the image compression with ECM communication.  1: When the other end machine is Ciscco, this permits the image compression other than JBIG or MMR with ECM communication.
6-7	Not used	Do not change these settings.

IP Fax	IP Fax Switch 03 [SP No. 1-111-004]			
No.	FUNCTION	COMMENTS		
0	Effective field limitation for G3 standard function information 0: OFF, 1: 4byte (DIS)	Limits the effective field for standard G3 function information.		
1	Switching between G3 standard and G3 non standard  0: Enable switching  1: G3 standard only	Enables/disables switching between G3 standard and G3 non-standard.		
2	Not used.	Do not change this setting.		
3	ECM frame size selection at transmitting 0: 256byte, 1: 64byte	Selects the ECM frame size for sending.		
4	DIS detection times for echo prevention 0: 1 time, 1: 2 times	Sets the number of times for DIS to detect echoes.		
5	CTC transmission selection 0: PPRx1 1: PPRx4	When "0" is selected, the transmission condition is decided by error frame numbers. When "1" is selected, the transmission condition is based on the ITU-T method.		
6	Shift down setting at receiving negative code 0: OFF, 1: ON	Selects whether to shift down when negative codes are received.		
7	Not used	Do not change this setting.		

IP Fax Switch 04 [SP No. 1-111-005]				
No.	FUNCTION	COMMENTS		
0	TCF error threshold	Sets the TCF error threshold level.		
1		[00 to 0f]		

2		The default is "1111" (0fH).
3		
4-7	Not used	Do not change these settings.

IP Fax Switch 05 [SP No. 1-111-006]							
No.	F	JNCTION		COMMENTS			
	Modem bit rate setting for transmission  Sets the modem bit rate for transmission. The default is "0110" (14.4K bps).						
	Bit 4	Bit 3	Bit	2	Bit 1		
	0	0	0		1	2400 bps	
	0	0	1		1	4800 bps	
	0	0	1		1	7200 bps	
	0	1	0		0	9600 bps	
	0	1	0		1	12.0 Kbps	
0-3	0	1	1		0	14.4 Kbps	
	0	1	1		1	16.8 Kbps	
	1	0	0		0	19.2 Kbps	
	1	0	0		1	21.6 Kbps	
	1	0	1		0	24.0 Kbps	
	1	0	1		1	26.4 Kbps	
	1	1	0		0	28.8 Kbps	
	1	1	0		1	31.2 Kbps	
	1	1	1		0	33.6 Kbps	
4-5	Modem setting for transmission						

Sets the modem for transmission.

The default is "00" (V29).

Bit 5: 0, Bit 4: 0 = V29

Bit 5: 0, Bit 4: 1 = V17

Bit 5: 1, Bit 4: 0 = V34\*

Bit 5: 1, Bit 4: 1 = **Not used** 

\*V34 is not supported for IP-Fax communication.

6-7 **Not used** 

Do not change these settings.

IP Fax Switch 06 [SP No. 1-111-007]							
No.	FUNCTION			COMMENTS			
0-3	Modem bit rate setting for reception  Sets the modem bit rate for reception. The default is "0110" (14.4K bps).						
	Bit 3	Bit 2		Bit 1	Bit 0		
	0	0		0	1	2400 bps	
	0	0		1	0	4800 bps	
	0	0		1	1	7200 bps	
	0	1		0	0	9600 bps	
	0	1		0	1	12.0 Kbps	
	0	1		1	0	14.4 Kbps	
	0	1		1	1	16.8 Kbps	
	1	0		0	0	19.2 Kbps	
	1	0		0	1	21.6 Kbps	
	1	0		1	0	24.0 Kbps	
	1	1 0		1	1	26.4 Kbps	
	1	1		0	0	28.8 Kbps	

	1	1	0	1	31.2 Kbps				
	1	1	1	0	33.6 Kbps				
	Modem setting for reception Sets the modem type for reception. The default is "0100" (V27ter, V29, V17).								
	Bit 7	Bit 6	Bit 5	Bit 4					
	0	0	0	1	V27ter				
	0	0	1	0	V27ter, V29				
4-7	0	0	1	1	V27ter, V29, V33 (invalid)				
	0	1	0	0	V27ter, V29, V17				
	0	1	0	0 1 V27ter, V29					
I	*V34 is not supported for IP-Fax communication.								

IP Fax	IP Fax Switch 07 [SP No. 1-111-008]						
No.	FUNCTION	COMMENTS					
0	TSI information 0: Not added, 1: Added	Adds or does not add TSI information to NSS(S).					
1	DCN transmission setting at T1 timeout 0: Not transmitted, 1: Transmitted	Transmits or does not transmit DCN at T1 timeout.					
2	Not used	Do not change this setting.					
3	Hang up setting at DIS reception disabled 0: No hang up 1: Hang up after transmitting DCN	Sets whether the machine disconnects after DIS reception.					

4	Number of times for training 0: 1 time, 1: 2 times	Selects the number of times training is done at the same bit rate.
5	Space CSI transmission setting at no CSI registration 0: Not transmitted, 1: Transmitted	When "0" is selected, frame data is enabled. When "1" is selected, the transmitted data is all spaces.
6-7	Not used	Do not change these settings.

	IP Fax Switch 08 [SP No. 1-111-009]					
No.	FUNCTION	COMMENTS				
0-1	T1 timer adjustment Adjusts the T1 timer. The default is "00" (35 seconds). Bit 1: 0, Bit 0: 0 = 35 sec Bit 1: 0, Bit 0: 1 = 40 sec Bit 1: 1, Bit 0: 0 = 50 sec Bit 1: 1, Bit 0: 1 = 60 sec	-				
2-3	T4 timer adjustment Adjust the T4 timer. The default is "00" (3 seconds). Bit 3: 0, Bit 2: 0 = 3 sec Bit 3: 0, Bit 2: 1 = 3.5 sec Bit 3: 1, Bit 2: 0 = 4 sec Bit 3: 1, Bit 2: 1 = 5 sec	-				
4-5	T0 timer adjustment Bit 5: 0, Bit 4: 0 = 75 sec Bit 5: 0, Bit 4: 1 = 120 sec Bit 5: 1, Bit 4: 0 = 180 sec Bit 5: 1, Bit 4: 1 = 240 sec	Adjusts the fail safe timer. This timer sets the interval between "setup" data transmission and T.38 phase decision. If your destination return is late on the network or G3 fax return is late, adjust the longer interval timer. The default is "00" (75 seconds).				
6-7	Not used	Do not change these settings.				

## **NCU Parameters**

The following tables give the RAM addresses and the parameter calculation units that the machine uses for ringing signal detection and automatic dialing. The factory settings for each country are also given. Most of these must be changed by RAM read/write (SP2-102), but some can be changed using NCU Parameter programming (SP2-103, 104 and 105); if SP2-103, 104 and 105 can be used, this will be indicated in the Remarks column. The RAM is programmed in hex code unless (BCD) is included in the Unit column.



- The following addresses describe settings for the standard NCU.
- Change the fourth digit from "5" to "6" (e.g. 680500 to 680600) for the settings for the first optional G3 interface unit and from "5" to "7" (e.g. 680700) for the settings for the second optional G3 interface unit.

Address	Function							
680500	Country/Area code for NCU parameters							
		. ,		ntry/area code o	•			
	Country /Area	Decimal	Hex	Country /Area	Decimal	Hex		
	France	00	00	USA	17	11		
	Germany	01	01	Asia	18	12		
	UK	02	02	Hong Kong	20	14		
	Italy	03	03	South Africa	21	15		
	Austria	04	04	Australia	22	16		
	Belgium	05	05	New Zealand	26	17		
	Denmark	06	06	Singapore	24	18		
	Finland	07	07	Malaysia	25	19		
	Ireland	08	08	China	26	1A		

Address	Function						
	Norway	09	09	Taiwan	27	1B	
	Sweden	10	0A	Korea	28	1C	
	Switzerland	11	0B	Turkey	32	20	
	Portugal	12	0C	Greece	33	21	
	Holland	13	0D	Hungary	34	22	
	Spain	14	0E	Czech	35	23	
	Israel	15	0F	Poland	36	24	

Address	Function	Unit	Remarks	
680501	Line current detection time		Line current detection is	
680502	Line current wait time	20 ms	disabled. Line current is not	
680503	Line current drop detect time		detected if 680501 contains FF.	
680504	PSTN dial tone frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680505	PSTN dial tone frequency upper limit (low byte)	(= 0 = )	detection is disabled.	
680506	PSTN dial tone frequency lower limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680507	PSTN dial tone frequency lower limit (low byte)	(505)	detection is disabled.	
680508	PSTN dial tone detection time	20 ms	If 680508 contains	
680509	PSTN dial tone reset time (LOW)		FF(H), the machine pauses for the pause	
68050A	PSTN dial tone reset time (HIGH)		time (address 68050D /	

Address	Function	Unit	Remarks	
68050B	PSTN dial tone continuous tone time		68050E). Italy: See Note 2.	
68050C	PSTN dial tone permissible drop time			
68050D	PSTN wait interval (LOW)		_	
68050E	PSTN wait interval (HIGH)			
68050F	PSTN ring-back tone detection time	20 ms	Detection is disabled if this contains FF.	
680510	PSTN ring-back tone off detection time	20 ms	-	
680511	PSTN detection time for silent period after ring-back tone detected (LOW)	20 ms	-	
680512	PSTN detection time for silent period after ring-back tone detected (HIGH)	20 ms	-	
680513	PSTN busy tone frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680514	PSTN busy tone frequency upper limit (low byte)	112 (333)	detection is disabled.	
680515	PSTN busy tone frequency lower limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680516	PSTN busy tone frequency lower limit (low byte)	, 12 (505)	detection is disabled.	
680517	PABX dial tone frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680518	PABX dial tone frequency upper		detection is disabled.	

Address	Function	Unit	Remarks	
	limit (low byte)			
680519	PABX dial tone frequency lower limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
68051A	PABX dial tone frequency lower limit (low byte)		detection is disabled.	
68051B	PABX dial tone detection time			
68051C	PABX dial tone reset time (LOW)		W 000745	
68051D	PABX dial tone reset time (HIGH)		If 68051B contains FF, the machine pauses for	
68051E	PABX dial tone continuous tone time	20 ms	the pause time (680520 / 680521).	
68051F	PABX dial tone permissible drop time			
680520	PABX wait interval (LOW)		_	
680521	PABX wait interval (HIGH)			
680522	PABX ringback tone detection time	20 ms	If both addresses	
680523	PABX ringback tone off detection time	20 ms	contain FF(H), tone detection is disabled.	
680524	PABX detection time for silent period after ringback tone detected (LOW)	20 ms	If both addresses	
680525	PABX detection time for silent period after ringback tone detected (HIGH)	20 ms	detection is disabled.	
680526	PABX busy tone frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680527	PABX busy tone frequency upper		detection is disabled.	

Address	Function	Unit	Remarks			
	limit (low byte)					
680528	PABX busy tone frequency lower limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone			
680529	PABX busy tone frequency lower limit (low byte)	(= 0 = )	detection is disabled.			
68052A	Busy tone ON time: range 1					
68052B	Busy tone OFF time: range 1					
68052C	Busy tone ON time: range 2	20 ms				
68052D	Busy tone OFF time: range 2					
68052E	Busy tone ON time: range 3	-				
68052F	Busy tone OFF time: range 3					
680530	Busy tone ON time: range 4					
680531	Busy tone OFF time: range 4	20 ms				
680532	Busy tone continuous tone detection time					
680533	Busy tone signal state time tolerance for all ranges, and number of cycles required for detection (a setting of 4 cycles means that ON-OFF-ON or OFF-ON-OFF must be detected twice).  Tolerance (±)  Bit 1: 0, Bit 0: 0 = 75% Bits 2 and 3 must always be kept at 0.  Bit 1: 0, Bit 0: 0 = 50% Bits 2 and 3 must always be kept at 0.  Bit 1: 0, Bit 0: 0 = 25%  Bit 1: 0, Bit 0: 0 = 12.5%  Bits 7, 6, 5, 4 - number of cycles required for cadence detection					
680534	International dial tone frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone			
680535	International dial tone frequency		detection is disabled.			

Address	Function	Unit	Remarks	
	upper limit (low byte)			
680536	International dial tone frequency lower limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
680537	International dial tone frequency lower limit (low byte)	detection is disabled.		
680538	International dial tone detection time			
680539	International dial tone reset time (LOW)		If 680538 contains FF,	
68053A	International dial tone reset time (HIGH)		the machine pauses for the pause time (68053D / 68053E).	
68053B	International dial tone continuous tone time	20 ms	Belgium: See Note 2.	
68053C	International dial tone permissible drop time			
68053D	International dial wait interval (LOW)		_	
68053E	International dial wait interval (HIGH)			
68053F	Country dial tone upper frequency limit (HIGH)		If both addresses	
680540	Country dial tone upper frequency limit (LOW)	Hz (BCD)	contain FF(H), tone detection is disabled.	
680541	Country dial tone lower frequency limit (HIGH)	(555)	If both addresses contain FF(H), tone	
680542	Country dial tone lower frequency limit (LOW)		detection is disabled.	

Address	Function	Unit	Remarks
680543 680544 680545	Country dial tone detection time  Country dial tone reset time (LOW)  Country dial tone reset time (HIGH)	20 ms	If 680543 contains FF, the machine pauses for the pause time (680548 / 680549).
680546	Country dial tone continuous tone time	-	-
680547	Country dial tone permissible drop time	20 ma	
680548	Country dial wait interval (LOW)	20 ms	-
680549	Country dial wait interval (HIGH)		
68054A	Time between opening or closing the DO relay and opening the OHDI relay	1 ms	See Notes 3, 6 and 8. SP2-103-012 (parameter 11).
68054B	Break time for pulse dialing	1 ms	See Note 3. SP2-103-013 (parameter 12).
68054C	Make time for pulse dialing	1 ms	See Note 3. SP2-103-014 (parameter 13).
68054D	Time between final OHDI relay closure and DO relay opening or closing	1 ms	See Notes 3, 6 and 8. SP2-103-015 (parameter 14). This parameter is only valid in Europe.
68054E	Minimum pause between dialed digits (pulse dial mode)	20 ms	See Note 3 and 8. SP2-103-016 (parameter 15).
68054F	Time waited when a pause is entered at the operation panel		SP2-103-017 (parameter 16). See

Address	Function	Unit	Remarks
			Note 3.
680550	DTMF tone on time	.1 ms	SP2-103-018 (parameter 17).
680551	DTMF tone off time		SP2-103-019 (parameter 18).
680552	Tone attenuation level of DTMF signals while dialing	-N x 0.5 -3.5 dBm	SP2-103-020 (parameter 19). See Note 5.
680553	Tone attenuation value difference between high frequency tone and low frequency tone in DTMF signals	-dBm x 0.5	SP2-103-021 (parameter 20). The setting must be less than –5dBm, and should not exceed the setting at 680552h above. See Note 5.
680554	PSTN: DTMF tone attenuation level after dialling	-N x 0.5 -3.5 dBm	SP2-103-022 (parameter 21). See Note 5.
680555	ISDN: DTMF tone attenuation level after dialling	-dBm x 0.5	See Note 5
680556	Not used	-	Do not change the settings.
680557	Time between 68054Dh (NCU parameter 14) and 68054Eh (NCU parameter 15)	1 ms	This parameter takes effect when the country code is set to France.
680558	Not used	-	Do not change the setting.
680559	Grounding time (ground start mode)	20 ms	The Gs relay is closed for this interval.

Address	Function	Unit	Remarks	
68055A	Break time (flash start mode)	1 ms The OHDI relay is optor this interval.		
68055B	International dial access code (High)	BCD	For a code of 100: 68055B - F1	
68055C	International dial access code (Low)		68055C - 00	
68055D	PSTN access pause time	20 ms	This time is waited for each pause input after the PSTN access code. If this address contains FF[H], the pause time stored in address 68054F is used. Do not set a number more than 7 in the UK.	
68055E	Progress tone detection level, and cadence detection enable flags	Bit 7: 0, Bit 6: 0, Bit 5: 0 = -25.0 dBm Bit 7: 0, Bit 6: 0, Bit 5: 1 = -35.0 dBm Bit 7: 0, Bit 6: 1, Bit 5: 0 = -30.0 dBm Bit 7: 1, Bit 6: 0, Bit 5: 0 = -40.0 dBm Bit 7: 1, Bit 6: 1, Bit 5: 0 = -49.0 dBm Bits 2, 0 - See Note 2.		
68055F To 680564	Not used	-	Do not change the settings.	
680565	Long distance call prefix (HIGH)	BCD	For a code of 0:	
680566	Long distance call prefix (LOW)	BCD	680565 – FF 680566 - FF	
680567 to 680571	Not used	-	Do not change the settings.	
680572	Acceptable ringing signal	1000/ N	SP2-103-003	

Address	Function	Unit	Remarks
	frequency: range 1, upper limit		(parameter 02).
680573	Acceptable ringing signal frequency: range 1, lower limit		SP2-103-004 (parameter 03).
680574	Acceptable ringing signal frequency: range 2, upper limit	(Hz).	SP2-103-005 (parameter 04).
680575	Acceptable ringing signal frequency: range 2, lower limit		SP2-103-006 (parameter 05).
680576	Number of rings until a call is detected	1	SP2-103-007 (parameter 06). The setting must not be zero.
680577	Minimum required length of the first ring	20 ms	See Note 4. SP2-103-008 (parameter 07).
680578	Minimum required length of the second and subsequent rings	20 ms	SP2-103-009 (parameter 08).
680579	Ringing signal detection reset time (LOW)	20 ms	SP2-103-010 (parameter 09).
68057A	Ringing signal detection reset time (HIGH)	20 1113	SP2-103-011 (parameter 10).
68057B to 680580	Not used	-	Do not change the settings.
680581	Interval between dialing the last digit and switching the Oh relay over to the external telephone when dialing from the operation panel in handset mode.	20 ms	Factory setting: 500 ms

Address	Function	Unit	Remarks		
680582	Bits 0 and 1 - Handset off-hook detect Bit 1:0, Bit 0: 0 = 200 ms Bit 1:0, Bit 0: 1 = 800 ms Other Not used Bits 2 and 3 - Handset on-hook detect Bit 3: 0, Bit 2: 0 = 200 ms Bit 3: 0, Bit 2: 1 = 800 ms Other Not used Bits 4 to 7 - <b>Not used</b>	-			
680583 To 6805A0	Not used	Do not change the settings.			
6805A1	Acceptable CED detection frequency upper limit (high byte)	BCD (Hz)	If both addresses contain FF(H), tone		
6805A2	Acceptable CED detection frequency upper limit (low byte)	e CED detection			
6805A3	Acceptable CED detection frequency lower limit (high byte)	BCD (Hz)	If both addresses contain FF(H), tone		
6805A4	Acceptable CED detection frequency lower limit (low byte)	1000 (112)	detection is disabled.		
6805A5	CED detection time	20 ms ± 20 ms	Factory setting: 200 ms		
6805A6	Acceptable CNG detection frequency upper limit (high byte)	BCD (Hz)	If both addresses contain FF(H), tone		
6805A7	Acceptable CNG detection frequency upper limit (low byte)	detection is disabled.			
6805A8	Acceptable CNG detection frequency lower limit (high byte)	BCD (Hz)	If both addresses contain FF(H), tone		
6805A9	Acceptable CNG detection		detection is disabled.		

Address	Function	Unit	Remarks	
	frequency lower limit (low byte)			
6805AA	Not used	-	Do not change the setting.	
6805AB	CNG on time	20 ms	Factory setting: 500 ms	
6805AC	CNG off time	20 ms	Factory setting: 3000 ms	
6805AD	Number of CNG cycles required for detection	-	The data is coded in the same way as address 680533.	
6805AE	Not used	-	Do not change the settings.	
6805AF	Acceptable AI short protocol tone (800Hz) detection frequency upper limit (high byte)	Hz (BCD)	If both addresses contain FF(H), tone	
6805B0	Acceptable AI short protocol tone (800Hz) detection frequency upper limit (low byte)	(305)	detection is disabled.	
6805B1	Acceptable AI short protocol tone (800Hz) detection frequency lower limit (high byte)	Hz(BCD)	If both addresses contain FF(H), tone	
6805B2	Acceptable AI short protocol tone (800Hz) detection frequency lower limit (low byte)	(000)	detection is disabled.	
6805B3	Detection time for 800 Hz Al short protocol tone	20 ms	Factory setting: 360 ms	
6805B4	PSTN: Tx level from the modem	-N – 3 dBm	SP2-103-002 (parameter 01).	
6805B5	PSTN: 1100 Hz tone transmission level	- N 6805B4 - See Note 7.	0.5N 6805B5 –3.5 (dB)	

Address	Function	Unit	Remarks				
6805B6	PSTN: 2100 Hz tone transmission level	- N6805B4 - 0.5N 6805B6 -3 (dB) See Note 7.					
6805B7	PABX: Tx level from the modem	- dBm	-				
6805B8	PABX: 1100 Hz tone transmission level	- N 6805B7 -	0.5N 6805B8 (dB)				
6805B9	PABX: 2100 Hz tone transmission level	- N 6805B7 -	0.5N 6805B9 (dB)				
6805BD	Modem turn-on level (incoming signal detection level)	-37-0.5N (dBm)	-				
6805BE to 6805C6	Not used	-	Do not change the settings.				
6805C7	Bits 0 to 3 – <b>Not used</b> Bit 4 = V.34 protocol dump 0: Simple, 1: Detailed (default) Bits 5 to 7 – <b>Not used.</b>						
6805C8 to 6805D9	Not used	-	Do not change the settings.				
6805DA	T.30 T1 timer	1 s					
6805E0 bit 3	Maximum wait time for post message	0: 12 s 1: 30 s	1: Maximum wait time for post message (EOP/EOM/MPS) can be changed to 30 s. Change this bit to "1" if communication errors occur frequently during V.17 reception.				
6805E3	Voltage setting to detect off-hook for voltage/DP detection for an	0: Auto	Do not change these settings				

113

Address		F	unction	1			Unit		Remarks
	externally connected line.								
	Here is a summary of the fixed voltage settings (1: Fixed) for an externally connected line.								
	Bit 7	Bit 6	Bit 5	Bit	4	-			
	0	0	0	0		Not	used		
	0	0	0	1		2.7	5 V		
	0	0	1	0		5.5	V		
	1	0	0	0		22 \	V		
	1	1	1	1		41.2	25 V		
	Bit 1 sets the level of the call signal, Bit 3			Bit 1 1		0	RT=0 (Low	<u>'</u> )	
						1	RT=1 (High	า)	
6805E4	sets the	e call sig		nal		0	RZ=0 (High	า)	0:, 1:
	impedance		Bit 3		1	RZ=1 (Composite	e)		
6805E5	Bit 0 se	ets the ri	ng	Bit 0		0	Auto		If any setting is changed,
		etection method, Bit sets the ring		Ū	1	Fixed		select a setting that is higher than the default	
	detection method		Bit 1		0	Use RDTP		setting.	
	when fixed.					1	Use RDTN		
	Here is a summary of the voltages for the detection of off-hook for DP detection.								
	Bit 7 Bit 6 Bit 5 Bit 4		Bit 4	-					
	0	0		0		0	Not used		
	0	0		0		1	2.75 V		

Address		Fund	ction		Unit	Remarks
	0	0	1	0	5.5 V	
	1	0	0	0	22 V	
	1	1	1	1	41.25 V	

#### **NOTES**

- 1. If a setting is not required, store FF in the address.
- 2. Italy and Belgium only

RAM address 68055E: the lower four bits have the following meaning.

Bit 2 - 1: International dial tone cadence detection enabled (Belgium)

Bit 1 - Not used

Bit 0 - 1: PSTN dial tone cadence detection enabled (Italy)

If bit 0 or bit 2 is set to 1, the functions of the following RAM addresses are changed. 680508 (if bit 0 = 1) or 680538 (if bit 2 = 1): tolerance for on or off state duration (%), and number of cycles required for detection, coded as in address 680533. 68050B (if bit 0 = 1) or 68053B (if bit 2 = 1): on time, hex code (unit = 20 ms) 68050C (if bit 0 = 1) or 68053C (if bit 0 = 1): off time, hex code (unit = 20 ms)

- 3. Pulse dial parameters (addresses 68054A to 68054F) are the values for 10 pps. If 20 pps is used, the machine automatically compensates.
- 4. The first ring may not be detected until 1 to 2.5 wavelengths after the time specified by this parameter.
- 5. The calculated level must be between 0 and 10.

The attenuation levels calculated from RAM data are:

High frequency tone:

- $-0.5 \times N_{680552}/_{680554}-3.5 \text{ dBm}$
- $-0.5 \times N_{680555} dBm$

Low frequency tone:

- $-0.5 \times (N_{680552}/_{680554} + N_{680553}) -3.5 \text{ dBm}$
- $-0.5 \times (N_{680555} + N_{680553}) dBm$



- N<sub>680552</sub>, for example, means the value stored in address 680552(H)
- 6. 68054A: Europe Between Ds opening and Di opening, France Between Ds closing and Di opening

68054D: Europe - Between Ds closing and Di closing, France - Between Ds opening and Di closing

- 7. Tone signals which frequency is lower than 1500Hz (e.g., 800Hz tone for AI short protocol) refer to the setting at 6805B5h. Tones which frequency is higher than 1500Hz refer to the setting at 6805B6h.
- 8. 68054A, 68054D, 68054E: The actual inter-digit pause (pulse dial mode) is the sum of the period specified by the RAM addresses 68054A, 68054D, and 68054E.

# **Dedicated Transmission Parameters**

There are two sets of transmission parameters: Fax and E-mail

Each Quick Dial Key and Speed Dial Code has eight bytes of programmable parameters allocated to it. If transmissions to a particular machine often experience problems, store that terminal's fax number as a Quick Dial or Speed Dial, and adjust the parameters allocated to that number.

The programming procedure will be explained first. Then, the eight bytes will be described.

# **Programming Procedure**

- 1. Set the bit 0 of System Bit Switch 00 to 1.
- Enter Address Book Management mode ([User Tools]> System Settings> Key Operator> Address Book Management).
- 3. Select the address book that you want to program.
- 4. For the fax parameter, select "Fax Dest.", for the E-mail parameter, select "E-mail", then press "Start". Make sure that the LED of the Start button lights green.
- 5. The settings for the switch 00 are now displayed. Press the bit number that you wish to change.
- 6. To scroll through the parameter switches, either:
- 7. Select the next switch: press "Next" or Select the previous switch: "Prev." until the correct switch is displayed. Then go back to step 6.
- 8. After the setting is changed, press "OK".
- 9. After finishing, reset bit 0 of System Bit Switch 00 to 0.

#### **Parameters**

#### Fax Parameters

The initial settings of the following fax parameters are all FF(H) - all the parameters are disabled.

### Switch 00

#### **FUNCTION AND COMMENTS**

ITU-T T1 time (for PSTN G3 mode)

If the connection time to a particular terminal is longer than the NCU parameter setting, adjust this byte. The T1 time is the value stored in this byte (in hex code), multiplied by 1

second.

# Range:

0 to 120 s (00h to 78h)

FFh - The local NCU parameter factory setting is used.

Do not program a value between 79h and FEh.

Switch 01							
No			FU	NCTIC	ON	COMMENTS	
	Tx lev	/el					
	Bit4	Bit3	Bit2	Bit1	Bit0		If communication with a particular
	0	0	0	0	0	0	remote terminal often contains errors, the signal level may be
	0	0	0	0	1	-1	inappropriate. Adjust the Tx level for
0-4	0	0	0	1	0	-2	communications with that terminal until the results are better.
0 1	0	0	0	1	1	-3	If the setting is "Disabled", the NCU
	0	0	1	0	0	-4	parameter 01 setting is used.
	+	1	1	1	+	<b>+</b>	■ Do not use settings other
	0	1	1	1	1	-15	than listed on the left.
	1	1	1	1	1	Disabled	
5-7	Bit 7: Bit 7: Bit 7: Bit 7:	Cable equalizer Bit 7: 0, Bit 6: 0, Bit 5: 0 = None Bit 7: 0, Bit 6: 0, Bit 5: 1 = Low Bit 7: 0, Bit 6: 1, Bit 5: 0 = Medium Bit 7: 0, Bit 6: 1, Bit 5: 1 = High Bit 7: 1, Bit 6: 1, Bit 5: 1 = Disabled			= Low = Medi = High	um	Use a higher setting if there is signal loss at higher frequencies because of the length of wire between the modem and the telephone exchange when calling the number stored in this Quick/Speed Dial.  Also, try using the cable equalizer if one or more of the following symptoms occurs.  Communication error with error codes such as 0-20, 0-23, etc.

Modem rate fallback occurs frequently.

Note

Do not use settings other than listed on the left.

If the setting is "Disabled", the bit switch setting is used.

Swit	Switch 02					
No			FUNC	TION		COMMENTS
0-3	Initial	Tx mo	dem ra	ate		If training with a particular remote terminal
	Bit3	Bit2	Bit1	Bit0	bps	always takes too long, the initial modem rate may be too high. Reduce the initial Tx
	0	0	0	0	Not used	modem rate using these bits.
	0	0	0	1	2400	For the settings 14.4 or kbps slower, Switch 04 bit 4 must be changed to 0.
	0	0	1	0	4800	<b>↓</b> Note
	0	0	1	1	7200	<ul> <li>Do not use settings other than listed on the left. If the setting is</li> </ul>
	0	1	0	0	9600	"Disabled", the bit switch setting is
	0	1	0	1	12000	used.
	0	1	1	0	14400	
	0	1	1	1	16800	
	1	0	0	0	19200	
	1	0	0	1	21600	
	1	0	1	0	24000	
	1	0	1	1	26400	
	1	1	0	0	28800	
	1	1	0	1	31200	

	1	1	1	0	33600
	1	1	1	1	Disabled
	Other	setting	gs: <b>No</b>	t used	
4-7	Not u	ısed			

Swit	Switch 03				
No	FUNCTION	COMMENTS			
0-1	Inch-mm conversion before tx Bit 1: 0, Bit 0: 0 = Inch-mm conversion available Bit 1: 0, Bit 0: 1 = Inch only Bit 1: 1, Bit 0: 0 = Not used Bit 1: 1, Bit 0: 1 = Disabled	The machine uses inch-based resolutions for scanning. If "inch only" is selected, the printed copy may be slightly distorted at the other end if that machine uses mm-based resolutions.  If the setting is "Disabled", the bit switch setting is used.			
2-3	DIS/NSF detection method Bit 3: 0, Bit 2: 0 = First DIS or NSF Bit 3: 0, Bit 2: 1 = Second DIS or NSF Bit 3: 1, Bit 2: 0 = Not used Bit 3: 1, Bit 2: 1 = Disabled	(0, 1): Use this setting if echoes on the line are interfering with the set-up protocol at the start of transmission. The machine will then wait for the second DIS or NSF before sending DCS or NSS. If the setting is "Disabled", the bit switch setting is used.			
4	V.8 protocol 0: Off 1: Disabled	If transmissions to a specific destination always end at a lower modem rate (14,400 bps or lower), disable V.8 protocol so as not to use V.34 protocol. 0: V.34 communication will not be possible. If the setting is "Disabled", the bit switch setting is used.			
5	Compression modes available in transmit mode 0: MH only 1: Disabled	This bit determines the capabilities that are informed to the other terminal during transmission. If the setting is "Disabled", the bit switch setting is used.			

ECM during transmission
Bit 7: 0, Bit 6: 0 = Off

Bit 7: 0, Bit 6: 1 = On
Bit 7: 1, Bit 6: 0 = Not used
Bit 7: 1, Bit 6: 1 = Disabled

For example, if ECM is switched on but is not wanted when sending to a particular terminal, use the (0, 0) setting.



- V.8/V.34 protocol and JBIG compression are automatically disabled if ECM is disabled.
- If the setting is "Disabled", the bit switch setting is used.

Switch 04 - Not used (do not change the settings)

Switch 05 - Not used (do not change the settings)

Switch 06 - Not used (do not change the settings)

Switch 07 - Not used (do not change the settings)

Switch 08 - Not used (do not change the settings)

Switch 09 - Not used (do not change the settings)

#### E-mail Parameters

The initial settings of the following e-mail parameters are all "0" (all parameters disabled).

Switch	00	
No	FUNCTION	COMMENTS
0	MH Compression mode for e-mail attachments  0: Off  1: On	Switches MH compression on and off for files attached to e-mails for sending.
1	MR Compression mode for e-mail attachments  0: Off  1: On	Switches MR compression on and off for files attached to e-mails for sending.

2	MMR Compression mode for e-mail attachments <b>0</b> : Off 1: On	Switches MMR compression on and off for files attached to e-mails for sending.
3-6	Not used	Do not change these settings.
7	Designates the bits to reference for compression method of e-mail attachments  0: Registered (Bit 0 to 6)  1: No registration.	The "0" selection (default) references the settings for Bits 00, 01, 02 above. The "1" selection ignores the selections of Bits 00, 01, 02.

Switch	01	
No	FUNCTION	COMMENTS
0	Original width of e-mail attachment: A4  0: Off 1: On	Sets the original width of the e-mail attachment as A4.
1	Original width of e-mail attachment: B4  0: Off 1: On	Sets the original width of the e-mail attachment as B4.
2	Original width of e-mail attachment: A3  0: Off  1: On	Sets the original width of the e-mail attachment as A3.
3-6	Not used	Do not change these settings.
7	Designates the bits to reference for original size of e-mail attachments  0: Registered (Bit 0 to 6)	The "0" selection (default) references the settings for Bits 00, 01, 02 above. The "1" selection ignores the selections of Bits 00, 01, 02.

1: No registration.	
---------------------	--

Switch	02	
No	FUNCTION	COMMENTS
0	Line resolution of e-mail attachment: 200 x 100  0: Off 1: On	Sets the line resolution of the e-mail attachment as 200 x100.
1	Line resolution of e-mail attachment: 200 x 200  0: Off 1: On	Sets the line resolution of the e-mail attachment as 200 x 200.
2	Line resolution of e-mail attachment: 200 x 400  0: Off 1: On	Sets the line resolution of the e-mail attachment as 200 x 400.
3	Not used	Do not change these settings.
4	Line resolution of e-mail attachment: 400 x 400  0: Off 1: On	Sets the line resolution of the e-mail attachment as 400 x 400.
5-6	Not used	Do not change these settings.
7	Designates the bits to reference for original size of e-mail attachments <b>0</b> : Registered (Bit 0 to 6)  1: No registration.	The "0" selection (default) references the settings for Bits 00, 01, 02, 04 above. The "1" selection ignores the selections of Bits 00, 01, 02, 04.

Switch 03 - Not used (do not change the settings)

Switch	04	
No	FUNCTION	COMMENTS
0	Full mode address selection 0: Full mode address 1: No full mode (simple mode)	If the other ends have the addresses, which have the full mode function flag ("0"), this machine determines them as full mode standard machines.  This machine attaches the "demand of reception confirmation" to a message when transmitting.  This machine updates the reception capability to the address book when receiving.
1-7	Not used	Do not change these settings.

Switch	05	
No	FUNCTION	COMMENTS
0	Directr transmission selection to SMTP server 0: ON 1: OFF	Allows or does not allow the direct transmission to SMTP server.
1-7	Not used	Do not change these settings.

Switch 06 - Not used (do not change the settings)
Switch 07 - Not used (do not change the settings)
Switch 08 - Not used (do not change the settings)
Switch 09 - Not used (do not change the settings)

# Service RAM Addresses

# CAUTION

Do not change the settings which are marked as "Not used" or "Read only."

#### 680001 to 680004(H) - ROM version (Read only)

680001(H) - Revision number (BCD)

680002(H) - Year (BCD)

680003(H) - Month (BCD)

680004(H) - Day (BCD)

680006 to 680015(H) - Machine's serial number (16 digits - ASCII)

**680018(H)** - Total program checksum (low)

680019(H) - Total program checksum (high)

680020 to 68003F(H) - System bit switches

680050 to 68005F(H) - Printer bit switches

680060 to 68007F(H) - Communication bit switches

680080 to 68008F(H) - G3 bit switches

680090 to 68009F(H) - G3-2 bit switches: Not used

6800A0 to 6800AF(H) - G3-3 bit switches: Not used

6800D0(H) - User parameter switch 00 (SWUER\_00) : Not used

6800D1(H) - User parameter switch 01 (SWUSR 01): Not used

6800D2(H) - User parameter switch 02 (SWUSR\_02)

Bit 0: Forwarding mark printing on forwarded messages 0: Disabled, 1: Enabled

Bit 1: Center mark printing on received copies

(This switch is not printed on the user parameter list.)

0: Disabled, 1: Enabled

Bit 2: Reception time printing

(This switch is not printed on the user parameter list.)

0: Disabled, 1: Enabled

Bit 3: TSI print on received messages 0: Disabled, 1: Enabled

Bit 4: Checkered mark printing

(This switch is not printed on the user parameter list.)

0: Disabled, 1: Enabled

Bit 5: Not used

Bit 6: Not used

Bit 7: Not used

#### 6800D3(H) - User parameter switch 03 (SWUSR\_03: Automatic report printout)

Bit 0: Transmission result report (memory transmissions) 0: Off, 1: On

Bit 1: Not used

Bit 2: Memory storage report 0: Off, 1: On

Bit 3: Polling reserve report (polling reception) 0: Off, 1: On

Bit 4: Polling result report (polling reception) 0: Off, 1: On

Bit 5: Transmission result report (immediate transmissions) 0: Off, 1: On

Bit 6: Not used

Bit 7: Journal 0: Off, 1: On

#### 6800D4(H) - User parameter switch 04 (SWUSR 04: Automatic report printout)

Bit 0: Not used

Bit 1: Automatic communication failure report and transfer result report output 0:

Off, 1: On

Bits 2 to 3: Not used

Bit 4: Indicates the parties 0: Not indicated, 1: Indicated

Bit 5: Include sender's name on reports 0: Off, 1: On

Bit 6: Not used

Bit 7: Inclusion of a sample image on reports 0: Off, 1: On

#### 6800D5(H) - User parameter switch 05 (SWUSR 05)

Bit 0: Substitute reception when the base copier is in an SC condition

0: Enabled, 1: Disabled

Bits 1 and 2: Condition for substitute rx when the machine cannot print messages

(Paper end, toner end, jam, and during night mode)

Bit 2: 0, Bit 1: 0 = The machine receives all the fax messages.

Bit 2: 0, Bit 1: 1 = The machine receives the fax messages with RTI or CSI.

Bit 2: 1, Bit 1: 0 = The machine receives the fax messages with the same ID code.

Bit 2: 1, Bit 1: 1 = The machine does not receive anything.

Bit 3: Not used

Bit 4: Not used

Bit 5: Just size printing 0: Off, 1: On

Bit 6: Not used

Bit 7: Add paper display when a cassette is empty 0: Off, 1: On

#### 6800D6(H) - User parameter switch 06 (SWUSR 06): Not used

## 6800D7(H) - User parameter switch 07 (SWUSR\_07)

Bit 0 Ringing 0: Off, 1: On

Bit1: Automatic answering message 0: Off, 1: On

Bit 2: Parallel memory transmission 0: Off, 1: On

Bits 3 and 4: Not used

Bit 5: Remote control 0: Off, 1: On

Bits 6 and 7: Not used

#### 6800D8(H) - User parameter switch 08 (SWUSR 08)

Bits 0 and 1: Not used.

Bit 2: Authorized reception

0: Only faxes from senders whose RTIs/CSIs are specified for this feature are accepted.

1: Only faxes from senders whose RTIs/CSIs are not specified for this feature are accepted.

Bits 3 to 7: Not used.

### 6800D9(H) - User parameter switch 09 (SWUSR 09): Not used

#### 6800DA(H) - User parameter switch 10 (SWUSR 0A)

Bits 0 to 2: Not used

Bit 3: Page reduction 0: Off, 1: On

Bits 4 and 5: Not used

Bit 6: Use both e-mail notification and printed reports to confirm the transmission

results 0: Off, 1: On

Bit 7: Not used

#### 6800DB(H) - User parameter switch 11 (SWUSR 0B)

Bits 0 and 1: Not used

Bit 2: White original detection 0: Off, 1: On (alarm and alert message on the LCD)

Bit 3: Receive rejection for 1300 Hz transmission 0: Off (receive), 1: On (not receive)

Bit 5: Not used

Bit 6: Printout of messages received while acting as a forwarding station 0: Off, 1:

On

Bit 7: Not used

# 6800DC(H) - User parameter switch 12 (SWUSR\_0C): Not used

6800DD(H) - User parameter switch 13 (SWUSR 0D): Not used

## 6800DE(H) - User parameter switch 14 (SWUSR\_0E)

Bit 0: Message printout while the machine is in Night Printing mode 0: On, 1: Off

Bit 1: Maximum document length detection 0: Double letter, 1: Longer than

double-letter (well log) - up to 1,200 mm

Bit 2: Not used

Bit 3: Fax mode settings, such as resolution, before a mode key

(Copy/Fax/Printer/Scanner) is pressed 0: Not cleared, 1: Cleared

Bits 4 to 6: Not used

Bit 7: Not used

# 6800DF(H) - User parameter switch 15 (SWUSR\_0F)

(This switch is not printed on the user parameter list.)

Bits 0, 1 and 2: Cassette for fax printout

Bit 2: 0, Bit 1: 0, Bit 0: 1 = 1st paper feed station

Bit 2: 0, Bit 1: 1, Bit 0: 0 = 2nd paper feed station

Bit 2: 0, Bit 1: 1, Bit 0: 1 = 3rd paper feed station

Bit 2: 1, Bit 1: 0, Bit 0: 0 = 4th paper feed station

Bit 2: 1, Bit 1: 0, Bit 0: 1 = LCT

Other settings Not used

Bits 3 and 4: Not used

Bit 5: Using the cassette specified by bits 0, 1 and 2 above only 0: On, 1: Off

Bits 6 and 7: Not used

#### 6800E0(H) – User parameter switch 16 (SWUSR\_10)

(This switch is not printed on the user parameter list.)

Bits 0 and 1: Not used

Bit 2: Paper size selection priority for an A4 size fax message when A4/LT size

paper is not available. 0: A3 has priority, 1: B4 has priority

Bits 3 to 7: Not used

#### 6800E1(H) - User parameter switch 17 (SWUSR 11)

Bit 0: Not used

Bit 1: Not used

Bit 2: Inclusion of the "Add" button when a sequence of Quick/Speed dials is

selected for broadcasting 0:Not needed, 1: Needed

Bits 3 to 6: Not used

Bit 7: Press "Start" key without an original when using the on hook dial or the

external telephone,

0: displays "Cannot detect original size". 1: Receives fax messages.

## 6800E2(H) - User parameter switch 18 (SWUSR\_12)

Bit 0: TTI date 0: Off, 1: On

Bit 1: TTI sender 0: Off, 1: On

Bit 2: TTI file number 0: Off, 1: On

Bit 3: TTI page number 0: Off, 1: On

Bits 4 to 6: Not used

Bit 7: Japan only

#### 6800E3(H) - User parameter switch 19 (SWUSR 13)

Bit 0: Not used

Bit 1: Journal format

0: The Journal is separated into transmissions and receptions

1: The Journal is separated into G3-1, G3-2, and G3-3 communications

Bit 2: Not used

Bit 3: 90° image rotation during B5 portrait Tx (This switch is not printed on the user parameter list.) 0: Off, 1: On

Bit 4: Reduction of sample images on reports to 50% in the main scan and sub-scan directions. (This switch is not printed on the user parameter list.) 0:

Technician adjustment (printer switch 0E bits 3 and 4), 1:50% reduction

Bit 5: Use of A5 size paper for reports (This switch is not printed on the user parameter list.) 0: Off, 1: On

Bits 6 and 7: Not used

#### 6800E4(H) - User parameter switch 20 (SWUSR\_14)

Bit 0: Automatic printing of the LAN fax result report 0: Off, 1: On

Bit 1: Not used.

Bits 2 to 5: Store documents in memory which could not be printed from PC fax (LAN fax) driver

Bit 5	Bit 4	Bit 3	Bit 2	Setting
0	0	0	0	0 min.
0	0	0	1	1 min.
+	+	+	+	<b>+</b>
1	1	1	0	14 min.
1	1	1	1	15 min.

Bits 6 and 7: Not used.

#### 6800E5(H) - User parameter switch 21 (SWUSR\_15)

Bit 0: Print results of sending reception notice request message 0: Disabled (print only when error occurs), 1: Enabled

Bit 1: Respond to e-mail reception acknowledgment request 0: Disabled, 1:

Enabled

Bit 2: Not used

Bit 3: File format for forwarded folders 0: TIFF, 1:PDF

Bit 4: Transmit Journal by E-mail 0: Disabled, 1: Enabled

Bit 5: Not used

Bit 6: Network error display 0: Displayed, 1: Not displayed

Bit 7: Transmit error mail notification 0: Enabled, 1: Disabled

#### 6800E6(H) - User parameter switch 22 (SWUSR 16)

(This switch is not printed on the user parameter list.)

Bit 0: Dial tone detection (PSTN 1) 0: Disabled, 1: Enabled

Bits 1 to 7: Not used

6800E7(H) - User parameter switch 23 (SWUSR 17): Not used

6800E8(H) - User parameter switch 24 (SWUSR 18): Not used

#### 6800E9(H) - User parameter switch 25 (SWUSR 19)

Bit 0: Not used

Bit 1: Reception mode switch timer 0: Off, 1: On (switching Fax or Fax/Tel)

Bit 2: Mode priority switch 0: Fax first, 1: Tel first

Bit 3: Dial in function (Japan Only)

Bit 4: RDS operation 0: Not acceptable, 1: Acceptable for the limit specified by system switch 03



 This bit is only effective when RDS operation can be selected by the user (see system switch 02).

Bits 5 to 7: Not used

6800EA(H) and 6800EB(H) - User parameter switches 26 and 27 (SWUSR\_1A and 1B): Not used

6800EC(H) - User parameter switch 28(SWUSR 1C)

Xxxxx

6800ED(H) - User parameter switch 29(SWUSR\_1D)

xxxxx

6800EE(H) and 6800EF(H) - User parameter switches 30 and 31 (SWUSR\_1E and 1F): Not used

#### 6800F0(H) - User parameter switch 32 (SWUSR 20)

Bit 0: Quotation priority for a destination when there is no destination of the specified type

0: Paper output priority = Priority order: 1. IP-fax destination, 2. Fax Number, 3.

E-mail address, 4. Folder 1: Electric putout order = Priority order: 1. E-mail address, 2. Folder, 3. IP-fax destination, 4. Fax number Bits 1 to 7: Not used 6800F1(H) - User parameter switch 33 (SWUSR\_21): Not used 6800F2(H) - User parameter switch 34 (SWUSR 22) Bit 0: Gatekeeper server used with IP-Fax 0: Disabled, 1: Enabled Bit 1: SIP server used with IP-Fax 0: Disabled, 1: Enabled Bits 2 to 7: Not used 680100 to 68010F(H) - G4 Parameter Switches - Not used 680110 to 68012F(H) - G4 Internal Switches - Not used 680130 to 68016F(H) - Service Switches 680170 to 68017F(H) - IFAX Switches 680180 to 68018F(H) - IP-FAX Switches **680190 to 6801AF(H)** - Service station's fax number (SP3-101) 6801B0 to 6801B9(H) - Own fax PABX extension number **6801BA to 6801C3(H)** - Own fax number (PSTN) - Not used 6801C4 to 6801D7(H) - Own fax number (ISDN G4) - Not used 6801D8 to 6801E3(H) - The first subscriber number (ISDN G3) - Not used 6801E4 to 6801EF(H) - The second subscriber number (ISDN G3) - Not used 6801F0 to 6801FB(H) - The first subscriber number (ISDN G4) - Not used 6801FC to 680207(H) - The second subscriber number (ISDN G4) - Not used 680208 to 68021B(H) - PSTN-1 RTI (Max. 20 characters - ASCII) - See the following note. 68021C to 68022F(H) - PSTN-2 RTI (Max. 20 characters - ASCII) - Not used 680230 to 680246(H) - PSTN-3 RTI (Max. 20 characters - ASCII) - Not used 680247 to 680286(H) - TTI 1 (Max. 64 characters - ASCII) - See the following note. 680287 to 6802C6(H) - TTI 2 (Max. 64 characters - ASCII) - Not used 6802C7 to 680306(H) - TTI 3 (Max. 64 characters - ASCII) - Not used 680307 to 68031A(H) - PSTN-1 CSI (Max. 20 characters - ASCII) 68031B to 68032E(H) - PSTN-2 CSI (Max.20 characters - ASCII) - Not used 68032F to 680342(H) - PSTN-3 CSI (Max.20 characters - ASCII) - Not used 680343(H) - Number of PSTN-1 CSI characters (Hex) 680344(H) - Number of PSTN-2 CSI characters (Hex) - Not used 680345(H) Number of PSTN-3 CSI characters (Hex) - Not used ■ Note

If the number of characters is less than the maximum (20 for RTI, 64 for TTI), add a

```
stop code (00[H]) after the last character.
680380 to 680387(H) - Last power off time (Read only)
        680380(H) - 01(H) - 24-hour clock, 00(H) - 12-hour clock (AM), 02(H) - 12-hour
        clock (PM)
        680381(H) - Year (BCD)
        680382(H) - Month (BCD)
        680383(H) - Day (BCD)
        680384(H) - Hour
        680385(H) - Minute
        680386(H) - Second
        680387(H) - 00: Monday, 01: Tuesday, 02: Wednesday, ///, 06: Sunday
680394(H) - Optional equipment (Read only – Do not change the settings)
        Bit 0: Page Memory
                                0: Not installed, 1: Installed
        Bit 1: SAF Memory
                                0: Not installed, 1: Installed
        Bits 2 to 7; Not used
680395(H) - Optional equipment (Read only – Do not change the settings)
        Bits 0 to 3: Not used
        Bit 4: G3-2 0: Not installed, 1: Installed
        Bit 5: G3-3 0: Not installed, 1: Installed
        Bit 6 and 7: Not used
680406 to 68040A – Option G3 board (G3-2) ROM information (Read only)
        680406(H) - Suffix (BCD)
        680407(H) - Version (BCD)
        680408(H) - Year (BCD)
        680409(H) - Month (BCD)
        68040A(H) - Day (BCD)
68040B to 68040F - Option G3 board (G3-3) ROM information (Read only)
        68040B(H) - Suffix (BCD)
        68040C(H) - Version (BCD)
        68040D(H) - Year (BCD)
        68040E(H) - Month (BCD)
        68040F(H) - Day (BCD)
680410(H) - G3-1 Modem ROM version (Read only)
680412(H) - G3-2 Modem ROM version (Read only)
680414(H) - G3-3 Modem ROM version (Read only)
680420(H) - Number of multiple sets print (Read only)
```

```
680476(H) - Time for economy transmission (hour in 24h clock format - BCD)
680477(H) - Time for economy transmission (minute - BCD)
680492(H) - Transmission monitor volume 00 - 07(H)
680493(H) - Reception monitor volume 00 - 07(H)
680494(H) - On-hook monitor volume 00 - 07(H)
680495(H) - Dialing monitor volume 00 - 07(H)
680496(H) - Buzzer volume
                             00 - 07(H)
680497(H) - Beeper volume
                               00 - 07(H)
6804A8(H) - Machine code (Check ram 4)
688E8E to 68918D(H) - SIP server address (Read only)
        688E8E(H) - Proxy server - Main (Max. 128 characters - ASCII)
        688F0E(H) - Proxy server - Sub (Max. 128 characters - ASCII)
        688F8E(H) - Redirect server - Main (Max. 128 characters - ASCII)
        68900E(H) - Redirect server - Sub (Max. 128 characters - ASCII)
        68908E(H) - Registrar server - Main (Max. 128 characters - ASCII)
        68910E(H) - Registrar server - Sub (Max. 128 characters - ASCII)
68918E(H) - Gatekeeper server address - Main (Max. 128 characters - ASCII)
68920E(H) - Gatekeeper server address - Sub (Max. 128 characters - ASCII)
68928E(H) - Arias Number (Max. 128 characters - ASCII)
68930E(H) - SIP user name (Max. 128 characters - ASCII)
68938E(H) - SIP digest authentication password (Max. 128 characters - ASCII)
68940E(H) - Gateway address information (Max. 7100 characters - ASCII)
68AFCA(H) - Stand-by port number for H.232 connection
68AFCCH) - Stand-by port number for SIP connection
68AFCE(H) - RAS port number
68AFD0(H) - Gatekeeper port number
68AFD2(H) - Port number of data waiting for T.38
68AFD4(H) - Port number of SIP server
68AFD6(H) - Priority for SIP and H.323 0: H.323, 1: SIP
68AFD7(H) - SIP function 0: Disabled, 1: Enabled
68AFD8(H) - H.323 function 0: Disabled, 1: Enabled
68AFD9(H) - SIP digest authentication function 0: Disabled, 1: Enabled
68AFDA(H) - IP-Fax backup data 00 - 600 (H)
69ECBE(H) - 69ECDE(H) - Dial tone detection parameter (Max. 11 x 3 lines)
        This initializes following order. [0x04, 0x40, 0x03, 0x60, 0x64, 0xf4, 0x01,0x64,
        0x04, 0xc8, 0x00]
```



**6BEBFE(H)** – Dial tone detection frequency – Upper limit (High)

Defaults: NA: 06, EU: 06, ASIA: 06

**6BEBFF(H)** – Dial tone detection frequency – Upper Limit (Low)

Defaults: NA: 50, EU: 50, ASIA: 50

**6BEC00(H)** – Dial tone detection frequency – Lower Limit (High)

Defaults: NA: 03, EU: 02, ASIA: 02

**6BEC01(H)** – Dial tone detection frequency – Lower Limit (Low)

Defaults: NA: 60, EU: 90, ASIA: 90

**6BEC02(H)** –Dial tone detection waiting time (20 ms)

Defaults: NA: 64, EU 64, ASIA: 64

**6BEC03 to 6BEC04** – Dial tone detection monitoring time (20 ms)

#### Defaults

Area	6BEC03	6BEC04
NA	F4	01
EU	F4	01
ASIA	F4	01

**6BEC05(H)** – Dial tone detect judge time (20 ms)


Defaults: NA: 64, EU: 1B, ASIA: 32

**6BEC06(H)** – Dial tone disconnect permission time (20 ms)

Defaults: NA: 11, EU: 0F, ASIA: 11

# **Detailed Section Descriptions**

# Overview




The basic fax unit consists of two PCBs: an FCU and an MBU.

The FCU controls all the fax communications and fax features, in cooperation with the controller board. The MBU contains the ROM and SRAM. Also, the FCU has an NCU circuit.

# Boards

# **FCU**



The FCU (Facsimile Control Unit) controls fax communications, the video interface to the base copier's engine, and all the fax options.

# FACE3 (Fax Application Control Engine)

- CPU
- Data compression and reconstruction (DCR)
- DMA control
- Clock generation
- DRAM backup control

# Modem (FAME)

V.34, V33, V17, V.29, V.27ter, V.21, and V.8

## DRAM

The 16 MB of DRAM is shared as follows.

SAF memory : 4MB

Working memory : 8MB
Page memory : 4MB

The SAF memory is backed up by a rechargeable battery.

## Memory Back-up

A Rechargeable battery backs up the SAF memory (DRAM) for 1 hour.

#### **MBU**

On this board, the flash ROM contains the FCU firmware, and the SRAM contains the system data and user parameters. Even if the FCU is changed, the system data and user parameters are kept on the MBU board.

#### **ROM**

3MB flash ROMs for system software storage
 2MB (16bit x 1MB) + 1MB (16bit x 512K)

#### **SRAM**

 The 128 KB SRAM for system and user parameter storage is backed up by a lithium battery.

#### Memory Back-up


 A lithium battery backs up the system parameters and programmed items in the SRAM, in case the base copier's main switch is turned off.

#### **Switches**

Item	Description	
SW1	Switches the SRAM backup battery on/off.	

# Video Data Path

# Transmission



Memory Transmission and Parallel Memory Transmission

The base copier's scanner scans the original at the selected resolution in inch format. The SBCU processes the data and transfers it to the FCU.



When scanning a fax original, the SBCU uses the MTF, independent dot erase and thresholding parameter settings programmed in the fax unit's scanner bit switches, not the copier's SP modes.

Then, the FCU converts the data to mm format, and compresses the data in MMR or raw format to store it in the SAF memory. If image rotation will be done, the image is rotated in page memory before compression.

At the time of transmission, the FCU decompresses the stored data, then re-compresses and/or reduces the data if necessary for transmission. The NCU transmits the data to the line.

#### Immediate Transmission

The base copier's scanner scans the original at the resolution agreed with the receiving terminal. The SBCU video processes the data and transfers it to the FCU.



When scanning a fax original, the SBCU uses the MTF, independent dot erase and thresholding parameter settings programmed in the fax unit's scanner bit switches, not the copier's SP modes.

Then the FCU stores the data in page memory, and compresses the data for transmission. The NCU transmits the data to the line.


## **JBIG Transmission**

- Memory transmission: If the receiver has JBIG compression, the data goes from the DCR to the QM-Coder. Then the NCU transmits the data to the line.
- Immediate transmission: If the receiver has JBIG compression, the data goes from the page memory to the QM-Coder. Then the NCU transmits the data to the line.

#### Adjustments

Priority for the line used for G3 transmission (PSTN 1): System switch 16 bit 1

#### Reception



First, the FCU stores the incoming data from either an analog line to the SAF memory. (The data goes to the FACE3 at the same time, and is checked for error lines/frames.)

The FCU then decompresses the data and transfers it to page memory. If image rotation will be done, the image is rotated in the page memory. The data is transferred to the SBCU.

#### JBIG Reception

When data compressed with JBIG comes in on PSTN-1 (the standard analog line), the data is sent to the QM-CODER for decompression. Then the data is stored in the page memory, and transferred to the SBCU.

### Fax Communication Features

#### Internet Mail Communication

#### Mail Transmission

This machine supports T.37 full mode. (ITU-, RFC232). The difference between T.37 simple mode and full mode is as follows.

Function	T.37 Simple Mode	T.37 Full Mode	
Resolution	200 x 100 200 x 200	200 x100 200 x 200 200 x 400 400 x 400 (if available)	
RX Paper Width	A4	A4, B4, A3	
RX Data Compression Method	мн	MH (default), MR, MMR,	
Signals  Image data transmission only		Image data transmission, exchange of capability information between the two terminals, and acknowledgement of receipt of fax messages	

#### **Data Formats**

The scanned data is converted into a TIFF-F formatted file.

The fields of the e-mail and their contents are as follows:

Field	Content	
From	Mail address of the sender	
Reply To	Destination requested for reply	
То	Mail address of the destination	
Всс	Backup mail address	

Subject	From CSI or RTI (Fax Message No. xxxx)	
Content Type	Multipart/mixed Attached files: image/tiff	
Content Transfer Encoding	Base 64, 7-bit, 8-bit, Quoted Printable	
Message Body	MIME-converted TIFF-F (MIME standards specify how files are attached to e-mail messages)	

#### **Direct SMTP Transmission**

Internet Fax documents can be sent directly to their destinations without going through the SMTP server. (Internet Faxes normally transmit via the SMTP server.)

#### For example:

e-mail address:	gts@ricoh.co.jp
SMTP server address:	gts.abcd.com

In this case this feature destination e-mail address (gts@ricoh.co.jp) is read as the SMTP server address "gts.abcd.com" and the transmissions bypass the SMTP server.

#### Selectable Options

These options are available for selection:

- With the default settings, the scan resolution can be either standard or detail. Inch-mm conversion before TX depends on IFAX SW01 Bit 7. Detail resolution will be used if Super Fine resolution is selected, unless Fine resolution is enabled with IFAX SW01.
- The requirements for originals (document size, scan width, and memory capacity) are the same as for G3 fax memory TX.
- The default compression is TIFF-F format.
- IFAX SW00: Acceptable paper widths for sending
- IFAX SW09: Maximum number of attempts to the same destination

#### Secure Internet Transmission

- SMTP Authentication: User Tools> System Settings> File Transfer> SMTP Authentication
- POP Before SMTP: User Tools> System Settings> File Transfer> POP Before SMTP

#### Mail Reception

This machine supports three types of e-mail reception:

- POP3 (Post Office Protocol Ver. 3.)
- IMAP4 (Internet Messaging Access Protocol)
- SMTP (Simple Mail Transfer Protocol)

For details: Core Technology Manual – Facsimile Processes – Faxing from a PC – Internet/LAN Fax Boards – Mail Reception

#### POP3/IMAP4 Mail Reception Procedure

The machine automatically picks up e-mail from the server at an interval which is adjustable in the range 2 to 1440 min. in 1-minute steps: User Tools> System Settings> File Transfer> E-mail Reception Interval

#### **SMTP Reception**

- The IFAX must be registered as an SMTP server in the MX record of the DNS server, and the address of the received mail must specify the IFAX.
- Enable SMTP reception: User Tools> System Settings> File Transfer> Reception
   Protocol

Even if the MX record on the DNS server includes the IFAX, mail cannot be received with SMTP until SMTP reception is enabled:

However, if SMTP reception is selected and the machine is not registered in the MX record of the DNS server, then either IMAP4 or POP3 is used, depending on the setting: User Tools> System Settings> File Transfer> Reception Protocol

#### Mail Delivery Conditions: Transferring Mail Received With SMTP

- The machine must be set up for SMTP mail delivery: User Tools> Facsimile Features>
   E-mail Settings> SMTP RX File Delivery Settings
- 2. If the user wishes to limit this feature so that the machine will only deliver mail from designated senders, the machine's "Auth. E-mail RX" feature must be set (User Tools> Facsimile Features> E-mail Settings> SMTP RX File Delivery Settings).
- 3. If the "SMTP RX File Delivery Setting" is set to 0 to prohibit SMTP receiving, and if there is mail designated for delivery, then the machine responds with an error. (User Tools> Facsimile Features> E-mail Settings> SMTP RX File Delivery Settings)
- 4. If the quick dial, speed dial, or group dial entry is incorrect, the mail transmission is lost, and the IFAX issues an error to the SMTP server and outputs an error report.

#### Auth. E-mail RX

In order to limit access to mail delivery with IFAX, the addresses of senders must be limited using the Access Limit Entry. Only one entry can be registered.

#### 1. Access Limit Entry

For example, to limit access to @IFAX.ricoh.co.jp:

gts@IFAX.ricoh.co.jp	Matches and is delivered.
gts@IFAX.abcde.co.jp	Does not match and is not delivered.
IFAX@ricoh.co.jp	Does not match and is not delivered.

#### 2. Conditions

- The length of the Access Limit Entry is limited to 127 characters.
- If the Access Limit Entry address and the mail address of the incoming mail do not match, the incoming mail is discarded and not delivered, and the SMTP server responds with an error. However, in this case an error report is not output.
- If the Access Limit Entry address is not registered, and if the incoming mail specifies a delivery destination, then the mail is delivered unconditionally.

#### Handling Mail Reception Errors

#### **Abnormal files**

When an error of this type occurs, the machine stops receiving and commands the server to erase the message. Then the machine prints an error report and sends information about the error by e-mail to the sender address (specified in the "From" or "Reply-to" field of the message). If there is an incomplete received message in the machine memory, it will be erased.

The machine prints an error message when it fails to send the receive error notification after a certain number of attempts.

The following types of files are judged to be abnormal if one or more of the following are detected:

#### 1. Unsupported MIME headers.

Supported types of MIME header

Header	Supported Types
Content-Type	Multipart/mixed, text/plain, message/rfc822 Image/tiff

Charset	US-ASCII, ISO 8859 X. Other types cannot be handled, and some garbage may appear in the data.
Content-Transfer-Encoding	Base 64, 7-bit, 8-bit, Quoted Printable

- 2. MIME decoding errors
- 3. File format not recognized as TIFF-F format
- 4. Resolution, document size, or compression type cannot be accepted

#### Remaining SAF capacity error

The machine calls the server but does not receive e-mail if the remaining SAF capacity is less than a certain value (the value depends on IFAX Switch 08. The e-mail will be received when the SAF capacity increases (for example, after substitute reception files have been printed). The error handling method for this type of error is the same as for "Abnormal files". If the capacity of the SAF memory drops to zero during reception, the machine operates in the same way as when receiving an abnormal file (refer to "Abnormal files" above).

#### Secure Internet Reception

To enable password encryption and higher level security: User Tools> System Settings> File Transfer> POP3/IMAP4 Settings> Encryption (set to "On")

Transfer Request: Request By Mail

For details: Core Technology Manual – Facsimile Processes – Faxing from a PC – Internet/LAN Fax Boards – Transfer Request

The fields of the e-mail and their contents are as follows:

Field	Content	
From	E-mail address of the requesting terminal	
То	Destination address (Transfer Station address)	
Всс	Blind carbon copy	
Subject	From TSI (Fax Message No. xxxx)	
Content-Type	Multipart/mixed	

	Text/Plain (for a text part), image/tiff (for attached files)
Content-Transfer-Encoding	Base 64, 7-Bit, 8-bit, Quoted Printable
Mail body (text part)	RELAY-ID-: xxxx (xxxx: 4 digits for an ID code) RELAY: #01#*X#**01
Message body	MIME-converted TIFF-F.

#### E-Mail Options (Sub TX Mode)

The following features are available as options for mail sending: entering a subject, designating the level of importance, confirming reception of the mail.

#### Subject and Level of Importance

You can enter a subject message with: Sub TX Mode> E-mail Options

The Subject entry for the mail being sent is limited to 64 characters. The subject can also be prefixed with an "Urgent" or "High" notation.

#### How the Subject Differs According to Mail Type

Mail Type	1	2		3
Subject Entry		Entry Condition		
		1. "CSI" ("RTI")		Fax Message No.
No Subject		2. "RTI"	CSI not registered	+
Entry		3. "CSI"	RTI not registered	File No.
		4. None	CSI, RTI not registered	
Confirmation	From	1. "CSI" ("RTI")		Normal:
of Reception		2. "RTI"	CSI not registered	Return Receipt (dispatched). You can select "displayed" with IFAX

				SW02 Bits 2 and 3.
		3. "CSI"	RTI not registered	Error:
		4. None	CSI, RTI not registered	Return Receipt (processed/error)
Mail delivery,		RTI or CSI of the station designated for delivery	Mail delivery	
memory transfer, SMTP	From	RTI or CSI of sender	Mail sending from G3 memory	Fax Message No. + File Number
receiving and delivery		Mail address of sender	Memory sending	
		Mail address of sender	SMTP receiving and delivery (Off Ramp Gateway)	
Mail error notification		Error Message	No. xxxx From CSI (RTI)	

Items ① ② ③ of the table above are in the Subject.

#### Subjects Displayed on the PC



#### E-mail Messages

After entering the subject, you can enter a message with:

Sub TX Mode> E-mail Options

An e-mail message (up to 5 lines) can be pre-registered with: User Tools> System Settings> File Transfer> Program/Change/Delete E-mail Message

#### **Limitations on Entries**

Item	Maximum
Number of Lines	5 lines
Line Length	80 characters
Name Length	20 characters

#### Message Disposition Notification (MDN)

For details: Core Technology Manual – Facsimile Processes – Faxing from a PC – Internet/LAN Fax Boards – E-mail Options

The network system administrator can confirm whether a sent mail has been received correctly or not. This function is enabled only when "I-FAX switch 02 Bit 4" is set to "1"This confirmation is done in four steps.

- 1. Send request for confirmation of mail reception. To enable or disable this request (known as MDN):
- 2. Sub TX Mode> E-mail Options
- 3. Mail reception (receive confirmation request)
- 4. Send confirmation of mail reception
- 5. Receive confirmation of mail reception

The other party's machine will not respond to the request unless the two conditions below are met:

- The other party's machine must be set up to respond to the confirmation request.
- The other party's machine must support MDN (Message Disposition Notification).
- Setting up the Receiving Party -

The receiving party will respond to the confirmation request if:

- 1. The "Disposition Notification To" field is in the received mail header (automatically inserted in the 4th line in the upper table on the previous page, if MDN is enabled), and
- Sending the disposition notification must be enabled (User Parameter Setting SW21 (15
   [H]) Bit 1 for this model). The content of the response is as follows:

Normal reception:	"Return Receipt (dispatched)" in the Subject line	
IFAX SW02 (Bit 2, 3)	"Return Receipt (displayed)" in the Subject line	
Error:	"Return Receipt (processed/error)" in the Subject line	

#### Handling Reports

- Sending a Request for a Return Receipt by Mail
   After the mail sender transmits a request for a return receipt, the mail sender's journal is annotated with two hyphens (--) in the Result column and a "Q" in the Mode column.
- 2. Mail Receipt (Request for Receipt Confirmation) and Sending Mail Receipt Response After the mail receiver sends a response to the request for a return receipt, the mail receiver's journal is annotated with two hyphens (--) in the Result column and an "A" in the Mode column.
- 3. Receiving the Return Receipt Mail
  - After the mail sender receives a return receipt, the information in the mail sender's journal about the receipt request is replaced, i.e. the journal is annotated with "OK" in the Result column.
  - When the return receipt reports an error, the journal is annotated with an "E" in the Result column.
  - The arrival of the return receipt is not recorded in the journal as a separate communication. Its arrival is only reported by the presence of "OK" or "E" in the Result column.
  - If the mail address used by the sender specifies a mailing list (i.e., a Group destination; the machine sends the mail to more than one location. See "How to set up Mail Delivery"), the Result column of the Journal is updated every time a return receipt is received. For example, if the mailing list was to 5 destinations, the Result column indicates the result of the communication with the 5th destination only. The results of the communications to the first 4 destinations are not shown.

Exceptions: If one of the communications had an error, the Result column will indicate E, even if subsequent communications were OK.

If two of the communications had an error, the Journal will indicate the destination for the first error only.

#### Report Sample

	DATE	TIME	ADDRESS MODE TIME RESULT	PAGE
	N 7 3 7 E	10.15	fuser 01@dom1g. ricoh. co. Mail SM 0'09"	2
1	MAI. J	10.13	ruser_oredomig. ricon. co. Mair sm 0 09	۷ .
		10:16	fuser_01@dom1g. ricoh. co. Mail SMQ 0'05"	1
		10:17	s_tadashi@dom1g. ricoh. co. Mail SMQ 0'09"	2
		10:19	m_masataka@dom1g. ri $\overset{ ext{OK}}{ ext{coh}}$ . co. Mail SMA 0'05"	1

### **IP-Fax**

#### What is IP-FAX?

For details: Core Technology Manual – Facsimile Processes – Faxing from a PC –

Internet/LAN Fax Boards - IP-FAX

T.38 Packet Format

TCP is selected by default for this machine, but you can change this to UDP with IPFAX SW 00 Bit 1.

**UDP Related Switches** 

IP-Fax Switch 01						
No.	FUNCTION					COMMENTS
	Select IP FAX Delay Level				el	Raise the level by selecting a higher setting
	Bit3	Bit2	Bit1	Bit0	on the network.  Level 0  Level 1  Level 1  Level 2  Setting on the network.  If TCP/UDP is enabled on the networ this setting on the T.30 machine. Increase the delay time allows the recovery of lost packets.	if too many transmission errors are occurring on the network.
	0	0	0	0		If TCP/UDP is enabled on the network, raise
0-3	0	0	0	1		this setting on the T.30 machine. Increasing the delay time allows the recovery of more
	0	0	1	0		lost packets.
	0	0	1	1		If only UDP is enabled, increase the number of redundant packets.
						Level 1~2: 3 Redundant packets Level 3: 4 Redundant packets

#### Settings

User parameter switch 34 (22[H]), bit 0

IP-Fax Gate Keeper usage 0: No, 1: Yes

IP Fax Switches: Various IP-FAX settings (see the bit switch table)

# Specifications

## General Specifications

Type:	Desktop type transceiver		
Circuit:	PSTN PABX		
Connection:	Direct couple		
Original Size:	Book (Face down)  Maximum Length: 432 mm [17 ins]  Maximum Width: 297 mm [11.7 ins]  ARDF (Face up) (Single-sided document)  Length: 128 - 1200 mm [5.0 - 47.2 ins]  Width: 105 - 297 mm [4.1 - 11.7 inch] (Double-sided document)  Length: 128 - 432 mm [5.0 - 17 inch]  Width: 105 - 297 mm [4.1 - 11.7 inch]		
Scanning Method:	Flat bed, with CCD		
Resolution:	G3 8 x 3.85 lines/mm (Standard) 8 x 7.7 lines/mm (Detail) 8 x 15.4 line/mm (Fine) 200 x 100 dpi (Standard) 200 x 200 dpi (Detail)		
Transmission Time:	G3: 3 s at 28800 bps; Measured with G3 ECM using memory for an ITU-T #1 test document (Slerexe letter) at standard resolution		
Data Compression:	MH, MR, MMR, JBIG		
Protocol: Group 3 with ECM			

Modulation:	V.34, V.33, V.17 (TCM), V.29 (QAM), V.27ter (PHM), V.8, V.21 (FM)		
G3: 33600/31200/28800/26400/24000/21600/  Data Rate: 19200/16800/14400/12000/9600/7200/4800/2400 bps  Automatic fallback			
With ECM: 0 ms/line Without ECM: 2.5, 5, 10, 20, or 40 ms/line			
Memory Capacity:	ECM: 128 KB SAF Standard: 4 MB Page Memory: Standard: 4 MB (Print: 2 MB + Scanner: 2 MB)		

## IFAX Specifications


Connectivity:	Local area network Ethernet 100base-Tx/10base-T IEEE1394 (IP over 1394) IEEE802.11b (wireless LAN)		
Resolution:	Main scan: 400 dpi, 200 dpi Sub scan: 400 dpi, 200 dpi, 100 dpi To use 400 dpi, IFAX SW01 Bit 4 must be set to "1".		
Transmission Time:	1 s (through a LAN to the server) Condition: ITU-T #1 test document (Selerexe Letter) MTF correction: OFF TTI: None Resolution: 200 x 100 dpi Communication speed: 10 Mbps Correspondent device: E-mail server Line conditions: No terminal access		
Document Size:	Maximum message width is A4/LT.  Note  To use B4 and A3 width, IFAX SW00 Bit 1 (B4) and/or Bit 2 (A3) must be set to "1".		
E-mail File	Single/multi-part MIME conversion Image: TIFF-F (MH, MR, MMR)		
Format:	MIME conversion		
	MIME conversion		
Format:	MIME conversion Image: TIFF-F (MH, MR, MMR)  Transmission: SMTP, TCP/IP Reception:		

Method:	POP before SMTP A-POP
Remark:	The machine must be set up as an e-mail client before installation.  Any client PCs connected to the machine through a LAN must also be e-mail clients, or some features will not work (e.g. Autorouting).

## **IP-FAX Specifications**

Network:	Local Area Network Ethernet/10base-T, 100base-TX IEEE1394 (IP over 1394) IEEE802.11b (wireless LAN)		
Scan line density:	8 x 3.85 lines/mm, 200 x 100dpi (standard characters) 8 x 7.7lines/mm, 200 x 200dpi (detailed characters)		
Original size:	Maximum A3 or 11"x 17" (DLT)		
Maximum scanning size:	Standard: A3, 297mm x 432mm Irregular: 297mm x 1200mm		
Transmission protocol:	Recommended: T.38 Annex protocol, TCP, UDP/IP communication		
Compatible machines:	IP-Fax compatible machines		
Specify IP address and send fax to an IP-Fax compatible through a network.  function:  Also capable of sending fax from a G3 fax connected to public telephone lines via a VoIP gateway.			
Receive a fax sent from an IP-Fax compatible fax through network.  function:  Also capable of receiving fax from a G3 fax connected the telephone lines via a VoIP gateway.			

## Fax Unit Configuration



Component	Code	No.	Remarks
FCU		1	
MBU	B267	2	Included with fax unit
Speaker		3	
Handset Type 1018	B433		NA only. Common with J-C2