Notes for Users

Please note the following additional information and corrections to these manuals.

Page	Additional I	nformation
P.61 Dos and Don'ts	 If room temperature where the machine is located is higher than 30°C (86°F), do not copy in full color continuously for more than two hours. If you do, white lines may appear on copies. If you will be making full color copies for two hours or longer and the temperature of the room in which the machine is located exceeds 30°C (86°F), use the Auto Off Timer setting to specify an interval of at least one hour. This interval allows the machine to cool down, preventing white lines from appearing on copies. During the interval, do not turn off the machine's operation switch or main power switch. When in standby mode, the machine becomes noisy when: room temperature is higher than 32°C (89.6°F) room temperature is 30°C(86°F), or higher and copying has been continuous. 	
P.108	The classification of thick paper may be different depending on the brand	
Paper	of paper.	
Thickness		
Page	Error	Corrections
P.28	Power consumption of low power	Power consumption of low power
Energy Star	mode:	mode:
Program:	<u>200W</u>	<u>Type 1 : 236W</u>
Specifications		<u>Type 2 : 293.8W</u>
P.71	Copying speed (Full Color / B&W):	Copying speed (Full Color / B&W):
Specifications	Type 1: 55/ <u>50</u> copies/minute	Type 1: 55/ <u>60</u> copies/minute
for the Main Unit		
P.75	Maximum number of pages per	Maximum number of pages per
Document	document:	document:
Server	<u>2,000</u> pages	<u>3,000</u> pages

1

Page	Error	Corrections
P.80	Finisher Shift Tray:	Finisher Shift Tray:
Specifications	Paper weight:	Paper weight:
for Finisher	Without Z-fold:	Without Z-fold:
SR4020	52- <u>256</u> g/ m ^{2,} 14- <u>68</u> lb.	52- <u>300</u> g/ m ^{2,} 14- <u>80</u> lb.

Copy/Document Server Reference

Page	Error	Corrections
P.46	•Tab stock can be loaded in	•Tab stock can be loaded in Trays
Copying onto	Trays 2 and 3 or Wide Large	2 and 3 or Wide Large Capacity
Tab Stock :	Capacity Tray (Wide LCT). Set	Tray (Wide LCT). <u>When loading</u>
Important	tab stock with the side to be	<u>tab stock in Tray 2 or 3, s</u> et tab
	copied facing down.	stock with the side to be copied
		facing down. <u>When loading tab</u>
		stock in Wide Large Capacity Tray
		(Wide LCT), set tab stock with the
		side to be copied facing up.
P.247	Stack and Staple:	Stack and Staple:
Function	Blank: These modes can be	●: These modes cannot be used
Compatibility	used together.	together. The second mode
		selected will be the mode you are
		working in.
P.254	You cannot punch on thick	You cannot punch on thick paper
Supplementary	paper heavier than <u>157</u> g/ m ²	heavier than <u>164</u> g/ m² (<u>43</u> lb.).
Information:	(<u>41.7</u> lb.).	
Punch		
P.257	Finisher SR5000	Finisher SR5000
Supplementary	5 Z-folded sheets and 0 to 40	5 Z-folded sheets and 0 to 50
Information:	unfolded sheets	unfolded sheets
Z-fold		

Facsimile Reference

Page	Error	Corrections
P.190	Printing of High Compression	If memory is insufficient or there
Mail to Print:	PDF files is not possible.	are other problems, printing of
Note		High Compression PDF files
		might not be possible.
P.317	Number of pages per document	Number of pages per document
Maximum	you can store in the Document	you can store in the Document
Values	Server	Server
	Standard/Expansion memory	Standard/Expansion memory
	(optional): <u>2,000</u>	(optional): <u>3,000</u>

Printer Reference

Page	Error	Corrections
This Volume	A Sample Print file cannot be	A Sample Print file cannot be
	stored if the file contains over	stored if the file contains over
	<u>2,000 pages</u> .	<u>3,000 pages</u> .
P.79	Some types of High	• If memory is insufficient or there
Printing a PDF	Compression PDF files may	are other problems, direct printing
File Directly:	not be printed.	of High Compression PDF files
Important		created using this device's scanner
		function might not be possible.
P.83	If a group password is	If a group password is specified for
PDF Direct	assigned to DeskTopBinder	this machine, enter it here. Printing
Print	Lite and this machine, enter	is not possible if the group
Properties	the group password in this	password specified on this
17. Group	field.The group password must	machine does not match the group
password:	be entered for printing to start.	password entered here.
P.145	Option:	Option:
Specifications:	 Giga Ethernet interface 	Giga Ethernet interface
Interface	(<u>1000BASE-TX</u> / 100BASE-TX	(<u>1000BASE-T</u> / 100BASE-TX /
	/ 10BASE-T)	10BASE-T)

Scanner Reference

Page	Error	Corrections
P.141	High Compression PDF files	If memory is insufficient or there
Notes About	created by this machine cannot	are other problems, direct
and Limitations	be printed using PDF Direct Print	printing of High Compression
of File Types:	function.	PDF files created using this
High		device's scanner function might
Compression		not be possible.
PDF		
P.165	Storable number of pages per file:	Storable number of pages per file:
Values of Set	<u>2,000</u> pages	<u>3,000</u> pages
Items for File		
Storage		
P.170	When using the E-mail/Scan to	When using the E-mail/Scan to
Specifications:	Folder/Network Delivery Scanner	Folder/Network Delivery
Scan speed	function:	Scanner function:
	Black and white: 81 page/min	Black and white: 81 page/min
	(Original size: A4립, Scan Type:	(Original size: A4 ^d , Scan Type:
	Text	Text/Line Art
P.170	Compression (Gray Scale/Full	Compression (Gray Scale/Full
Specifications:	Color): Compression Level 2	Color): Compression Level
Scan speed		<u>default</u>
P.171	SMTP, POP3	<u>SMTP</u>
Specifications:		
Protocol for		
sending e-mail		

EN USA D015-7101B Printed in Japan Copyright© 2007

