

Model: Model-J P1c		Date: 2-Aug-04	No.: MG082001
Modified Article: Transfer Unit		Prepared by: H.Taguchi	
From: 1st Tech. Support Sec. Service Support Dept.			
Reason for Modification:	<input type="checkbox"/> Parts catalog correction <input type="checkbox"/> To facilitate assembly <input type="checkbox"/> Part standardization	<input type="checkbox"/> Vendor change <input checked="" type="checkbox"/> To improve reliability <input type="checkbox"/> Other	<input type="checkbox"/> To meet standards ()

The transfer unit has been modified from a transfer brush to a transfer roller system in order to further improve the accuracy of color line positioning.

Old part number	New part number	Description	Q'ty	Int	Page	Index	Note
G0773841	G0773842	Transfer Unit:Ass'y	1 - 1	X/O*	37	19	

Note*: In accordance with this change, the following firmware upgrade and SP mode setting should be done at transfer unit installation.

Firmware Upgrade, SP Settings at Transfer Unit Installation

- Model J-P1b, Model J-P1CF -

- Upgrade to the following firmware.

Model:	Code:	Engine Firmware:	System Firmware:
Model J-P1b	G060	B1.28 or newer	2.22 or newer
Model J-P1CF	G060 + G570	B1.28 or newer	1.12 or newer

- Do the following to allow the machine to detect the new unit..
 - Access SP2-399-001 [Trans_Cur_Chg] and select "1".
 - Select "OK".
 - Exit SP mode and turn the main switch Off/On.

Number:	Description:	Default Setting:	Adjustable Range:
SP2-399-001	Trans_Cur_Chg	0	0: Transfer Brush Type 1: Transfer Roller Type

Model: Model-J P1c

Date: 2-Aug-04

No.: MG082001

- Model J-P1c -

1. Upgrade to the following firmware (SP mode setting is automatically performed).

Model:	Code:	Engine Firmware:	System Firmware:
Model J-P1c	G082	C1.28 or newer	(Unnecessary)

- The firmware for models J-P1c and J-P1b are different (ex. **C1.28** vs. **B1.28**).
- If installing the new transfer unit on a J-P1c machine with Engine **B1.28 or newer** already installed, and you wish to update to a C-version firmware with the same numeric name (e.g. from **B1.28** → **C1.28**), please be sure to 1) first downgrade to B1.27 and then 2) install **C1.28 or newer**. This is because it is not possible to directly update a Bxxx version to a Cxxx version with the same numeric name.



Part Change Information List

Date: March 18, 2009

Model	Code	PCIL Number	PCIL Correction	Old part number	New part number	Description	Old Q'ty	New Q'ty	Int	3DPC	Page	Index	Set	Set Int	RTB	Note	Ref Number
Model-J P1c	G082	200903		AW010048	AW010106	PAPER FEED SENSOR	1	1	O/O		29	11					V0804408



Part Change Information List

Date: April 28, 2011

Model	Code	PCIL Nr.	PCIL Correction	Old part number	New part number	Description	Old Q'ty	New Q'ty	Int	3DPC	Page	Index	Set	Set Int	RTB	Note	Ref. Nr.	ECN Nr.
J P1c	G082	201104		G0604457	B1804457	BRACKET:EXIT ROLLER:FLOPPY DISK	1	1	O/O		65	2					V1100577	
J P1c	G082	201104		G0602834	B1802834	POSITIONING PLATE:LOWER:ASS'Y	1	1	O/O		101	12					V1100577	