


### **Quick Reference Fax Guide**


## ⇒Please put this guide above your machine <=

### How to send a fax... (1. Transmission)

- Specify a transmission mode:
- Memory Transmission, or
- Immediate Transmission (selected by pressing [Immed. TX])
- 2 Place the original.
- Exposure glass (face down)



 Auto Document Feeder (face up)



- Make the scan settings you require.
- Specify a destination.
- Depress the [Start] key.

If you choose Memory Transmission, you can send to more destinations at once. To do this, after

- [Add] and specify destinations - the [Start] key
- To send an Internet Fax, press [Internet Fax] to switch the transmission type to Internet Fax.



## How to fax to Document Server... (5. Storing a

- 1 Press [Store File].
- 2 Select [Send & Store].
- **B** Set the user name, file name, and password as necessary, and then press [OK].
- Specify a destination, and then press the [Start] key.

#### To send a fax from Document Server:

- Press [Select Stored File].
- 2 Select the documents to be sent, and then press [OK].
- B Specify a destination, and then press the [Start] key.

- 1. Confidential File indicator
- 2. Communicating indicator
- 3. Receiving File indicator
- 4. [User Tools/Counter] key
- 5. Display panel

Standard available:

Document Server: 1

Copier: 🗖

Printer: 凸

Facsimile: (

6. [Clear Modes] key

User Tool :/Counter

**®**/**3** 

Сору

Printer

∠ Scanner

**€** Facsimile

Other Function

Communicating

P

Document Server

- Press to clear the current settings. 7. [Program] key
- Press to select the program mode.
- 8. Main power indicator
- 9. Operation switch
- 10. [Simplified Display] key 11. [Start] key

 Reg. No.
 Edit Dest.
 Recent.
 Select Line
 Adv. February
 Tone
 Pause
 On Hook
 Immed. To

 Frequent
 AB
 CD
 EF
 GH
 LJK
 LMN
 CP0
 RST
 UW
 XYZ
 Owner Title

TX File Status RX File Status Sender Name TX Mode

Registers entered numbers or settings.

ore File Change TX / Info Check Modes

- 12. [#] key (enter key)
- Press to switch to the facsimile mode.
- 16. Error indicator
  - 17. Function keys

14. Number keys

13. [Clear/Stop] key

15. [Facsimile] key

Clear dodes Program Interrupt

(C/O)

14 13 12

Start

### Memory

8 9

Simplified

10

While the original is being transmitted:

1 Press the [Clear/Stop] key.

Memory + Immediate

2 Select the file you want to cancel.

Press the [Clear Modes] key.

1 Press the [Clear/Stop] key.

Press [Stop Transmission], and then press [OK].

How to cancel a transmission... (1. Transmission)

Before the original is scanned = before pressing the [Start] key:

While the original is being scanned = after pressing the [Start] key:

4 Press [Exit].

Before the transmission is started:

- 1 Press [Change TX / Info].
- Press [Check / Stop Transmission File].
- **B** Select the file you want to cancel.
- Press [Stop Transmission], and then press [OK].
- D Press [Exit] twice.

# 

16 15 This button needs to be

(General Settings Guide 7. Registering Addresses

and Users for Facsimile

selected as first step

## You can also print and scan on this machine! Please ask your sales person for these options.

How to program a Destination key...

Press the [User Tools/Counter] key.

Press [Address Book Management].

Press the [User Tools/Counter] key.

updated...'. Press [Exit].

5 Check that [Program / Change] is selected.

Press [Change] and set user's information, press [OK].

Press [Change] and enter the fax number using the number keys, press [OK] under Fax Destination.

1 You will get a message 'Destination list / machine settings are

2 Press [System Settings].

**6** Press [New Program].

Press [Fax Dest.].

Press [OK].

Press [Exit].

Press [Administrator Tools].

*17* 

Transmission Using this function, you can instruct the machine to send the

can take advantage of off-peak telephone charges, without being at the machine.

- 1 Place the original, and then select the scan settings you require.
- Press [TX Mode].
- number keys, and then press [OK].



- **G** Specify a destination, and then press the [Start] key.

## How to send at a specific time (Send Later)

fax at a later time via Memory Transmission. Advantage: you

- Press [Send Later].
- Enter the time (24 hour format) using the
- Press [OK].

## How to print the Journal...

(4. Changing/Confirming

The Journal is printed automatically after every 50 communications. You can also request a Journal at any time, by following below procedure.

Press [Change TX / Info].



- 2 Select [Print Journal].
- **B** Select the printing method:
- [Print per File No.]
  - [Print per User]
- Press the [Start] key.
- Press [Exit] twice

# Print per File No.

### **Advanced Features Fax**

Please see the <Facsimile Reference> Operating Instructions:

- SUB/SEP Codes (1. Transmission) Privacy can be protected when faxing with a SUB/SEP Code, since only people who know the SUB/SEP Code can receive or print the fax document.
- Printed reports (4. Changing/Confirming Communication Information) Inform you if a fax has been saved, sent, or failed to be transmitted.
- LAN-Fax features Sending a fax from a computer (6. Fax via Computer)

