## Quick Reference Fax Guide

# ⇒Please put this guide above your machine <=

- 1. Indicators
- 2. [User Tools/Counter] key
- 3. Display Panel
- 4. [Check Modes] key

Press before pressing the [Start] key to check the settings selected for the fax about to send.

5. [Program] key

Press to select the program mode.

- 6. [Clear Modes] key
- Press to cancel the current settings.
- 7. On indicator
- 8. Main power indicator
- 9. Operation switch
- 10. Data In indicator
- 11. Confidential file indicator
- 12. Receive File indicator
- 13. Communicating indicator
- 14. Function status indicators 15. [Facsimile] key

Press to switch facsimile mode. 16. [Start Manual RX] key

Press when reception mode is set to

Manual Reception. 17. [On Hook Dial] key

Press when manual facsimile reception is set to Manual Reception.

18. [Tone] kev

Press to send tonal signals down a pulse dialing line.

- 19. [Pause/Redial] key
- 20. Number keys
- 21. [#] key (Enter kev)

Registers entered numbers or settings.

- 22. [Clear/Stop] key
- 23. Start key



- · Memory Transmission, or
- Immediate Transmission
- Placing Originals
- Exposure Glass (Face down)




Document Feeder (Face up)



- B Make required settings
- 4 Dial a destination
- D Press the [Start] key

If you choose Memory Transmission, you can send to more destinations at once. To do this, after step 4, press:

- [Add] and specify destinations
- the [Start] key



You can also print and scan on this machine! Please ask your sales person for these options.



## How to fax to Document Server... 7. Simplifying

- 1 Press [Store File].
- 2 Choose [Store & Transmit].
- Make your settings via [File Info. Setting].
- Press [OK].

Copyright © 2005

**5** Select desired destinations and press the [Start] key.

#### To send a fax from Document Server:

- Press [Sub TX Mode].
- 2 Press [Select Stored File].
- **B** Select the document you want to send, and then press [OK] twice.
- Select the destinations you want to send to, and then press the [Start] key.

## How to registering a Quick Dial... 5. Registering Addresses and Users Press the [User Tools/Counter] key.

- Press [System Settings].
- Press [Administrator Tools] and then press [Next].
- Press [Address Book Management].
- D Press [New Program].
- Press [Change] and set user's information, press [OK].
- Press [Fax Dest.] and enter fax number with number keys. Press [OK] twice.
- Press [Exit] three times.
- 9 You will get a message 'Destination list is updated..'.

## How to send at a specific time (Send later) 1. Transmission Mode)


Using this function, you can instruct the machine to send the fax at a later time via Memory Transmission. Advantage: you can take advantage of off-peak telephone charges, without being at the

Place the original, and then select the required settings.

2 Press [Transmission Mode].



- B Select [Send Later].
- Enter the time using the number keys (24 hr format), and then press [OK].
- Press [OK].
- d Dial and press the [Start] key.



#### How to cancel a Transmission...

Memory + immediate

Before original is scanned = before pressing [Start] key:

Press [Clear Modes] key.

While original is being scanned = after pressing [Start] key:

Press [Clear/Stop] key.

#### Memory

While original is being transmitted:

- Press [Clear/Stop] kev.
- 2 Select the file you want to cancel.
- Press [Stop Transmission].
- 4 Press [Exit].

Before the transmission is started:

- Press [Change/Stop TX File].
- 2 Select file to be cancelled.
- Press [Stop Transmission]. Press [Exit].

### How to print the journal...

The journal is printed automatically after every 50 communications. You can also request a journal at any time, by following below procedure.

Press [Information].



- Select [Print Journal].
- B Select a printing mode:
- [Print per File No.] - [Print per User]
- Press [Start] key.
- Press [Exit] twice.



#### **Advanced Features Fax**

Please see the <Fax Advanced Features> Operating Instructions:

- Confidential transmission (1. Transmission Mode) Message is stored in memory at the other end and not printed until an ID is insterted
- Printed Reports (4. Other Transmission Features) To inform you if fax has been saved, send or failed to be
- Lan fax features Sending a fax from pc (6. Fax via Computer)

