To use a new color of Special Toner for Pro C7110S/C7110/C7100S, configure the setting as follows:

■Procedure for configuring the setting

- 1. Launch Command Workstation.
- 2. Open [Device Center], and then click the [Resources] tab.
- 3. Select [Specialty Colors], and then click [New] to add a new special color to the [Clear] group.
- 4. In [New Special Color], enter "Special" in the name column, and then click the [OK] button.

Job Center Device Center		
🚊 General 🛛 🌍 Color Setup	🛞 Resources 🛛 🔊 Workflows 🛛 🧍 Logs	
Paper Catalog VDP Resource	s Profiles Spot Colors Specialty Colors Fonts	
🕂 New 📝 Edit 🕋 Delete		
Group Name	Clear	
🔬 Clear	Last Updated:11/8/2016 11:34:17 AM Number of colors: 2	
	Copyright (c) 2014 Electronics for Imaging, Inc.	
	Name	
	Clear	
	Special	

*If "Special" has already been specified, adding it is not needed.

Other notices to users

When displayed on the screen, some terms used for the control panel of the main unit, Command Workstation, and the printer driver are not consistent. Read them as specified on the back of this page.

Where displayed	How displayed on the screen
Control panel of the main unit Displayed as "Special".	Supplies Info Maintenance Info K: Black Image: Comparison of the second
Command Workstation Read "Clear Toner" displayed as "Special"	Consumables Toner Levels Black: 100% Yellow: 30% Magenta: 30% Cyan: 70% Clear toner: 60%
 Command Workstation Job Properties EFI printer driver Read "Clear Toner" displayed as "Special". 	Image Image Image <thimage< th=""> <thimage< th=""></thimage<></thimage<>